

## Adderlist

i test 1 skrives 1 i pos 19 og 39  
i alle celler (LI)

i test 2 udskrives først R reg. og  
med hvert gennemløb adderes nu  
et i henholdsvis pos 19 og 39.

Ved hvert stop (manuelt) skal de  
to halvdele af R være ens (indtil  
overløb fra sidste halvdel når første  
halvdel)

OVERSIGT OVER BESKREVNE TESTPROGRAMMER.

- B1: (Topsøe's tromletest). Tester med tilfældige tal kanal 1-319. Mærkebits testes ikke.
- B2: Trykning af et smukt bitmønster. Udgaar i nærmeste fremtid.
- B3: Trykning af Kanal 0 som bitmønster. Udgaar i nærmeste fremtid.
- B4: Ferritlagertest med manuelt indsat bitmønster. Celle 60-1022 testes, men ikke mærkebits.
- B5: Test af kanal 0. Kanal 0 sammenlignes med en korrekt version, der indlæses som en del af programmet.
- B6: Ferritlagertest, der ogsaa tester mærkebits. Der forsøges skrivning af ettere og nuller i cellerne 50-1023 og 0-40.
- B7: (Topsøe's flydende test). Test af operationerne arf, srf, mkf og dkf.
- B8: Undersøgelse af tromletransporttiden. Udgaar snarest.
- B9: Skrivemaskinetest. Et indtastet tegn gentages ni gange. Tester ogsaa caseskift.
- B10: Ferritlagertest med mærkebits. Bruger enten automatisk genererede bitmønstre eller manuelt indsatte. Tester celle 512-1023.
- B11: Som test B10, men test af celle 0-511.
- B12: Indikatorertest. Tester indikatoroperationerne og saa vidt vides alle indikatorbetingelserne.
- B13: (Magnus tromletest). Tester tromlen med tilfældige tal og kan foretage simultanregning. Mærkebits testes.
- B14: Test af læser. Tester læsning af samtlige gyldige hulkombinationer.
- B15: Test af hulning og læsning af 5-kanals tape i TELEX kode.

- B17: Printertest. Trykker samtlige tegn i alle kolonner.
- B18: Disktest. Test af diskfile som tromle. Tester et defineret omraade af disken med adressen paa det paagældende ord.
- B25: Disktest. Test af diskfile som tromle. Tester hele disken med enten manuelt indsat information eller med spornummer som information.
- A200: Program til hulning af strimler til indlæsning med kanal 0.
- A201: Perforatortest. Huller en strimmel, der testes ved umiddelbar læsning.
- A203: (Buffertest 2). Tester bufferen med tilfældige tal. Tester ogsaa mærkebits.
- A204: (Buffertest 3). Tester bufferen efter samme principper som B10 og B11.
- A205: Sorteringstest. Tester sortering paa 3 baandstationer.
- A206: Program til hulning af strimmel til B14.
- A208: Bundgaards rutinetest af GIER.
- A209: Test af adressering paa diskfile tilsluttet bufferen.
- A210: Test af diskfile tilsluttet buffer. Der testes med manuelt indsat information.
- A211: Hurtig sumcheck af diskfile tilsluttet buffer.
- A212: Test af læsning fra diskfile tilsluttet som tromle. Læser med størst mulig bevægelse af armene.
- A213: Test af hovedvalg paa diskfile tilsluttet buffer.
- A215: Test af diskfile paa buffer. Test af simultanregning. Valg af spor i tilfældig orden ved læsning. Hele statusordet undersøges.

```

93 8.8.69 849
slip<
vk0
lk100
sy1
zq
e10
1

```

KANAL 0 i HJÆLP 3

```

94 8.8.69 e14
print, p100..139<

```

|                  |               |
|------------------|---------------|
| 100. qq          | .hh 23        |
| 101. it 960      | .pt 1         |
| 102. qq          | .gk 2         |
| 103. vy 529      | .hv 6         |
| 104. ann s64     | V MK t479     |
| 105. ml (p64)    | VD LPB t921   |
| 106. gi 3        | IPC           |
| 107. gm 6        | MPC           |
| 108. gs 7        | IOB           |
| 109. gr 8        | MOB           |
| 110. ga 9        | .tl -39       |
| 111. pm s        | IRB           |
| 112. gr 11       | .hr r1 [413]  |
| 113. gp 12       | .arn 4        |
| 114. sr -1       | .tk 21        |
| 115. hv 29       | NZ            |
| 116. hv 33       | NA            |
| 117. arn 5       | .pm -1        |
| 118. ga 19       | .tk 10        |
| 119. sy -1       | .ck -4        |
| 120. nc          | .hv 18        |
| 121. lyn -1      | .gm -1        |
| 122. bs 1        | .hv 27        |
| 123. gs 10       | .vyn 528      |
| 124. tl -6       | .ca           |
| 125. ly r4 [429] | .hs r-1 [424] |
| 126. gm s3       | M t-1         |
| 127. ca          | .hv 33        |
| 128. nc 17       | .hv 17        |
| 129. vk 960      | .it 1         |
| 130. vk 294      | .it 40        |
| 131. sk          | .it -1        |
| 132. nc 24       | .hh 29        |
| 133. vkf 960     | .vkf 1        |
| 134. lk 40       | .vkn 38       |
| 135. ar 37       | .pa 22        |
| 136. ar 2        | D LA          |
| 137. hv (35)     | D NB t1       |
| 138. hv (17)     | D NZ t-1      |
| 139. arn 1       | IQC           |

start primitiv  
iaseprogram →

|    |    |
|----|----|
| 61 | 51 |
| 18 | 25 |
| 59 | 50 |

Indlæsning af "C" TESTS indsat celle 23-24-25

BY = 0

Start celle 23

Udskrift af kanal 0 i HJÆLP-systemet.

|        |      |      |           |       |  |  |
|--------|------|------|-----------|-------|--|--|
| [ 0 ]  | qd   |      |           |       |  |  |
| [ 1 ]  | it   | 1    | ,pa       | 10    | gem h-bit                              |  |
| [ 2 ]  | gk   | 1    | ,vy       | r-497 | bit 20-39 er konstant for spærreord    |  |
|        |      |      |           |       | gem tk og by, spær hp-knap             |  |
|        |      |      |           |       | vælg skrivemaskine in/output           |  |
| [ 3 ]  | gi   | 2    | IPC       |       | gem in, indicer A og B                 |  |
| [ 4 ]  | gm   | 3    | MPC       |       | gem M, A og B                          |  |
| [ 5 ]  | vk   | 32   | IOB t-1   |       | vk er irrelevant, indicer overløb      |  |
| [ 6 ]  | gr   | 4    | MOB       |       | gem R og R[00]                         |  |
| [ 7 ]  | tl   | -39  | ,pm       | 24    | 2R[00]+R[0]->R[39],M[0-19]:=-1         |  |
| [ 8 ]  | gr   | 7    | ,tln      | -19   | gem R[00],R[0],2*(-19)-2*(-39)->M      |  |
| [ 9 ]  | arn  | 2    | ,cm       | -1    | r:=spærreord, sammenlign operationsdel |  |
|        |      |      |           |       | i celle -1 med spærreord               |  |
| [ 10 ] | pmfn | r    | IRB       |       | R:=0, RE=h, M irrelevant               |  |
| [ 11 ] | pi   | 66   | IZA t-511 |       | in=-,sp,0,0,1,0,0,0,0,1,h              |  |
| [ 12 ] | hh   | 17   | NZA       |       | hop hvis hp-knap spærret               |  |
| [ 13 ] | gp   | 8    | ,pp       | 38    | gem p, p:=38                           |  |
| [ 14 ] | vk   | 319  |           | t-1   | )                                      |  |
| [ 15 ] | sk   | -24  |           | t-40  | ) gem celle 40-959 paa kanal 295-318   |  |
| [ 16 ] | bt   | 23   |           | t-1   | )                                      |  |
| [ 17 ] | hv   | 14   | ,pp       | 294   | hvis hp-knap spærret then p:=294       |  |
| [ 18 ] | gs   | 6    | ,gin      | 9     | gem s, gem in, R:=0                    |  |
| [ 19 ] | vk   | 25   | ,lk       | -64   | læs kanal 25                           |  |
| [ 20 ] | vk   | p    | ,lk       | -73   | læs kanal med oprindeligt indhold      |  |
|        |      |      |           |       | af celle 0-39                          |  |
| [ 21 ] | vk   | (5)  | ,lk       | -124  | )                                      |  |
| [ 22 ] | ps   | 41   | ,ud       | 5     | )                                      |  |
| [ 23 ] | ps   | s-1  | ,ar       | s-125 | ) summer kanal 0-31                    |  |
| [ 24 ] | bs   | s-1  | ,hv       | r-1   | )                                      |  |
| [ 25 ] | bs   | (5)  | IOB t-1   |       | )                                      |  |
| [ 26 ] | pp   | ( )  | ,hv       | 21    | ) p = indhopsadresse                   |  |
| [ 27 ] | sy   | 64   | V NZ      |       | vr hvis FEJL                           |  |
| [ 28 ] | arn  | -25  | ,hv       | -29   | hent en konstant, hop til HJÆLP        |  |
| [ 29 ] | sy   | 29   | ,sy       | 60    | )                                      |  |
| [ 30 ] | sy   | 54   | ,sy       | 53    | ) skriv: FEJL                          |  |
| [ 31 ] | sy   | 33   | ,sy       | 35    | )                                      |  |
| [ 32 ] | gr   | -512 | MOB       |       | gem sum i 512, overløb i B             |  |
| [ 33 ] | ly   | 33   | ,vy       | -496  | vent, vælg strimmel input              |  |
| [ 34 ] | pmn  | 64   | XD IZA    |       | )                                      |  |
| [ 35 ] | tl   | -7   | ,ly       | r1    | )                                      |  |
| [ 36 ] | pi   |      | LZA t508  |       | ) primitivt indlæseprogram             |  |
| [ 37 ] | xr   |      | X IZB     |       | )                                      |  |
| [ 38 ] | hv   | 35   | LZB       |       | )                                      |  |
| [ 39 ] | gr   | 41   | MRC t-1   |       | )                                      |  |

Ovenstaaende gælder for standard-GIER med hp-knap spærret med by0=1.

For hp-knap spærret med by3=1:

|        |    |    |     |     |
|--------|----|----|-----|-----|
| [ 2 ]  | gk | 1  | ,vy | r79 |
| [ 33 ] | ly | 33 | ,vy | 80  |

[Testprogram no. 1. Topsøes test of the drum.

The program writes pseudo- random numbers on the tracks 1-319( the same number on all tracks) and compares the number that has been read with the written number. After each comparison for all the tracks is typed ok on the typewriter. By errors is typed track number, word number, the written word and the word that has been read. Bit 40 and 41 do not contain random numbers. KA=1 effects simultaneous computation by writing, KB=1 effects simultaneous computation by reading. Output on the typewriter can be removed by setting by=0 after the testprogram is read in. First instruction to be executed is zqLKB. The drum parity check should be removed during run by the switch in GIER.]

i=41

|                        |   |
|------------------------|---|
| [ 41] zqLKB            | ;stop if KB=1                               |
| [ 42] vy 16            | ;choice of typewriter                       |
| [ 43] pa r8 t0         | ;choice of start track                      |
| [ 44] pa r3 t-305      | ;choice of start address for random numbers |
| [ 45] hs r31           | ;jump to sequ. for random numbers           |
| [ 46] tk 1 ,it 1       | ;shift                                      |
| [ 47] gr -305,hs r29   | ;store random numbers from 720 and jump     |
| [ 48] tk -30,ac (r-1)  | ;shift and add                              |
| [ 49] it(r-2),bs -265  | ;is repeated 40-                            |
| [ 50] hh r-5           | ;times                                      |
| [ 51] vk 0 t1          | ;choice of track                            |
| [ 52] sk -304          | ;write track                                |
| [ 53] hv r5 NKA        | ;jump if KA=0                               |
| [ 54] pa r2 t50        | ;put in 50 as counting number               |
| [ 55] hs r21 t29       | ;compute 50-                                |
| [ 56] bt 50 t-1        | ;random numbers simultaneously-             |
| [ 57] hv r-2           | ;with writing                               |
| [ 58] vk(r-7),lk -504  | ;choose track and read until 520            |
| [ 59] hv r5 NKB        | ;jump if KB=0                               |
| [ 60] pa r2 t50        | ;place 50                                   |
| [ 61] hs r15           | ;compute 50-                                |
| [ 62] bt 50 t-1        | ;random numbers simultaneously-             |
| [ 63] hv r-2           | ;with reading                               |
| [ 64] pa r3 t-305      | ;choice of start address for random numbers |
| [ 65] pa r3 t-505      | ;choice of start address for read numbers   |
| [ 66] vk (r-15)        | ;wait for the drum                          |
| [ 67] arn -305 t1      | ;take the written                           |
| [ 68] sr -505 t1       | ;subtract the read                          |
| [ 69] gr r15,arn r15   | ;store the difference and fetch it again    |
| [ 70] hv r15 NZ        | ;jump to typeout if not zero                |
| [ 71] it (r-3),bs -465 | ;this is repeated-                          |
| [ 72] hv r-5           | ;40 times                                   |
| [ 73] it (r-22),bs 319 | ;if track number < 319                      |
| [ 74] hv r-23          | ;jump back                                  |
| [ 75] hv r42           | ;else jump to typeout of ok                 |
| [ 76] pm r7,mln r5     | ;RAND-1, subroutine for random numbers      |
| [ 77] tk 8,gm r6       |   |
| [ 78] ar r5            |   |
| [ 79] sr r5 L0         |   |
| [ 80] gr r3,hr s1      | ;jump back                                  |
| [ 81] gtn p,dln r434   | ;constant                                   |
| [ 82] udn (p511),gc -1 | ;constant                                   |
| [ 83] sn p206 X t-228  | ;constant                                   |
| [ 84] qq               |   |
| [ 85] sy 64,ud r39     | ;type CR and count down in 120              |

```

[ 86] arn(r-35) D           ;fetch track number
[ 87] hs r17                ;jump to decimal typeout
[ 88] qq
[ 89] arn(r-21) D           ;fetch word number relatively

[ 90] sr -504 D             ;find word number
[ 91] hs r13                ;jump to decimal typeout
[ 92] qq
[ 93] sy 64                 ;type CR
[ 94] arn(r-27),tk 1        ;fetch the written word and-
[ 95] sy 1 V LT            ;write-
[ 96] sy                    ;it-
[ 97] hh r-3 NZ             ;until the rest is only o-es
[ 98] sy 64                 ;write CR
[ 99] arn(r-31),tk 1        ;fetch the read word and-
[100] sy 1V LT             ;write it-
[101] sy                    ;until the rest is only o-es
[102] hh r-3 NZ             ;
[103] hvr-32                ;jump to repeat
[104] ck 10,tk 30           ;decimal typeout
[105] ck -10,pt r9
[106] dk r9 X
[107] pp 4,mln r9
[108] pp p-1,tk 20
[109] ar r5 V LZ
[110] pt r4 t16
[111] gt r , sy
[112] bs p510,ud r-2
[113] bs p , hh r-6
[114] hr s1,qq 16          ;jump back
[115] qq9 t-241
[116] qq IZA
[117] sy 38 ,sy 34          ;type ok
[118] sy ,sy               ;type two spaces
[119] sy ,sy               ;type two spaces
[120] bt 12 t-1            ;up until 12 times
[121] hv 43                ;jump to repeat
[122] pa r-2 t12           ;else place 12 as counting number
[123] sy 64 ,hv 43         ;write CR and jump to repeat
[124] pa r-4 t-1           ;count down to second to the last

```

e41

[Testprogram no. 2, typeout of bit-configuration or bit-pattern. Set the TYPEWRITER to the shortest distance between the lines.]

Program is stored from location 41 to 89. The first instruction to be executed is zq LKB. The program will stop after 20 lines have been typed if KB=1. The typeout will be repeated by pressing START-button.]

```

i=41
[ 41] zq LKB ;stop if KB=1
[ 42] vy16 ,hs 50 ;choice of typewriter and jump
[ 43] qq 70 t1 ;constant and counter
[ 44] bt 19 t-1 ;is performed-
[ 45] hh r-3 ;20 times
[ 46] zq LKB ;stop if KB=1
[ 47] pa r-3 t19 ;set number of words
[ 48] pa r-5 t70 ;set start address
[ 49] hh r-7 ;go to repeat
[ 50] arn(s1) IPC ;typeoutprogram.Fetch a word
[ 51] sy 64 , sy 60 ;type CR and upper case
[ 52] sy 6, tk 1 ;type [ and shift
[ 53] sy 57 V LT ;type I if sign is-
[ 54] sy ;else type space
[ 55] bt 39 t-1 ;is performed
[ 56] hh r-4 ;40 times
[ 57] pa r-2 t39 ;set number of bits
[ 58] sy 57 V LPA ;type I if A-mark
[ 59] sy ;else type space
[ 60] sy 57 V LPB ;type I if B-mark
[ 61] sy ;else type space
[ 62] sy 7,hr s1 ;type ] and jump back
[ 63] qq ;empty
[ 64] qq
[ 65] qq
[ 66] qq
[ 67] qq
[ 68] qq
[ 69] qq
[ 70] qq s1 IB t1 ;1 word in bitpattern
[ 71] qq p3 IC t3
[ 72] qq (p7) IKC t7
[ 73] qqn (p15) IOC t15
[ 74] zqn (p31) IRC t31
[ 75] srn (p63) MRC t63
[ 76] scn (p127) LRC t127
[ 77] nkn (p255) D LRC t255
[ 78] ppn (p511) VD LRC t511
[ 79] udn (p-1) XVD LRC t-1
[ 80] udn (p-1) XVD LRC t-1
[ 81] udn (r-2) XVD LRA t-2
[ 82] udn (-4) XVD LR t-4
[ 83] udn -8 XVD LQ t-8
[ 84] ud -16 XVD LT t-16
[ 85] zl -32 XVD L t-32
[ 86] hh -64 XVD N t-64
[ 87] hv -128 XVD t-128
[ 88] pc -256 XV t-256
[ 89] pa -512 X t-512 ;last word in bitpattern

```

e41



[Testprogram no. 3. Typeout of track no. 0 in bit-pattern. Set the TYPEWRITER to double distance between the lines.

The testprogram is stored in locations 41 to 63, it uses the locations 64 to 103 for storing. The first instruction to be performed is zq LKB. The run can be repeated by pressing the START-button.]

```

i=41
[ 41] zq LKB                ;stop if KKB=1
[ 42] vk 0,lk 64            ;choose and read track no. 0
[ 43] vy 16,vk 0            ;choose typewriter and wait for the drum
[ 44] sy 62,hs 51           ;black ribbon and jump to typeoutprogram
[ 45] qq 64 t1              ;constant and counter
[ 46] bt 39 t-1             ;is performed-
[ 47] hh r-3                ;40 times
[ 48] pa r-3 t64            ;set start address
[ 49] pa r-3 t39            ;set number of words
[ 50] zq 0,hv r-7           ;stop and go to restart
[ 51] arn (s1) IPC          ;typeoutprogram.Fetch a word
[ 52] sy 64,sy 60           ;type CR and upper case
[ 53] sy 6,tk 1             ;type [ and shift
[ 54] sy 57 V LT           ;type I if sign is-
[ 55] sy 4                  ;else type =
[ 56] bt 39 t-1             ;is performed-
[ 57] hh r-4                ;40 times
[ 58] pa r-2 t39            ;set number of bits
[ 59] sy 57 V LPA           ;type I if A-mark
[ 60] sy 4                  ;else type =
[ 61] sy 57 V LPB           ;type I if B-mark
[ 62] sy 4                  ;else type =
[ 63] sy 7 ,hr s1          ;type ] and jump back
[ 64] qq                    ;empty
e41

```

[Testprogram no. 4. Test of the fast memory or core-store. The content of M is stored in a location and is read back. If the read is equal to the written, the program will continue with the next location. The test is performed for the locations 60 - 1022. If KB=1 the program will stop and a new content can be placed in M. Position 40 and 41 in a location are not included in the test. By errors <f> is typed on the typewriter every time a content of a location is not hit right. If KA=1 GIER will stop while the number of the location that was hit wrong is placed in the in-register, and the difference between the read and the written is placed in the R-register. By restart or if KA=0 the program will go on testing the next location. The first instruction is zq LKB.]

i=41

|                   |  |
|-------------------|--|
| [41] zq 0 LKB     | ;stop if KB=1                            |
| [42] gm 43 V      | ;store M in location no. 43              |
| [43] qq 0         | ;empty                                   |
| [44] gm 59 M t1   | ;store M in running location             |
| [45] arn 43       | ;add content of location no. 43          |
| [46] sr (44)      | ;subtract running location               |
| [47] hv 52 NZ     | ;jump if R $\neq$ 0                      |
| [48] arn 44       | ;add content of location no. 44          |
| [49] ca 1022      | ;if number of running location is 1022   |
| [50] pa 44 t59    | ;set 59 as address in location no. 44    |
| [51] hv 41        | ;go to restart                           |
| [52] vy 16, sy 54 | ;choose typewriter and type f            |
| [53] pi (44)      | ;place no. of location in in-register    |
| [54] zq 0 LKA     | ;stop if KA=1                            |
| [55] bt 40 t-1    | ;until 40 times                          |
| [56] hv 48        | ;jump                                    |
| [57] pa 55 t40    | ;else place 40 as address in location 55 |
| [58] sy 64, hv 48 | ;type CR and jump                        |
| [59] qq 0         | ;empty                                   |

e41

[Testprogram no. 5. Test of track no. 0.

The program reads drum track no. 0 to the locations 128-167 in the core store and compares for each location with the correct content of track no. 0, that is read in to the locations 70-109 after the program. If there is no error in track no. 0 the message ok will be typed. If there is an error in one or more locations, the program will stop after having typed -i- for errors in positions 0-39 and -m- for errors in the mark-positions. The content of the wrong location can be observed in the R-register and the address of the wrong location in the s-register (read modulo 128). In the M-register is -by errors in pos. 0-39 - placed the difference from the subtraction and - by errors in the mark-bits - the correct mark-bits in position 8 and 9.]

i=41

|                       |   |
|-----------------------|---|
| [41] zq LKB           |   |
| [42] vy 16, sy 58     | ;the typewriter in lower case                   |
| [43] zq LKB           |   |
| [44] vk 0, lk 128     | ;read track 0 to loc. 128 and on                |
| [45] vk ,pi           | ;wait for the drum                              |
| [46] arn 69 IRC +1    | ;correct run cellcontent to R (markbits indic.) |
| [47] sr 127 +1        | ;subtract next variable location                |
| [48] gi 66, pp        | ;correct marks to location no. 66               |
| [49] hv 60 NZ         | ;jump if R $\neq$ 0                             |
| [50] arn (47) IRC     | ;read marks indic.                              |
| [51] arn 66 IK        | ;correct marks to R, read marks to p            |
| [52] ncp, hv 63       | ;jump if wrong marks                            |
| [53] arn 47,nc 167    | ;typeout if 40 locations are tested             |
| [54] hh 45            | ;or jump back                                   |
| [55] sy 64            | ;type CR  |
| [56] sy 38, sy 34     | ;type ok  |
| [57] pa 46 +69        | ;replace address number                         |
| [58] pa 47 +127       | ;replace address number                         |
| [59] hv 43            |   |
| [60] sy 57 X          | ;type -i-, difference to M                      |
| [61] arn (47), ps(47) | ;wrong cellcontent to R, address to s           |
| [62] zq ,hv 50        |   |
| [63] sy 36 X          | ;type -m-, correct marks to M pos. 8 and 9      |
| [64] arn(47), ps(47)  | ;wrong cellcontent to R, address to s           |
| [65] zq, hv 53        |   |
| [66] qq               | ;location used for storing during run           |

[From location 70 to 109 is now placed the correct content of track no. 0. In this version it is assumed, that the HP-button is blocked by position 0 in the by-register. For a GIER, where the HP-button is blocked by pos. 3 in the by-register, the program can be used, if you before the run change the right half-word instructions in loc. 72 and 103 to vy r79 and vy 80 ]

i=70  
 [70] qq  
 [71] it 1, pa 10  
 [72] gk 1, vy r-497  
 [73] gi 2 IPC  
 [74] gm 3 MPC  
 [75] vk 32 IOB t-1  
 [76] gr 4 MOB  
 [77] tl -39, pm 24  
 [78] gr 7, tln -19  
 [79] arn 2, cm -1  
 [80] pmfn r IRB  
 [81] pi 66 IZA t-511  
 [82] hh 17 NZA  
 [83] gp 8, pp 38  
 [84] vk 319 t-1  
 [85] sk -24 t-40  
 [86] bt 23 t-1  
 [87] hv 14, pp 294  
 [88] gs 6, gin 9  
 [89] vk 25, lk -64  
 [90] vk p, lk -73  
 [91] vk(5), lk -124  
 [92] ps 41, ud 5  
 [93] ps s-1, ar s-125  
 [94] bs s-1, hv r-1  
 [95] bs (5) IOB t-1  
 [96] pp (), hv 21  
 [97] sy 64 V NZ  
 [98] arn -25, hv -29  
 [99] sy 29, sy 60  
 [100] sy 54, sy 53  
 [101] sy 33, sy 35  
 [102] gr -512 MOB  
 [103] ly 33, vy -496  
 [104] pmn 64 XD IZA  
 [105] tl -7, ly r1  
 [106] pi LZA t508  
 [107] xr X IZB  
 [108] hv 35 LZB  
 [109] gr 41 MRC t-1  
 e41

;gk 1,vy r79 for HP blocked by pos. 3 in by-reg.

;ly 33,vy 80 for HP blocked by pos. 3 in by-reg.

[Testprogram no. 6. Test of the core-store including marks.

The program examines the whole core-store except for the locations that are occupied by the program itself.

At first zeroes are send to a location and the answer is checked, then ones are send to the same location and the answer is checked.

If stop in location 44 (r1=45): R0-39  $\neq$  0, existing ones are wrong.

If stop in location 46 (r2=47): R40-41  $\neq$  0, existing ones are wrong.

If stop in location 50 (r1=51): R0-39  $\neq$  0, to position(s) containing a one and having a zero on the right side a zero has been send from the store instead of a one.

If stop in location 52 (r1=53): R=40.41  $\neq$  1.1 , existing zeroes are wrong.

With LKB=1 the program will stop after having examined the core store from location 58 to 1023 and further on from location 0 to 40. In the indicator, the address of the location that is tested, can be observed.]

i=41

|                       |  |
|-----------------------|--|
| [41] zq LKB           |  |
| [42] grn 57 M +1      | ;zero to variable location                   |
| [43] arn(42) ,pi (42) |  |
| [44] zq NZ            | ;stop if R0-39 $\neq$ 0                      |
| [45] qq V NC          |  |
| [46] zq               | ;stop if R40.41 $\neq$ 0.0                   |
| [47] srn 57           | ;constant is subtracted                      |
| [48] gr (42) MC       | ;ones to variable location                   |
| [49] arn 57 , ar (42) | ;constant to R, content of location is added |
| [50] zq NZ            | ;stop if R0-39 $\neq$ 0                      |
| [51] qq V LC          |  |
| [52] zq               | ;stop if R40.41 $\neq$ 1.1                   |
| [53] arn 42 ,nc 40    |  |
| [54] hv 42            | ;examine the next (variable) location        |
| [55] pa 42 +57        | ;replace the address 57 in location 42       |
| [56] hv 41            | ;restart with location no. 58                |
| [57] qq IB            | ;constant( 1 bit in position 39)             |

e41

[Testprogram no. 7. Topsøes test of the floating point operations: AR F, SR F, MK F and DK F.

The testprogram operates in 6000 cycles. In each cycle two random, floating point numbers, a and b, are generated by means of the subroutines RAND-1 and RAND-2. The four floating point operations are then carried out on the numbers a and b, and the four results are added (as fixed points numbers) to four sum cells.

After 6000 cycles a line is printed on the typewriter, containing the number 6000 and the four sum cells in octal notation. The four sum cells are then cleared and 6000 new cycles are calculated, etc. If KB=1 the program will stop after 6000 cycles, and can be repeated by pressing the NORMAL START-button.

The correct output is (only the numbers):

```
6000 35271407753020 36242706607000 66043725657530 15577777733744
6000 35271407753020 36242706607000 66043725657530 15577777733744
etc.
test of:      add.           sub.           mult.           div.
```

Calculation of 6000 cycles takes about 35 sec. The value of 6000 is stored in cell 114 as an integer in pos. 39. It may be changed if required. If KA is set to 1, output is obtained after each cycle.

The program is stored from cell 41 to 136. The first instruction to be executed is zq LKB.]

i=41

|       |                  |                                   |
|-------|------------------|-----------------------------------|
| [ 41] | zq LKB           | ;stop if KB=1                     |
| [ 42] | vy 16,hv r4      | ;typewriter output,go to 46       |
| [ 43] | qq 0             |                                   |
| [ 44] | qq 0             |                                   |
| [ 45] | zq LKB           | ;stop if KB=1                     |
| [ 46] | grn r71 [117]    | ;sum:=0                           |
| [ 47] | grn r71 [118]    | ;sum:=0                           |
| [ 48] | grn r71 [119]    | ;sum:=0                           |
| [ 49] | grn r71 [120]    | ;sum:=0                           |
| [ 50] | hv r19           | ;go to 69                         |
| [ 51] | qq 0             |                                   |
| [ 52] | qq 0             |                                   |
| [ 53] | qq IZA           | ;parameter                        |
| [ 54] | gcn s9 t320      | ;parameter                        |
| [ 55] | pi t-65          | ;from 55 to 66 is placed -        |
| [ 56] | arn r-2,gr r-13  | ;a subroutine for printing -      |
| [ 57] | dlr r-14,tk 20   | ;out the counter in location -    |
| [ 58] | pi 64 NZ t-65    | ;115 in decimal notation.         |
| [ 59] | hv r3 NZ         |                                   |
| [ 60] | hv r2 NTB        |                                   |
| [ 61] | sy 16,hv r2      |                                   |
| [ 62] | gt r, sy         |                                   |
| [ 63] | gm r-11,pm r-20  |                                   |
| [ 64] | dlr r-11,gr r-21 |                                   |
| [ 65] | hr s2 LZ         |                                   |
| [ 66] | pm r-14,hv r-9   |                                   |
| [ 67] | qq t256          | ;parameter                        |
| [ 68] | qq IB            | ;parameter                        |
| [ 69] | grn r-25         | ;zeroes to cell 44                |
| [ 70] | arn r39,gr r65   | ;mge start-random from 109 to 135 |
| [ 71] | grn r44          | ;counter:=0                       |
| [ 72] | pp 2,pp p-1      | ;p:=2 , p:=p-1                    |
| [ 73] | grn p121,hs r51  | ;cell:=0 , go to RAND-2           |
| [ 74] | qq 20            | ;parameter                        |

|       |                   |                                  |
|-------|-------------------|----------------------------------|
| [ 75] | sr 10 D           | ;-10                             |
| [ 76] | ga p121,hs r52    | ;set exp. ,go to RAND-1          |
| [ 77] | tk 2 ITA          | ;set sign                        |
| [ 78] | ck -6,t1 -6       | ;Roo:=0                          |
| [ 79] | ac p121,arn r-12  | ;store , fetch 1                 |
| [ 80] | tk 1 LTA          | ;if neg. then -2                 |
| [ 81] | ac p121           | ;add to cell                     |
| [ 82] | bs p,hh r-10      | ;repeat                          |
| [ 83] | pp 4,pp p-1       | ;p:=4 , p:=p-1                   |
| [ 84] | arfn r37,udf p110 | ;fetch b , execute               |
| [ 85] | grf r38           | ;store in 123                    |
| [ 86] | arn r37,ac p117   | ;add to cell                     |
| [ 87] | bs p,hh r-4       | ;repeat                          |
| [ 88] | hsn r5 X LKA t52  | ;check output                    |
| [ 89] | arn r-21,ar r26   | ;count                           |
| [ 90] | gr r25,sr r24     | ;- limit                         |
| [ 91] | hv r-19 LT        | ;repeat                          |
| [ 92] | psn r43           | ;final output                    |
| [ 93] | sy 64,arn r22     | ;CAR RET,counter to R-reg.       |
| [ 94] | hs r-39 X t59     | ;print counter                   |
| [ 95] | qq 257 t-144      | ;parameters                      |
| [ 96] | sy ,sy            | ;2 SPACES                        |
| [ 97] | pp 4,pp p-1       | ;p:=4 , p:=p-1                   |
| [ 98] | arn p117,t1 -10   | ;fetch number , shift            |
| [ 99] | ga r17,sr r17     | ;delete bits 0-9                 |
| [100] | t1 3,ca           | ;shift , if zero                 |
| [101] | sy 16,hv r2       | ;then print zero                 |
| [102] | ga r14,sy (r14)   | ;store and print                 |
| [103] | bt 13 t-1         | ;repeat 13 times                 |
| [104] | hv r-5            |                                  |
| [105] | pan r-2 X t13     | ;reset address in bt-instruction |
| [106] | sy ,sy            | ;2 SPACES                        |
| [107] | bs p,hh r-10      | ;repeat                          |
| [108] | hr s1             | ;exit ( to 136)                  |
| [109] | bs p104 V t-333   | ;start random                    |
| [110] | dkf r11           | ;/b                              |
| [111] | mkf r11           | ;xa                              |
| [112] | srf r10           | ;-a                              |
| [113] | arf r9            | ;+a                              |
| [114] | qq (s) XV LT      | ;6000 = limit                    |
| [115] | qq                | ;counter                         |
| [116] | qq                | ;storage of address              |
| [117] | qq                | ;storage of div.                 |
| [118] | qq                | ;storage of mult.                |
| [119] | qq                | ;storage of subtr.               |
| [120] | qq                | ;storage of add.                 |
| [121] | qq                | ;storage of b                    |
| [122] | qq                | ;storage of a                    |
| [123] | qq                | ;storage of result               |
| [124] | hs r4 t44         | ;RAND-2                          |
| [125] | xr ,mkn s1        |                                  |
| [126] | mb 511 D          |                                  |
| [127] | hr s2             |                                  |
| [128] | pm r7,mln r5      | ;RAND-1                          |
| [129] | tk 8,gm r6        |                                  |
| [130] | ar r5             |                                  |
| [131] | sr r3 LO          |                                  |
| [132] | gr r3,hr s1       |                                  |
| [133] | gtm p,dln r434    |                                  |
| [134] | udn (p511),pc -1  |                                  |
| [135] | qq                | ;age of start random             |
| [136] | hv 45             | ;go to 6000 new cycles           |

[Testprogram no. 8. Test of drum track transfer time.

The time for execution of an LK instruction is tested by the program. If KA is set to 1, the transfer time for all tracks is printed out. If KA=0 there will only be output for tracks with a transfer time different from 20 ms. The output is in binary notation for the transfer times as well as for the track numbers.

After the end of a test run ( output <slut> on the typewriter), the test can be repeated by pressing the NORMAL START-button. If the qq instruction in location 57 is changed to a zq instruction, the actual transfer time can after stop in location 57 be observed in the R-register in microseconds with unit in pos. 19.

First instruction to be executed is zq LKB in location 41.]

|                   |                                       |
|-------------------|---------------------------------------|
| i=41              |                                       |
| [41] zq LKB       | ;stop if KB=1                         |
| [42] vy 16, sy 64 | ;select typewriter, CR                |
| [43] sy 58, sy 36 | ;lower case, m                        |
| [44] sy 18        | ;s                                    |
| [45] bt 10 t-1    | ;write 10 SPACE                       |
| [46] sy , hv 45   |                                       |
| [47] sy 19, sy 41 | ;t, r                                 |
| [48] sy 49, sy 51 | ;a, c                                 |
| [49] sy 34, sy 64 | ;k, CR                                |
| [50] bt 320 t-1   | ;select -                             |
| [51] vk -1 V t1   | ; - tracks 0-319                      |
| [52] hv 75        | ;go to 75 if track no. =319           |
| [53] lkn -512     | ;read track, zeroes to R              |
| [54] hk 57        | ;if transfer finished then go to 57 - |
| [55] ar 74        | ;else add 113 microseconds            |
| [56] hv 54        | ;and go to 54                         |
| [57] qq           | ;empty                                |
| [58] nc 20 NKA    | ;output for all tracks if KA=1 -      |
| [59] ps 66 V      | ; - else only output for tracks -     |
| [60] hv 50        | ; - with transfer time $\neq$ 20 ms   |
| [61] tk 1         | ;shift 1 position to the left         |
| [62] sy 1 V LT    | ;print 1 if sign                      |
| [63] sy 38        | ;else print 0                         |
| [64] bt 9 t-1     | ;and repeat 9 times -                 |
| [65] hv 61        | ; - from 61                           |
| [66] hv s1        |                                       |
| [67] sy , sy      | ;2 SPACE                              |
| [68] pa 64 t9     | ;reset address in loc. 64             |
| [69] arn (51) D   | ;track no. to R                       |
| [70] hs 61        | ;print track no.                      |
| [71] pa 64 t9     | ;reset address in loc. 64             |
| [72] sy 64        | ;CR                                   |
| [73] hv 50        | ;go to new track                      |
| [74] qq t113      | ;number of microseconds               |
| [75] sy 18        | ;s                                    |
| [76] sy 35, sy 20 | ;l, u                                 |
| [77] sy 19, sy 64 | ;t, CR                                |
| [78] zq           | ;stop                                 |
| [79] pa 45 t10    | ;reset loc. 45                        |
| [80] pa 50 t320   | ;reset loc. 50                        |
| [81] pa 51 t-1    | ;reset loc. 51                        |
| [82] hv 41        | ;go to start                          |
| e41               |                                       |



[Testprogram no. 9. Test of the IBM-typewriter for input/output.

When the testprogram is read into GIER, a correct run will be, that every character, that is manually typed on the typewriter, is typed out again 9 times by the program. If upper case is typed, a serie of case shifts will be done.

If KA=0, the characters are tested in lower case, if KA=1, they are tested in upper case.

First instruction to be executed is zq LKB.]

|      |                  |
|------|------------------|
| i=41 |                  |
| [41] | zq LKB           |
| [42] | vy 17, ly r3     |
| [43] | sy 60 LKA        |
| [44] | sy 58 NKA        |
| [45] | qq 0, ca 60      |
| [46] | hv r5            |
| [47] | pa r1 t9         |
| [48] | bt 9 t-1         |
| [49] | sy (r-4), hv r-1 |
| [50] | sy 64, hh 42     |
| [51] | sy 60, sy 58     |
| [52] | sy 60, sy 58     |
| [53] | sy 60, sy 58     |
| [54] | sy 60, sy 58     |
| [55] | sy 60, LKA       |
| [56] | hh 42            |
| e41  |                  |

  

|  |                                      |
|--|--------------------------------------|
|  | ;typewriter input/output, read to 45 |
|  | ;upper case if KA=1                  |
|  | ;lower case if KA=0                  |
|  | ;if upper case is input-character    |
|  | ;then go to caseshift                |
|  | ;reset address in loc. 48            |
|  | ;9 times -                           |
|  | ;- print the read character          |
|  | ;type CR, go to new character        |
|  | ;case shift                          |
|  |                                      |
|  | ;end in upper case if KA=1           |
|  | ;go to new character                 |

The program test reading and writing in cells 512-1023 in the fast memory. If a cell in this interval is mistaken for another cell in the same interval there will be no errorreaction, because the program use the same bitpattern in all cells during one testcycle. The program is stored from cell 41 to 131.

#### INPUT OF PROGRAM

The program is published in a condensed version ( a B-tape ) to be read into the machine by the basic inputprogram on channel 0, cells 34-39. After the input a sumcheck of the program is performed. If this check is ok. the program writes <CR, t 10 > on the typewriter with black ribbon, otherwise the programname will be typed in red, and the program stops in cell 49.

#### TESTDIGITS

After reading in and sumcheck the program will stop in cell 51 if KB=1. During this stop the registers R and In contains zeroes. If no bits are inserted the program itself will generate the testdigits for the run. If bits are inserted in R or In these bits will serve as testdigits during the run. In In only RA and RB gives sense.

#### BUILD IN TESTDIGITS

When the build in testdigits are used, 42 consecutive bits is taken from a group of bits containing:

$$\underbrace{1,1,1,1,\dots,1,0,0,0,0,\dots,0,1,1,1,1,\dots,1}_{42 \text{ bits}} \quad \underbrace{\phantom{1,1,1,1,\dots,1,0,0,0,0,\dots,0,1,1,1,1,\dots,1}}_{42 \text{ bits}} \quad \underbrace{\phantom{1,1,1,1,\dots,1,0,0,0,0,\dots,0,1,1,1,1,\dots,1}}_{41 \text{ bits}}$$

This means that each cell is automatically tested with 84 different ( but known ) bitpatterns.

#### OPERATORS TESTDIGITS

If the operator choose the testdigits each cell will be tested 81 times with the choosen bitcombination. The operator must insert the bits in R0-39 and the marks in In[RA,RB].

#### ERROR REACTIONS

During the running of the program, the normal condition of KA and KB is KA=KB=0. In this case there will be no error-output before one complete run is terminated. A complete run means writing and reading in cells 512-1023 of either the 84 generated bitpatterns or 81 times with the operators bits.

NO ERROR: If no error is registrated the run will terminate with the typed message <CR,ok> and a hoot at 1000 c/s in 5 seconds.

ERROR: If an error is registrated the run will terminate with the typed message <CR,-> and the frequency of the hoot will alternate between 950 c/s and 1100 c/s.

KA=1 will cause the program to stop when an error is detected in the bits 0-39 or the marks in the cell in question. There is two possible stoppoints in the program:

- 1) Stop with r1=122 [0001111010] indicates error in bits 0-39. The testbits used will be found in M.Bits in R set to 1 are errors. Depressing the START-button two times while the STOP-button is depressed will transfer the adress of the cell to p and the cellcontent to R0-39. Depressing START will continue the test.
- 2) Stop with r1=125 [0001111101] indicates error in the marks. The testmarks is stored in R8-9 and the marks of the cell in In[RA,RB]. The adress of the cell is transferred to p. Depressing START will continue the test.

Setting KB=1 when the machine is stopped in an error, and depressing START, will cause cycling in a loop as long as KB=1. In this loop th content of M0-39 and In[RA,RB] is stored in the cell, and the content of the cell is read to R0-39 and In[QA,QB]. ]

[Test of the fast memory, cell 512-1023]

```

i= 41
[ 41] vy 16 ,psn 132
[ 42] ps s-1 ,ar s
[ 43] bs s-41 ,hv r-1 [42] ;form checksum of the program
[ 44] sy 62 ,tk 1
[ 45] sy 29 NZ ;if errorsum then redshift
[ 46] sy 64 ,sy 19
[ 47] sy ,sy 1
[ 48] sy 16 ,sy 62 ;outtext(outcr,<<t 10>,blackshift)
[ 49] zq NZ ;if errorsum then stop
[ 50] pin ;R:=In:=0
[ 51] zq LKB ;if KB then stop for manual testdigits
[ 52] gr r57 [109] M ;controlcell 40,41 := 0,0
[ 53] pa r35 [88] t1 ;manualdigits:=true
[ 54] gi r2 [56] V LZ ;if R=0 then c56adr:=In / goto c56
[ 55] pa r18 [73] ,hv r36 [91] ;error:=false / goto operators testdigits
[ 56] nc ,hv r-1 [55] ;if In=0 then goto c55
[ 57] pa r31 [88] ,pa r16 [73] ;manualdigits:=false / error:=false
[ 58] pm D ;M:=0
[ 59] pi ,hs 101 ;In:=0 / test
[ 60] pi 1 ,hs 101 ;In:=1 / test
[ 61] pi 3 ,hs 101 ;In:=3 / test
[ 62] pm r37 [99] ,hs 101 ;M 0-39 := all 1 / test
[ 63] xrm ,cl -1 ;R:=MX2(-1)
[ 64] hh r-2 [62] X NZ ;if M=0 then begin M:=R;goto c62 end
[ 65] pm r34 [99] ,pi 2 ;M 0-39 := all 1 / In:=2
[ 66] hs 101 ;test
[ 67] pi ,hs 101 ;In:=0 / test
[ 68] xr ,tk 1 ;R:=MX2
[ 69] pm r30 [99] ,cm r31 [100] ;if R=-1 then begin M:=R;goto c71 end
[ 70] hh r-3 [67] X ;else goto c67
[ 71] gr r38 [109] XV MRC ;controlcell 40,41 := 1,1 / M:=R
[ 72] hs 101 ;test
[ 73] ps ,sy 64 ;s:=error / outcr
[ 74] can s ,hv r2 [76] ;if -,error then goto c76
[ 75] sy 32 ,hv r2 [77] ;else writetext(<<->) / goto c77
[ 76] sy 38 ,sy 34 ;writetext(<<ok>)
[ 77] pa r9 [86] t9
[ 78] pa r5 [83] t511 ;initialize hootduration
[ 79] pa r2 [81] t7 ;initialize frequency-cycle
[ 80] ar s128 D ;RadR := (if error then 8 else 0)+128+RadR
[ 81] bt 7 t-1 ;for i:=7 step -1 until 1 do
[ 82] hv r-2 [80] ;goto c80
[ 83] bt 511 t-1 ;for j:=511 step -1 until 1 do
[ 84] hv r-5 [79] ;goto c79
[ 85] ns s ,ps s ;s:=-s
[ 86] bt 9 t-1 ;for k:=9 step -1 until 1 do
[ 87] hv r-9 [78] ;goto c78
[ 88] bs ;if manualdigits then
[ 89] hv r-38 [51] X ;goto newtest(Operatorsdigits)
[ 90] hv r-40 [50] ;else goto newtest(buildindigits)
[ 91] pm r8 [99] ,cm r9 [100] ;Operatorsdigits:=
[ 92] hv r2 [94] ;if R=-1 then goto c94
[ 93] gr r16 [109] MRC ;controlcell 0-39 := R ,40,41:=RA,RB
[ 94] pa r2 [96] X t80 ;M:=R / for i:=1 step 1 until 81 do
[ 95] hs 101 ;test

```

|       |     |             |        |            |
|-------|-----|-------------|--------|------------|
| [ 96] | bt  |             | t-1    |            |
| [ 97] | hv  | r-2 [95]    |        |            |
| [ 98] | hv  | r-25 [73]   |        |            |
| [ 99] | udn | (p-1)       | XVDLRC | t-1        |
| [100] | qq  | -512        |        |            |
| [101] | pa  | r3 [104]    |        | t511       |
| [102] | pa  | r1 [103]    |        |            |
| [103] | gm  |             | MRC    | t-1        |
| [104] | bt  | 511         |        | t-1        |
| [105] | hv  | r-2 [103]   |        |            |
| [106] | pa  | r12 [118]   |        | t511       |
| [107] | pa  | r7 [114]    |        |            |
| [108] | grn | r1 [109]    | XV     |            |
| [109] | qq  |             |        |            |
| [110] | sc  | r-1 [109]   | X      |            |
| [111] | gi  | r9 [120]    |        |            |
| [112] | pi  |             | ,arn   | r-3 [109]  |
| [113] | srn | r-4 [109]   | LC     |            |
| [114] | ar  |             | IRC    | t-1        |
| [115] | hv  | r6 [121]    | NZ     |            |
| [116] | gi  | r1 [117]    | ,arn   | r4 [120]   |
| [117] | nc  |             | ,hh    | r6 [123]   |
| [118] | bt  |             |        | t-1        |
| [119] | hv  | r-7 [112]   |        |            |
| [120] | pi  |             | ,hr    | s1         |
| [121] | zq  |             | LKA    |            |
| [122] | pp  | (r-8)[114]  | ,arn   | p          |
| [123] | hv  | r2 [125]    | ,pp    | (r-9)[114] |
| [124] | zq  |             | LKA    |            |
| [125] | pa  | r-52 [73]   |        | t8         |
| [126] | pi  | (r-6)[120]  | ,hv    | r3 [129]   |
| [127] | gm  | p           | MRC    |            |
| [128] | arn | p           | IQC    |            |
| [129] | hv  | r-2 [127]   | LKB    |            |
| [130] | pi  | (r-10)[120] | ,hv    | r-12 [118] |
| [131] | gmn | -319        | X LP   | t488       |

S

```

;test finished
;constant 0-39 := all 1
;procedure test;begin
;entry to test
;for j:=1023 step -1 until 512 do
;cell j 0-39:= M cellj 40-41 :=RA,RB
...
;for i:=1023 step -1 until 512 do begin
;controlcell 0-39 := 0 / R:=testdigits
;controlcell:=-testdigits / M:=testdigits
;c120adr:=In
;In:=0 / R:=-testdigits
;if R=-1 then R:=(-testdigits)
;R:=R+cell[i] / In[RA,RB]:=cell i 40,41
;if R#0 then goto errorincell
;c117adr:= In / R:= old In
;if newmarks#oldmarks then goto errorinmarks
;one cell tested
...
;In:=Original marks / end of procedure test;
;errorincell: if errorincell/KA then stop
;p:=adress of wrong cell / R:=wrong cell
;goto seterror / errorinmarks: p:=adress of wrong
;if error in marks /KA then stop
;seterror: error:=true
;In:=original marks
;testdigits to cell
;cell to R
;if KB then cycle in 127-128
;In:=Original marks / continue the test
;checksum of program

```

## [Testprogram t11 (ferrittest)]

The program test reading and writing in cells 0-511 in the fast memory. If a cell in this interval is mistaken for another cell in the same interval there will be no errorreaction, because the program use the same bitpattern in all cells during one testcycle. The program is stored from cell 513 to 603.

## INPUT OF PROGRAM

The program is published in a condensed version ( a B-tape ) to be read into the machine by the basic inputprogram on channel 0, cells 34-39. After the input a sumcheck of the program is performed. If this check is ok, the program writes <CR, t 10 > on the typewriter with black ribbon, otherwise the programname will be typed in red, and the program stops in cell 521.

## TESTDIGITS

After reading in and sumcheck the program will stop in cell 523 if KB=1. During this stop the registers R and In contains zeroes. If no bits are inserted the program itself will generate the testdigits for the run. If bits are inserted in R or In these bits will serve as testdigits during the run. In only RA and RB gives sense.

## BUILD IN TESTDIGITS

When the build in testdigits are used, 42 consecutive bits is taken from a group of bits containing:

1,1,1,1,....,1,0,0,0,0,....,0,1,1,1,1,....,1

42 bits                      42 bits                      41 bits

This means that each cell is automatically tested with 84 different ( but known ) bitpatterns.

## OPERATORS TESTDIGITS

If the operator choose the testdigits each cell will be tested 81 times with the choosen bitcombination. The operator must insert the bits in R0-39 and the marks in In[RA,RB].

## ERROR REACTIONS

During the running of the program, the normal condition of KA and KB is KA=KB=0. In this case there will be no error-output before one complete run is terminated. A complete run means writing and reading in cells 0-511 of either the 84 generated bitpatterns or 81 times with the operators bits.

NO ERROR: If no error is registrated the run will terminate with the typed message <CR,ok> and a hoot at 1000 c/s in 5 seconds.

ERROR: If an error is registrated the run will terminate with the typed message <CR,-> and the frequency of the hoot will alternate between 950 c/s and 1100 c/s.

KA=1 will cause the program to stop when an error is detected in the bits 0-39 or the marks in the cell in question. There is two possible stoppoints in the program:

- 1) Stop with r1=594[1001010010] indicates error in bits 0-39. The testbits used will be found in M.Bits in R set to 1 are errors. Depressing the START-button two times while the STOP-button is depressed will transfer the adress of the cell to p and the cellcontent to R0-39. Depressing START will continue the test.
- 2) Stop with r1=597[1001010101] indicates error in the marks. The testmarks is stored in R8-9 and the marks of the cell in In[RA,RB]. The adress of the cell is transferred to p. Depressing START will continue the test.

Setting KB=1 when the machine is stopped in an error, and depressing START, will cause cycling in a loop as long as KB=1. In this loop th content of M0-39 and In[RA,RB] is stored in the cell, and the content of the cell is read to R0-39 and In[QA,QB]. ]

[Test of the fast memory, cells 0-511]

i= -511

```

[-511] vy 16 ,psn -420
[-510] ps s-1 ,ar s
[-509] bs s511 ,hv r-1 [-510] ;form checksum of the program
[-508] sy 62 ,tk 1
[-507] sy 29 NZ ;if errorsum then redshift
[-506] sy 64 ,sy 19
[-505] sy ,sy 1
[-504] sy 1 ,sy 62 ;typetext(CR,<<t 11>>,blackshift)
[-503] zq NZ ;if errorsum then STOP
[-502] pin ;R:=In:=0
[-501] zq LKB ;if KB=1 then STOP for manual testdigits
[-500] gr r57 [-443] M ;controlcell 40,41:= 0,0
[-499] pa r35 [-464] t1 ;manualdigits:=true
[-498] gi r2 [-496] V LZ ;if R=0 then c528adr:=In / goto c528
[-497] pa r18 [-479] ,hv r36 [-461] ;error:=false / goto operators testdigits
[-496] nc ,hv r-1 [-497] ;if In=0 then goto c527
[-495] pa r31 [-464] ,pa r16 [-479] ;manualdigits:= false / error:= false
[-494] pm D ;M:= 0
[-493] pi ,hs -451 ;In:= 0 / test
[-492] pi 1 ,hs -451 ;In:= 1 / test
[-491] pi 3 ,hs -451 ;In:= 3 / test
[-490] pm r37 [-453] ,hs -451 ;MO-39:= all 1 / test
[-489] xrm ,cl -1 ;R:= MX2^(-1)
[-488] hh r-2 [-490] X NZ ;if M=0 then begin M:=R;goto c534 end
[-487] pm r34 [-453] ,pi 2 ;MO-39:= all 1 / In:=2
[-486] hs -451 ;test
[-485] pi ,hs -451 ;In:= 0 / test
[-484] xr ,tk 1 ;R:= MX2
[-483] pm r30 [-453] ,cm r31 [-452] ;if R=-1 then begin M:=R;goto c543 end
[-482] hh r-3 [-485] X ;else goto c539
[-481] gr r38 [-443] XV MRC ;controlcell 40,41:= 1,1 / M:=R
[-480] hs -451 ;test
[-479] ps ,sy 64 ;s:= error / typetext(CR)
[-478] can s ,hv r2 [-476] ;if -,error then goto c548
[-477] sy 32 ,hv r2 [-475] ;else typetext(<<->>) / goto c549
[-476] sy 38 ,sy 34 ;typetext(<<ok>>)
[-475] pa r9 [-466] t9
[-474] pa r5 [-469] t511
[-473] pa r2 [-471] t7
[-472] ar s128 D ;initialize hootduration
[-471] bt 7 t-1 ;initialize frequencycycle
[-470] hv r-2 [-472] t-1 ;Radr:= Radr+128+(if error then 8 else 1)
[-469] bt 511 t-1 ;for i:= 7 step -1 until 1 do
[-468] hv r-5 [-473] ;goto c552
[-467] ns s ,ps s ;for j:= 511 step -1 until 1 do
[-466] bt 9 t-1 ;goto c551
[-465] hv r-9 [-474] ;s:= -s
[-464] bs ;for k:= 9 step -1 until 1 do
[-463] hv r-38 [-501] X ;goto c550
[-462] hv r-40 [-502] ;if manualdigits then
[-461] pm r8 [-453] ,cm r9 [-452] ;newtest(operators testdigits)
[-460] hv r2 [-458] ;else newtest(buildin testdigits)
[-459] gr r16 [-443] MRC ;operators testdigits:
[-458] pa r2 [-456] X t80 ;if R=-1 then goto c566
[-457] hs -451 ;controlcell0-39:= R , 40-41:=RA-RB
[-456] bt t-1 ;M:=R / for i:= 1 step 1 until 81 do
[-455] hv r-2 [-457] ;test
[-454] hv r-25 [-479] ;test finished
[-453] udn (p-1) XVDLRC t-1 ;constant0-39= all 1

```



INDICATOR TEST

B 12 - 1

Before start KA, KB are set to 0, 1. The test is supplied with a number of loops, so if any error occurs, KA is set to one, and the program will run in the loop, where the error appeared. All stops indicate errors. Cellnumber is found by subtraction of one from the content of  $r_1$ .

|    |     |           |     |   |
|----|-----|-----------|-----|---|
| 41 | zq  |           | LKB |   |
| 42 | grn | 300       |     |   |
| 43 | pi  | -1        |     |   |
| 44 | gi  | 300       |     |   |
| 45 | arn | 300       |     |   |
| 46 | sr  | -1        | D   |   |
| 47 | zq  |           | NZ  |   |
| 48 | hv  | 43        | LKA | loop A, test of flip-flops for "ones"   |
| 49 | pi  |           |     |   |
| 50 | gi  | 300       | MOC |   |
| 51 | arn | 300       |     |   |
| 52 | zq  |           | NZ  |   |
| 53 | hv  | 49        | LKA | loop B, test of flip-flops for "zeroes" |
| 54 | pi  | -1        |     | t-2 inhibit changing all except RB      |
| 55 | zq  |           | NRB |   |
| 56 | pi  | -2        |     | t-3 inhibit changing all except RA      |
| 57 | zq  |           | NRA |   |
| 58 | hv  | 60        | LRC | } proving "L" indicator orders          |
| 59 | zq  |           |     |   |
| 60 | zq  |           | LOA |   |
| 61 | zq  |           | LOB |   |
| 62 | zq  |           | LTA |   |
| 63 | zq  |           | LTB |   |
| 64 | zq  |           | LPA |   |
| 65 | zq  |           | LPB |   |
| 66 | zq  |           | LQA |   |
| 67 | zq  |           | LQB |   |
| 68 | gi  | 300 , arn | 300 |   |
| 69 | sr  | 3         | D   |   |
| 70 | zq  |           | NZ  |   |

96: gi 300, arn 300  
 169: pi -512 t<sub>511</sub>



|     |     |     |      |                                      |
|-----|-----|-----|------|--------------------------------------|
| 71  | qq  |     | MOC  | $R_{40-41}$ are set to zero          |
| 72  | ppn |     | IRB  | dummy order , RB: = 0                |
| 73  | ppn |     | IRA  | dummy order , RA: = 0                |
| 74  | zq  |     | LRB  |                                      |
| 75  | zq  |     | LRA  |                                      |
| 76  | qq  |     | M    | $R_{40-41}$ are set to one           |
| 77  | ck  | 10  | IRB  | dummy order, RB: = 1                 |
| 78  | ck  | 10  | IRA  | dummy order, RA: = 1                 |
| 79  | zq  |     | NRA  |                                      |
| 80  | zq  |     | NRB  |                                      |
| 81  | hv  | 54  | LKA  | loop C, test of RA, RB               |
| 82  | pi  | -4  |      | t-5 inhibit changing all except QB   |
| 83  | zq  |     | NQB  |                                      |
| 84  | pi  | -8  |      | t-9 inhibit changing all except QA   |
| 85  | zq  |     | NQA  |                                      |
| 86  | hv  | 88  | LQC  | } proving "L and N" indicator orders |
| 87  | zq  |     |      |                                      |
| 88  | zq  |     | LOA  |                                      |
| 89  | zq  |     | LOB  |                                      |
| 90  | zq  |     | LTA  |                                      |
| 91  | zq  |     | LTB  |                                      |
| 92  | zq  |     | LPA  |                                      |
| 93  | zq  |     | LPB  |                                      |
| 94  | zq  |     | NRA  |                                      |
| 95  | zq  |     | NRB  |                                      |
| 96  | gi  |     | ,arn | 300                                  |
| 97  | sr  | 15  | D    |                                      |
| 98  | zq  |     | NZ   |                                      |
| 99  | gmn | 400 | IQB  | dummy order, QB: = 0                 |
| 100 | gmn | 400 | IQA  | dummy order, QA: = 0                 |
| 101 | zq  |     | LQB  |                                      |
| 102 | zq  |     | LQA  |                                      |
| 103 | qq  |     | M    |                                      |
| 104 | tk  | 2   | IQB  | dummy order, QB: = 1                 |
| 105 | tk  | 2   | IQA  | dummy order, QA: = 1                 |
| 106 | zq  |     | NQB  |                                      |
| 107 | zq  |     | NQA  |                                      |
| 108 | hv  | 82  | LKA  | loop D, test of QA, QB               |

|     |     |      |     |  |
|-----|-----|------|-----|--|
| 109 | pi  | -16  |     | t-17 inhibit changing all except PB    |
| 110 | zq  |      | NPB |  |
| 111 | pi  | -32  |     | t-33 inhibit changing all except PA    |
| 112 | zq  |      | NPA |  |
| 113 | hv  | 115  | LPC | } proving "L" and "N" indicator orders |
| 114 | zq  |      |     |  |
| 115 | zq  |      | LOA |  |
| 116 | zq  |      | LOB |  |
| 117 | zq  |      | LTA |  |
| 118 | zq  |      | LTB |  |
| 119 | zq  |      | NQA |  |
| 120 | zq  |      | NQB |  |
| 121 | zq  |      | NRA |  |
| 122 | zq  |      | NRB |  |
| 123 | gi  | 300  |     |  |
| 124 | arn | 300  |     |  |
| 125 | sr  | 63   | D   |  |
| 126 | zq  |      | NZ  |  |
| 127 | gmn | 400  | IPB | dummy order, PB: = 0                   |
| 128 | gmn | 400  | IPA | dummy order, PA: = 0                   |
| 129 | zq  |      | LPB |  |
| 130 | zq  |      | LPA |  |
| 131 | qq  |      | M   |  |
| 132 | tl  | 4    | IPB | dummy order, PB: = 1                   |
| 133 | tl  | 4    | IPA | dummy order, PA: = 1                   |
| 134 | zq  |      | NPB |  |
| 135 | zq  |      | NPA |  |
| 136 | hv  | 109  | LKA | loop E, test of PA and PB              |
| 137 | pi  | -64  |     | t-65 inhibit changing all except TB    |
| 138 | zq  |      | NTB |  |
| 139 | pi  | -128 |     | t-129 inhibit changing all except TA   |
| 140 | zq  |      | NTA |  |
| 141 | hv  | 143  | LTC |  |
| 142 | zq  |      |     |  |

|     |     |      |       |  |
|-----|-----|------|-------|--|
| 143 | zq  |      | LOA   |  |
| 144 | zq  |      | LOB   |  |
| 145 | zq  |      | NTA   |  |
| 146 | zq  |      | NTB   |  |
| 147 | zq  |      | NPA   | } proving "L" and "N" indicator orders |
| 148 | zq  |      | NPB   |  |
| 149 | zq  |      | NQA   |  |
| 150 | zq  |      | NQB   |  |
| 151 | zq  |      | NRA   |  |
| 152 | zq  |      | NRB   |  |
| 153 | gi  | 300  |       |  |
| 154 | arn | 300  |       |  |
| 155 | sr  | 255  | D     |  |
| 156 | zq  |      | NZ    |  |
| 157 | qqn |      | ITB   | TB: = 0                                |
| 158 | qqn |      | ITA   | TA: = 0                                |
| 159 | zq  |      | LTB   |  |
| 160 | zq  |      | LTA   |  |
| 161 | arn | -1   | D ITB | TB: = 1                                |
| 162 | arn | -1   | D ITA | TA: = 1                                |
| 163 | zq  |      | NTB   |  |
| 164 | zq  |      | NTA   |  |
| 165 | hv  | 137  | LKA   | loop F, test of TA and TB              |
| 166 | pi  | -256 |       | t-257 inhibit changing all except OB   |
| 167 | zq  |      | NOB   |  |
| 168 | zq  |      | NZB   |  |
| 169 | pi  | -512 |       | t-511 inhibit changing all except OA   |
| 170 | zq  |      | NOA   |  |
| 171 | zq  |      | NZA   |  |
| 172 | hv  | 174  | LOC   | } proving "L" and "N" indicator orders |
| 173 | zq  |      |       |  |
| 174 | hv  | 176  | LZC   |  |
| 175 | zq  |      |       |  |
| 176 | zq  |      | NTA   |  |
| 177 | zq  |      | NTB   |  |
| 178 | zq  |      | NPA   |  |
| 179 | zq  |      | NPB   |  |
| 180 | zq  |      | NQA   |  |
| 181 | zq  |      | NQB   |  |
| 182 | zq  |      | NRA   |  |
| 183 | zq  |      | NRB   |  |

|     |     |      |       |                              |
|-----|-----|------|-------|------------------------------|
| 184 | gi  | 300  |       |                              |
| 185 | arn | 300  |       |                              |
| 186 | sr  | -1   | D     |                              |
| 187 | zq  |      | NZ    |                              |
| 188 | arn |      | IOB   | dummy order, OB: = 0         |
| 189 | qqn |      | IOA   | dummy order, OA: = 0         |
| 190 | zq  |      | LOB   |                              |
| 191 | zq  |      | LOA   |                              |
| 192 | arn | -1   | D     |                              |
| 193 | ar  | -512 | D IOB | OB: = 1                      |
| 194 | ar  | -512 | D IOA | OA: = 1                      |
| 195 | zq  |      | NOB   |                              |
| 196 | zq  |      | NOA   |                              |
| 197 | hv  | 166  | LKA   | loop G, test of OA, OB       |
| 198 | pi  | -1   |       |                              |
| 199 | pi  |      | t-1   |                              |
| 200 | hv  | 202  | LZC   | proving "L" indicator orders |
| 201 | zq  |      |       |                              |
| 202 | hv  | 204  | LOC   |                              |
| 203 | zq  |      |       |                              |
| 204 | hv  | 206  | LTC   |                              |
| 205 | zq  |      |       |                              |
| 206 | hv  | 208  | LPC   |                              |
| 207 | zq  |      |       |                              |
| 208 | hv  | 210  | LQC   |                              |
| 209 | zq  |      |       |                              |
| 210 | hv  | 212  | LRC   | proving Z combinations       |
| 211 | zq  |      |       |                              |
| 212 | arn | 211  | IZB   |                              |
| 213 | ar  | 211  | IZA   |                              |
| 214 | zq  |      | LZB   |                              |
| 215 | zq  |      | LZA   |                              |
| 216 | pmm |      | IZC   |                              |
| 217 | zq  |      | NZB   |                              |
| 218 | zq  |      | NZA   |                              |
| 219 | pin |      |       |                              |
| 220 | qq  |      | IZB   |                              |
| 221 | ar  | 212  |       |                              |
| 222 | zq  |      | NZB   |                              |
| 223 | pin |      |       |                              |
| 224 | qq  |      | IZA   |                              |
| 225 | ar  | 213  |       |                              |
| 226 | zq  |      | NZA   |                              |

B 12 - 6

|     |    |     |                       |
|-----|----|-----|-----------------------|
| 227 | pi |     |                       |
| 228 | hv | 198 | LKA loop H, test of Z |
| 229 | hv | 41  |                       |

[ Tromtest 4. This program writes random numbers on previous selected drum tracks, reads and compares the contents word by word incl. flag bits. Calculations may be performed simultaneously with the drum test by means of an adder test.

After the message ,klar, the typewriter is ready for input of 3 arbitrary numbers (each terminated by CR) intended for the production of the random test numbers.

The program has several adjustment variations. The p-register contains the track no. to be tested. The five last bits of the in-register have the following meaning:

- KB=0 : Adder test simultaneously with the drum test.
- KB=1 : Either adder test or drum test depending on when KB is set equal to 1.
- KA=0 : No stop if adder error.
- KA=1 : Stop if adder error.
- The typewriter writes ,1, if adder test is ok, and ,3, if adder error.
- RB=0 : No counting in the p-register. Test of the same track.
- RB=1 : Counting in the p-register. Track no. is increased with 1.
- RA=0 : Output of number of errors per track.
- RA=1 : Output of number of errors totally only.
- QB=0 : Output of the read and written bit pattern, track no. and word no. if error.
- QB=1 : No output of the read and written bit pattern, track no. and word no.

By entry a normal adjustment is set intended for a routine test of tracks 1-319 and output only of the number of errors totally (cf. the instructions in cell 42). By installations with Three Drum Cabinet the instruction in cell 51 should be changed to: arn 959 D.

The only way to change the normal adjustment is to change the contents of the in- and p-registers manually and jump to cell 43. The program starts with the instruction ,zq 0 LKB, and stops only if the operator interferes.]

|       |     |     |          |   |
|-------|-----|-----|----------|---|
| i= 41 |     |     |          |   |
| [ 41] | zq  |     | LKB      | [ Stop if KB=1]                                 |
| [ 42] | pi  | 7   | ,pp      | [ Normal adjustment. Start on track 1]          |
| [ 43] | gp  | 53  | ,hs 89   | [ Jump to input of 3 numbers]                   |
| [ 44] | pt  | 61  | t45      | [ Initialising return jump to drum test]        |
| [ 45] | hv  | 257 | ,grn 76  | [ Start adder test, clear error counter tot.]   |
| [ 46] | pp  | p1  | LRB      | [ Add 1 to track no.]                           |
| [ 47] | hs  | 187 |          | [ Store inputed numbers]                        |
| [ 48] | hv  | 155 | ,hv 191  | [ Fill track, store numbers]                    |
| [ 49] | grn | 77  | ,hs 187  | [ Clear error counter per track, store numbers] |
| [ 50] | hv  | 164 | ,hv 199  | [ Read track, transfer numbers]                 |
| [ 51] | arn | 319 | D        | [ If more tracks]                               |
| [ 52] | ncp |     | ,hv 46   | [ then jump to new test]                        |
| [ 53] | pp  |     | ,sy 64   | [ else reset start track, write CR]             |
| [ 54] | arn | 76  | ,hs 203  | [ Jump to output of number of errors totally]   |
| [ 55] | sy  | 64  | ,hh 45   | [ Write CR, jump to new test]                   |
| [ 56] | pt  | 61  | V163     | [ Entry interrupt drum test]                    |
| [ 57] | pt  | 61  | t168     | [ Entry interrupt drum test]                    |
| [ 58] | pm  | 195 | ,arn 196 | [ Reset R and M before]                         |
| [ 59] | gs  | 61  | ,hv 290  | [ jump to adder test]                           |
| [ 60] | gm  | 195 | ,gr 196  | [ Entry interrupt adder test]                   |
| [ 61] | ps  |     | ,hh      | [ Jump to drum test]                            |
| [ 62] | qq  |     |          |   |

|       |                  |  |                  |
|-------|------------------|--|------------------|
| [ 63] | qq               |  | [ Working cells] |
| [ 64] | qq               |  |                  |
| [ 65] | qq               |  |                  |
| [ 66] | qq               |  |                  |
| [ 67] | qq               |  |                  |
| [ 68] | qq               |  |                  |
| [ 69] | qq               |  |                  |
| [ 70] | qq               |  |                  |
| [ 71] | 0/1023/1023/1023 |  | [ Constant]      |
| [ 72] | 1                |  | [ Constant]      |
| [ 73] | qq               |  |                  |
| [ 74] | qq               |  |                  |
| [ 75] | qq               |  |                  |
| [ 76] | qq               |  |                  |
| [ 77] | qq               |  |                  |

|       |     |    |     |   |
|-------|-----|----|-----|---|
| [ 78] | pm  | 68 |     | [ Subroutine, produce random test number]     |
| [ 79] | arn | 68 | X   | [ From the numbers in cells 66, 67, and 68]   |
| [ 80] | mk  | 66 |     | [ 3 numbers are produced to be placed in the] |
| [ 81] | sc  | 67 |     | [ same cells. The contents of R is on exit]   |
| [ 82] | dl  | 68 | X   | [ depending on the contents of these cells]   |
| [ 83] | ac  | 66 | IOA | [ and used as a test number. Possibly]        |
| [ 84] | ml  | 67 |     | [ overflow is indicated in respective OA]     |
| [ 85] | ac  | 68 | IOB | [ and OB for later check of flag bits.]       |
| [ 86] | hr  | s1 |     |   |

|        |     |     |          |  |
|--------|-----|-----|----------|--|
| [ 87]  | 0   |     |          | [ Subroutine, input of 3 numbers]            |
| [ 88]  | 10  |     |          | [ Working cell]                              |
| [ 89]  | pa  | 106 | t62      | [ Constant]                                  |
| [ 90]  | pa  | 107 | t2       | [ Reset start cell]                          |
| [ 91]  | vy  | 17  | ,sy 64   | [ Reset counting]                            |
| [ 92]  | sy  | 34  | ,sy 35   | [ Select typewriter as I/O, write CR]        |
| [ 93]  | sy  | 49  | ,sy 41   | [ Write k, write l]                          |
| [ 94]  | sy  | 64  |          | [ write a, write r]                          |
| [ 95]  | pt  | 102 |          | [ Write CR]                                  |
| [ 96]  | xrn |     | ,lyn 87  | [ Set jump address for positive number]      |
| [ 97]  | nc  | 32  | ,hv 100  | [ Clear M, input of 1 character]             |
| [ 98]  | pt  | 102 | t105     | [ If character $\neq 32$ then jump]          |
| [ 99]  | hh  | 96  |          | [ else set jump address for negative number] |
| [ 100] | ca  | 16  | ,hvn 103 | [ Jump to input of next character]           |
| [ 101] | ca  | 64  |          | [ If character=0 then clear R and jump]      |
| [ 102] | xr  |     | ,hv      | [ If character=64]                           |
| [ 103] | tk  | -30 | ,ml 88   | [ then exchange M and R and jump to storing] |
| [ 104] | hh  | 96  |          | [ else produce a decimal number in M]        |
| [ 105] | mt  | -1  | D        | [ Jump to input of next character]           |
| [ 106] | gr  | 62  | t1       | [ If negative number then change sign]       |
| [ 107] | bt  | 2   | t-1      | [ Store the decimal number in working cell]  |
| [ 108] | hv  | 95  |          | [ Counter for input of 3 numbers]            |
| [ 109] | hr  | s1  |          | [ Jump within 3 numbers]                     |
|        |     |     |          | [ else exit]                                 |

|        |    |     |    |   |
|--------|----|-----|----|---|
| [ 110] | pa | 121 | t3 | [ Subroutine, output of bit pattern from R] |
| [ 111] | tl | -10 |    | [ Prepare output in 4 groups]               |
| [ 112] | pa | 118 | t9 | [ Prepare output of 1 bit at a time]        |
| [ 113] | mb | 71  |    | [ Prepare 10 positions in each group]       |
|        |    |     |    | [ Clear R pos. 0-9]                         |

|        |    |     |       |  |
|--------|----|-----|-------|--|
| [ 114] | tl | 1   |       | [ Produce 1 bit]                         |
| [ 115] | ca |     |       | [ If it is 0]                            |
| [ 116] | sy | 16  | V     | [ then write 0]                          |
| [ 117] | sy | 1   |       | [ else write 1]                          |
| [ 118] | bt | 9   | t-1   | [ Counter for output of 10 pos.]         |
| [ 119] | hv | 113 |       | [ Jump back within a group]              |
| [ 120] | sy |     |       | [ else write SP]                         |
| [ 121] | bt | 3   | t-1   | [ Counter for output of 4 groups]        |
| [ 122] | hv | 112 |       | [ Jump back within 4 groups]             |
| [ 123] | sy | 1   | V LPA | [ else write ,1, or ,0, according to PA] |
| [ 124] | sy | 16  |       | [ which corresponds to bit 40]           |
| [ 125] | sy | 1   | V LPB | [ Write ,1, or ,0, according to PB]      |
| [ 126] | sy | 16  |       | [ which corresponds to bit 41]           |
| [ 127] | hr | s1  |       | [ Exit]                                  |

|        |     |     |         |   |
|--------|-----|-----|---------|---|
| [ 128] | sy  |     | ,sy     | [ Subroutine, output of track no. and word no.] |
| [ 129] | sy  | 34  | ,sy 49  | [ Write SP, write SP]                           |
| [ 130] | sy  | 37  | ,sy 49  | [ Write k, write a]                             |
| [ 131] | sy  | 35  | ,sy     | [ write n, write a]                             |
| [ 132] | arn | p   | D       | [ write l, write SP]                            |
| [ 133] | ck  |     | ,tl -30 | [ Prepare output]                               |
| [ 134] | hs  | 203 |         | [ of track no.]                                 |
| [ 135] | sy  |     | ,sy     | [ Jump to output of track no.]                  |
| [ 136] | sy  | 38  | ,sy 41  | [ Write SP, write SP]                           |
| [ 137] | sy  | 52  | ,sy 37  | [ Write o, write r]                             |
| [ 138] | sy  | 41  | ,sy 59  | [ write d, write n]                             |
| [ 139] | srn | 314 | D       | [ write r, write .]                             |
| [ 140] | ar  | 170 | ,tl -30 | [ Prepare output]                               |
| [ 141] | hs  | 203 |         | [ of word no.]                                  |
| [ 142] | hr  | s1  |         | [ Jump to output of word no.]                   |
|        |     |     |         | [ Jump back to error output]                    |

|        |     |       |        |   |
|--------|-----|-------|--------|---|
| [ 143] | arn | 72    | ,ac 76 | [ Subroutine, error output]                 |
| [ 144] | ac  | 77    |        | [ Add 1 to number of errors totally]        |
| [ 145] | hv  | 180   | LQB    | [ Add 1 to number of errors per track]      |
| [ 146] | arn | 69    | IPC    | [ If QB=1 then jump back without output]    |
| [ 147] | vy  | 16    | ,sy 64 | [ else prepare output of test number]       |
| [ 148] | sy  | 64    |        | [ Select typewriter, write CR]              |
| [ 149] | hs  | 110   |        | [ Write CR]                                 |
| [ 150] | sy  | 64    |        | [ Jump to output of bit pattern]            |
| [ 151] | arn | (170) | IPC    | [ Write CR]                                 |
| [ 152] | hs  | 110   |        | [ Prepare output of read test number]       |
| [ 153] | hs  | 128   |        | [ Jump to output of bit pattern]            |
| [ 154] | hv  | 180   |        | [ Jump to output of track no. and word no.] |
|        |     |       |        | [ Jump back to next test]                   |

|        |    |     |         |   |
|--------|----|-----|---------|---|
| [ 155] | pa | 158 | t215    | [ Fill drum track]                              |
| [ 156] | pa | 159 | t39     | [ Reset start address]                          |
| [ 157] | hs | 78  |         | [ Reset counting]                               |
| [ 158] | gr | 215 | MOC t1  | [ Jump to produce random test number]           |
| [ 159] | bt | 39  | t-1     | [ Store result incl. flag bits]                 |
| [ 160] | hv | 157 |         | [ Counter for 40 words]                         |
| [ 161] | vk | p   | ,sk 216 | [ Jump back within a track]                     |
| [ 162] | hv | 56  | NKB     | [ else select actual track no., write on track] |
| [ 163] | vk | p   | ,hh 48  | [ Interrupt if KB=0]                            |
|        |    |     |         | [ Exit]   |



|        |     |     |     |      |   |
|--------|-----|-----|-----|------|---|
| [ 164] | pa  | 180 |     | t39  | [ Read track and check]                         |
| [ 165] | pa  | 170 |     | t313 | [ Reset counting]                               |
| [ 166] | vk  | p   | ,lk | 314  | [ Reset start address]                          |
| [ 167] | hv  | 57  |     | NKB  | [ Select actual track no., read track]          |
| [ 168] | vk  | p   | ,hs | 78   | [ Interrupt if KB=0]                            |
| [ 169] | gr  | 69  |     | MOC  | [ Jump to produce random test number]           |
| [ 170] | sr  | 313 |     | t1   | [ Store test number incl. flag bits]            |
| [ 171] | hv  | 143 |     | NZ   | [ Subtract read number]                         |
| [ 172] | hv  | 175 |     | LOB  | [ Jump to error output if R pos. 0-39+0]        |
| [ 173] | hv  | 143 |     | LB   | [ Jump to error output if OB=0^b=1]             |
| [ 174] | hv  | 176 |     |      |   |
| [ 175] | hv  | 143 |     | NB   | [ Jump to error output if OB=1^b=0]             |
| [ 176] | hv  | 179 |     | LOA  |   |
| [ 177] | hv  | 143 |     | LA   | [ Jump to error output if OA=0^a=1]             |
| [ 178] | hv  | 180 |     |      |   |
| [ 179] | hv  | 143 |     | NA   | [ Jump to error output if OA=1^a=0]             |
| [ 180] | bt  | 39  |     | t-1  | [ Counter for 40 words]                         |
| [ 181] | hv  | 168 |     |      | [ Jump back within a track]                     |
| [ 182] | hh  | 50  |     | LRA  | [ else if RA=1 then return jump]                |
| [ 183] | vy  | 16  | ,sy | 64   | [ else select typewriter, write CR]             |
| [ 184] | arn | 77  |     |      | [ Prepare output of number of errors per track] |
| [ 185] | hs  | 203 |     |      | [ Jump to output of number of errors]           |
| [ 186] | sy  | 64  | ,hh | 50   | [ Write CR, exit]                               |

|        |     |    |     |    |   |
|--------|-----|----|-----|----|---|
| [ 187] | arn | 63 | ,gr | 66 | [ Transfers of working cells]             |
| [ 188] | arn | 64 | ,gr | 67 | [ Storing of the 3 input numbers]         |
| [ 189] | arn | 65 | ,gr | 68 |   |
| [ 190] | hr  | s1 |     |    |   |
| [ 191] | arn | 66 | ,gr | 73 | [ Storing of the 3 numbers produced by]   |
| [ 192] | arn | 67 | ,gr | 74 | [ passage of Produce random test number]  |
| [ 193] | arn | 68 | ,gr | 75 |   |
| [ 194] | hv  | 49 |     |    |   |
| [ 195] | qq  |    |     |    | [ Working cells]                          |
| [ 196] | qq  |    |     |    |   |
| [ 197] | qq  |    |     |    |   |
| [ 198] | qq  |    |     |    |   |
| [ 199] | arn | 73 | ,gr | 63 | [ Results for later use as start numbers] |
| [ 200] | arn | 74 | ,gr | 64 |   |
| [ 201] | arn | 75 | ,gr | 65 |   |
| [ 202] | hv  | 51 |     |    |   |

|        |     |     |     |     |   |
|--------|-----|-----|-----|-----|---|
| [ 203] | pa  | 210 |     | t4  | [ Output of number of errors]           |
| [ 204] | dk  | 215 |     |     | [ Adjustment for 5 digits]              |
| [ 205] | ar  | 214 | X   |     | [ Transform to machine number]          |
| [ 206] | mln | 213 |     |     | [ Possibly round off, exchange M and R] |
| [ 207] | tk  | 30  | ,ga | 209 | [ Prepare ]                             |
| [ 208] | sy  | 16  | V   | LZ  | [ output of 1 digit]                    |
| [ 209] | sy  |     |     |     | [ If digit=0 then write 0]              |
| [ 210] | bt  | 4   |     | t-1 | [ else write digit]                     |
| [ 211] | hv  | 206 |     |     | [ Counter for output of 5 digits]       |
| [ 212] | hr  | s1  |     |     | [ Jump within 5 digits]                 |
|        |     |     |     |     | [ else exit]                            |

|        |        |  |  |  |  |
|--------|--------|--|--|--|--|
| [ 213] | 10     |  |  |  | [ Constants]                           |
| [ 214] | 1      |  |  |  |  |
| [ 215] | 100000 |  |  |  |  |
| [ 216] | qq     |  |  |  | [ 40 cells for the instruction sk 216] |

|        |      |                |  |
|--------|------|----------------|--|
| i= 256 |      |                | [ Simultaneous calculating by adder test 5]      |
| [ 256] | gr   | 309            | [ Only intended for corrections]                 |
| [ 257] | arn  | 304            | [ Entry by start of adder test]                  |
| [ 258] | gr   |                | [ Set address for floating-point overflow]       |
| [ 259] | pan  | 296            |  |
| [ 260] | arfn | 305            |  |
| [ 261] | grf  | 310            |  |
| [ 262] | arfn | 306            |  |
| [ 263] | grf  | 311            |  |
| [ 264] | arfn | 307            |  |
| [ 265] | grf  | 312            | [ Transfers of test numbers]                     |
| [ 266] | arfn | 308            | [ Adder test]                                    |
| [ 267] | grf  | 313            |  |
| [ 268] | arf  | 310            |  |
| [ 269] | mkf  | 311            |  |
| [ 270] | acf  | 312            |  |
| [ 271] | anf  | 313            |  |
| [ 272] | mlf  | 310            | X  |
| [ 273] | scf  | 311            |  |
| [ 274] | srf  | 312            |  |
| [ 275] | mtf  | 313            |  |
| [ 276] | grf  | 310            |  |
| [ 277] | snf  | 311            |  |
| [ 278] | dkf  | 312            |  |
| [ 279] | gmf  | 313            |  |
| [ 280] | dlf  | 310            |  |
| [ 281] | ar   | 310            |  |
| [ 282] | mk   | 311            |  |
| [ 283] | ac   | 312            |  |
| [ 284] | an   | 313            |  |
| [ 285] | ml   | 310            | X  |
| [ 286] | sc   | 311            |  |
| [ 287] | sr   | 312            |  |
| [ 288] | tl   | -1             |  |
| [ 289] | hk   | 60             | NKB [ Jump to drum test if transfer is finished] |
| [ 290] | mt   | 313            |  |
| [ 291] | gr   | 310            |  |
| [ 292] | sn   | 311            |  |
| [ 293] | dk   | 312            |  |
| [ 294] | gm   | 313            |  |
| [ 295] | dl   | 310            |  |
| [ 296] | bt   | 1              | t1 [ Counter for 512 passages]                   |
| [ 297] | hv   | 268            | [ Jump back within 512 passages]                 |
| [ 298] | sr   | 309            | ,ck [ else subtract result]                      |
| [ 299] | sy   | 1              | LZ [ Write ,1, if adder is ok]                   |
| [ 300] | hv   | 259            | LZ [ Jump to new test if adder is ok]            |
| [ 301] | zq   |                | LKA [ Stop if adder error/AKA=1]                 |
| [ 302] | sy   | 3              | [ Write ,3, if adder error]                      |
| [ 303] | hv   | 259            | [ Jump to new test]                              |
| [ 304] | hv   | 269            |  |
| [ 305] |      | 1234567890     | [ Test number]                                   |
| [ 306] |      | 2345678901     |  |
| [ 307] |      | 3456789012     |  |
| [ 308] |      | 4567890123     |  |
| [ 309] |      | 275/446/57/624 | [ Result of adder test]                          |
| [ 310] |      | 0              |  |
| [ 311] |      | 0              |  |
| [ 312] |      | 0              |  |
| [ 313] |      | 0              |  |
| [ 314] |      | 0              | [ 40 cells for the instruction lk 314]           |

[Test Program No. 14. Reader Test. 15/1-1965.]

-----

The program is to be used with an infinite 8-hole punched paper tape containing sets of characters with odd parity and values ranging from 0-127. Between each set of 128 characters there is about 1 inch of blank tape. Such tapes can be produced with Test Program A 206.

Input of the test tape should be started with blank tape and the program stops in case of error. When the START button is pressed, the program proceeds with the next character.

In case of error the character read is to be found in the R register and the character which it ought to have been in the p register. The p register can be altered manually during error stop. ]

```
i=41
zq   LKB           ; stop if KB
zq   NKB           ; stop if not KB
vy                   ; choose reader
pm 127 D           ; set mask for bits 3-9
pp 1023            ; set first character to -1
lyn r-4, pp p+1    ; read, add 1 to p
cm p D             ; compare
zq                   ; error stop
hv r-3             ; jump
e41
-
```

Should it be impossible to input the test program by means of the reader, it can be done manually from the console by insertion of the following in cells 0-3:

```
[0] lyn 2, pp p+1; bits No. 8,19-22,24,25,31-35,38-40
[1] cm p D       ; bits No. 20,24,25,28,29,32
[2] zq           ; bit No. 25
[3] hv           ; bits No. 20-22
```

Also the following must be inserted in the registers:

```
by = 0
M = 127x9-9; bits No. 3-9
p = 1023 ; bits No. 0-9
```

The test is started by a jump to cell No. 0 and the test is performed as described above.

TEST B-25  
GIER-DISK  
RIALTO 3/6/66  
JFM

## PROGRAM FOR TEST OF THE DISKFILE

### GENERAL

The program occupies cells 41-501 of the core store, and use cells 640-959 and 980-1199 during the run. The program is published in a condensed version (a B-tape) to be read by the track 0 readprogram. The program starts in cell 41 with the instruction zq LKB.

### FUNCTIONS

After reading in some questions are typed on the console typewriter. The answers will define the run-path of the program. It is possible to select between writing with stop after writing or reading only. In this way one read and test a diskkit written days ago. If KA is set to 1 during the read cycle the reading will continue until KA is set to zero again. One can select whether one want to write the tracknumbers (by tracknumbers I shall understand the AneLex tracknumbers in the range from 0 to 99) on the tracks, or one can write and test with a bitpattern inserted in the R-register positions 0-41. After a writecycle with bitpattern, the pattern will be typed out (use paper in A4-horizontal format). The information (tracknumbers or bitpattern) will be written in all words of all tracks on the file. There is two different ways of selecting tracks for writing or reading. The first one is called the normal way. In this the tracknumbers are increased by one from 0 to 99. The second, called the modular way, select tracks in the following manner, always starting with 0:

0-99-1-98-2- . . . -50

Using this method of trackselection the arms will be moved over several tracks.

### USE OF KA AND KB

The setting of KA and KB will have the following effects:

|      |   |
|------|---|
| KA=0 | : Normal read-write cycle   |
| KA=1 | : After one read cycle the reading is repeated  |
| KB=0 | : Normal track selection during reading and writing   |
| KB=1 | : The first 32 sectors of track 0 are <u>not</u> tested (these sectors are normally locked for writing) |

### PRINTING OF ERRORS

When an error has been found during the check reading, an errormessage will be typed. It will be in one of the following two formats:

- 1) In the addressing mode:

|   |         |
|---|---------|
| w <written tracknumber><head number><sector number> | (black) |
| r <read tracknumber> <tensgroup>                    | (red )  |
| w <written flagbits>                                | (black) |
| r <read flagbits>                                   | (red )  |
- 2) In the bitpattern mode:

|   |         |
|---|---------|
| w <written bitpattern> <head number><sector number> | (black) |
| r <read bitpattern> <tensgroup> <tracknumber>       | (red )  |
| w <written flagbits>                                | (black) |
| r <read flagbits>                                   | (red )  |

If no error has been detected during the read cycle the message <no errors> will be typed.

[Test Program No. A 206.

Production of Tape for Reader Test No. 14. 15/1-1965.

-----

Punches characters with the values 0-127 and stops. When the START button is pushed, the program is repeated. ]

|                |                                 |
|----------------|---------------------------------|
| i = 10         |                                 |
| vy 32          | ; choose punch                  |
| pa r1 t 1023   | ; set first character to -1     |
| sy t 1         | ; print character +1            |
| bs (r-1) t 126 | ; next order if 127             |
| zq             | ; stop, jump to first character |
| hv r-3         | ; jump to next character        |
| e10            |                                 |
| <u>  </u>      |                                 |

TEST A-209  
Diskfile on Buffer  
RIALTO 21/6/66  
JFM

Addressing test for diskfile connected to the buffer store.

The program writes the tracknumbers in position 39 of all words in all blocks on the file. The blocklength is normally 400 words (i.e. max. blocklength), but can be changed by a redefinition during reading of the programtape. After reading of a few lines the reading stops and one can type:

d d30 = <wanted blocklength>  
I

After reading in and typing of filename etc. the program starts. During run KA=0 will give rewriting after one checkcycle, and KA=1 will give rereading.

#### PRINTING OF ERRORS

If an error is detected the following line will be typed, one line per word with error:

+ <correct tracknumber>-<tracknumber from file> w <wordnumber in block>

Jan Flemming Madsen

TEST A-210  
Diskfile on Buffer  
RIALTO 21/6/66  
JFM

#### TB-TEST OF DISKFILE ON BUFFER

The program writes specified bitpatterns on the file and checks the written information. The area to be tested is specified by the user.

The program occupies cells 41-281 of the core store and use cells 622-1022 during running. The first instruction to be executed after reading in the program is zq LKB.

#### RUNNING

After start the program ask for the filename (0, 1, 2 or 3). Then the users types the wanted blocklength (in the range from 0 to 400). At last the starttrack and endtrack is typed. The condition for acceptance of the typed values for these are:

$$0 < \text{first track} < \text{last track} < 1199$$

After this the wanted bitpattern is inserted in the R-register positions 0-41 and the NORMAL START button is depressed. Now the bitpattern given will be written on the given area and checked. After checking, the reading will continue if KA=1. If KA=0 and KB=1 the program will rewrite the same area. If both KA and KB is zero the program jump to the startsituation.

#### ERRORSTOP

When errors is detected the machine stop with the r1-register set to either 162 or 165.

- 1) r1=162, INFORMATION ERROR  
The correct bitpattern is in the M-register,  
the wrong in the R-register.
- 2) r1=165, ERROR IN FLAGBITS  
The correct marks are in R position 8 and 9,  
the wrong marks are in the In-register positions RA and RB.

If a parity error is found the program tries to read the track in question two times more. If this still fails a <p> is typed and the test continue with the next track.

Jan Flemming Madsen

TEST A-211  
Diskfile on Buffer  
RIALTO 21/6/66  
JFM

FAST INFORMATIONTEST OF DISKFILE ON BUFFER

The program writes some, more or less, random numbers on the entire file and check this information. The check is performed as a sumcheck, and the program types 'sum-error' in red whenever this summation fails. At the start-point the filename (0, 1, 2 or 3) should be typed.

Jan Flemming Madsen



TEST 212a  
GIER-DISK  
RIALTO 20/6/66  
JFM

#### TEST OF THE ARM MOVING

The program occupies cells 41-63 of the core store.

#### METHOD

The program READS the entire diskkit sector by sector. The sectors to be read are selected in the following manner:

|             |       |     |        |     |
|-------------|-------|-----|--------|-----|
| 1.          | track | 0,  | sector | 0   |
| 2.          | -     | 99, | -      | 959 |
| 3.          | -     | 0,  | -      | 1   |
| etc. up to: |       |     |        |     |
| 9599.       | -     | 99, | -      | 959 |
| 9600.       | -     | 0,  | -      | 0   |

After reading the program select sector 0 of the SLIP system and jump to the first instruction. Depending on the information on the given diskkit, the program will end with one of the messages:

hp-knap xx  
algol  
SUM-ALGOL  
FEJL

Jan Flemming Madsen

Beschreibung vom Programm Roots, das beim Übernahmetest von GIER  
angewendet wird.

Das Programm testet die Prozedur Roots, die sämtliche Komplexwurzeln in einem n'ten Grad Polynom  $P_n(z)$  mit Komplexkoeffizienten findet.

Das geschieht, indem man Nullstellen für  $F(x,y) = |P_n(x + i y)|^2$  mit Hilfe einer Gradientenmethode sucht.

Das Testprogramm, das ein ALGOL Programm ist, wird eingelesen und übersetzt, darauf werden die n (n=75) komplexen Zahlen, die nach dem Programm auf demselben Streifen stehen, eingelesen.

Das Programm generiert nun die Koeffizienten in diesem Polynom, welches diese Zahlen als Wurzel hat und wendet diese Koeffizienten als Parameter für Roots an. Die Lösung kommt als Ausgabe auf den Lochstreifenlocher.

Danach beginnt automatisch das Aufsuchen der Wurzeln im gleichen Polynom, und die Wurzeln von jedem Durchlauf können nun verglichen werden. Ein Durchlauf dauert etwa 40 Minuten.

Will man untersuchen, wie weit die Maschine in einem Durchlauf gekommen ist, drückt man K B und jedesmal wenn die Maschine eine Wurzel gefunden hat, wird sie - solange K B gedrückt ist - schreiben, wieviele Wurzeln noch zu finden sind.

Ved ny hjælp (hjælp 3) skal strukturen startes efter de header.

| Tid<br>celle | Før start     | 1. ord indlæst<br>og lagret | 2. ord indlæst<br>og lagret | 3. ord indlæst<br>og lagret | 4. ord indlæst<br>og lagret |
|--------------|---------------|-----------------------------|-----------------------------|-----------------------------|-----------------------------|
| 34           | pm n 64 DXIZA | pm n 64 DXIZA               | pm n 64 DXIZA               | pm n 64 DXIZA               | pm n 64 DXIZA               |
| 35           | tl -7, ly r+1 | tl -7, ly r+1               | tl -7, ly r+1               | tl -7, ly r+1               | tl -7, ly r+1               |
| 36           | pl 0 LZA t508 | pl 0 LZA t508               | pl 0 LZA t508               | pl 0 LZA t508               | pl 0 LZA t508               |
| 37           | xr 0 XIZB     | xr 0 XIZB                   | xr 0 XIZB                   | xr 0 XIZB                   | xr 0 XIZB                   |
| 38           | hv 35 LZB     | hv 35 LZB                   | hv 35 LZB                   | hv 35 LZB                   | hv 35 LZB                   |
| 39           | gr 41 MRC t-1 | gr 40 MRC t-1               | gr 42 MRC t-1               | gr 41 MRC t-1               | gr 40 MRC t-1               |
| 40           |               | hv 34                       | hv 34                       | hv 34                       | gr 46 MRC t-2               |
| 41           |               |                             |                             | hv 34                       | hv 34                       |
| 42           |               |                             |                             |                             |                             |
| 43           |               |                             |                             |                             |                             |
| 44           |               |                             |                             |                             |                             |
| 45           |               |                             |                             |                             |                             |
| 46           |               |                             |                             |                             |                             |

| Tid<br>celle | 4. ord indlæst<br>og lagret | 5. ord indlæst<br>og lagret | 5. ord indlæst<br>og lagret | 6. ord indlæst<br>og lagret | Sidste ord indlæst<br>og lagret |
|--------------|-----------------------------|-----------------------------|-----------------------------|-----------------------------|---------------------------------|
| 34           | pm n 64 DXIZA               | pm n 64 DXIZA               | pm n 64 DXIZA               | pm n 64 DXIZA               |                                 |
| 35           | tl -7, ly r+1               | tl -7, ly r+1               | tl -7, ly r+1               | tl -7, ly r+1               |                                 |
| 36           | pl 0 LZA t508               | pl 0 LZA t508               | pl 0 LZA t508               | pl 0 LZA t508               |                                 |
| 37           | xr 0 XIZB                   | xr 0 XIZB                   | xr 0 XIZB                   | xr 0 XIZB                   |                                 |
| 38           | hv 35 LZB                   | hv 35 LZB                   | hv 35 LZB                   | hv 35 LZB                   |                                 |
| 39           | gr 40 MRC t-1               | gr 44 MRC t-2               | gr 42 MRC t-2               | gr 41 MRC t-1               |                                 |
| 40           | gr 44 MRC t-2               | gr 34                       | gr 34                       | gr 34                       |                                 |
| 41           | hv 34                       | gr 46 MRC t-2               | gr 46 MRC t-2               | gr 46 MRC t-2               |                                 |
| 42           |                             |                             |                             |                             |                                 |
| 43           |                             |                             |                             |                             |                                 |
| 44           |                             |                             |                             |                             |                                 |
| 45           |                             |                             |                             |                             |                                 |
| 46           |                             |                             |                             |                             |                                 |

REGNECENTRALEN  
Dansk Institut for  
Matematikmaskiner

Tegnet 10.8.63.  
Kontrol  
Godk.

Startprocedure ved  
indlæsning med kanal 0  
Bl. Hjælp

| DECIMAL | OPE. | EINARY VALUE<br>20 21 22 23 24 25 |   |   |   |   |   | OPE. | DECIMAL | BINARY VALUE<br>20 21 22 23 24 25 |   |   |   |   |   |
|---------|------|-----------------------------------|---|---|---|---|---|------|---------|-----------------------------------|---|---|---|---|---|
| 0       | qq   | .                                 | . | . | . | . | . | ab   | 9       | .                                 | . | 1 | . | . | 1 |
| 1       | zq   | .                                 | . | . | . | . | 1 | ac   | 6       | .                                 | . | . | 1 | 1 | . |
| 2       | ar   | .                                 | . | . | . | 1 | . | an   | 4       | .                                 | . | . | 1 | . | . |
| 3       | sr   | .                                 | . | . | . | 1 | 1 | ar   | 2       | .                                 | . | . | . | 1 | . |
| 4       | an   | .                                 | . | . | 1 | . | . | bs   | 49      | 1                                 | 1 | . | . | . | 1 |
| 5       | sn   | .                                 | . | . | 1 | . | 1 | bt   | 39      | 1                                 | . | . | 1 | 1 | 1 |
| 6       | ac   | .                                 | . | . | 1 | 1 | . | ca   | 25      | .                                 | 1 | 1 | . | . | 1 |
| 7       | sc   | .                                 | . | . | 1 | 1 | 1 | ck   | 19      | .                                 | 1 | . | . | 1 | 1 |
| 8       | mb   | .                                 | . | 1 | . | . | . | cl   | 20      | .                                 | 1 | . | 1 | . | . |
| 9       | ab   | .                                 | . | 1 | . | . | 1 | cm   | 38      | 1                                 | . | . | 1 | 1 | . |
| 10      | mt   | .                                 | . | 1 | . | 1 | . | dk   | 13      | .                                 | . | 1 | 1 | . | 1 |
| 11      | mk   | .                                 | . | 1 | . | 1 | 1 | dl   | 14      | .                                 | . | 1 | 1 | 1 | . |
| 12      | ml   | .                                 | . | 1 | 1 | . | . | ga   | 22      | .                                 | 1 | . | 1 | 1 | . |
| 13      | dk   | .                                 | . | 1 | 1 | . | 1 | gc   | 47      | 1                                 | . | 1 | 1 | 1 | 1 |
| 14      | dl   | .                                 | . | 1 | 1 | 1 | . | gg   | 46      | 1                                 | . | 1 | 1 | 1 | . |
| 15      | nk   | .                                 | . | 1 | 1 | 1 | 1 | gi   | 29      | .                                 | 1 | 1 | 1 | . | 1 |
| 16      | nl   | .                                 | 1 | . | . | . | . | gk   | 54      | 1                                 | 1 | . | 1 | 1 | . |
| 17      | hr   | .                                 | 1 | . | . | . | 1 | gm   | 26      | .                                 | 1 | 1 | . | 1 | . |
| 18      | tl   | .                                 | 1 | . | . | 1 | . | gp   | 42      | 1                                 | . | 1 | . | 1 | . |
| 19      | ck   | .                                 | 1 | . | . | 1 | 1 | gr   | 21      | .                                 | 1 | . | 1 | . | 1 |
| 20      | cl   | .                                 | 1 | . | 1 | . | . | gs   | 61      | 1                                 | 1 | 1 | 1 | . | 1 |
| 21      | gr   | .                                 | 1 | . | 1 | . | 1 | gt   | 23      | .                                 | 1 | . | 1 | 1 | 1 |
| 22      | ga   | .                                 | 1 | . | 1 | 1 | . | hh   | 60      | 1                                 | 1 | 1 | 1 | . | . |
| 23      | gt   | .                                 | 1 | . | 1 | 1 | 1 | hk   | 34      | 1                                 | . | . | . | 1 | . |
| 24      | tk   | .                                 | 1 | 1 | . | . | . | hr   | 17      | .                                 | 1 | . | . | . | 1 |
| 25      | ca   | .                                 | 1 | 1 | . | . | 1 | hs   | 50      | 1                                 | 1 | . | . | 1 | . |
| 26      | gm   | .                                 | 1 | 1 | . | 1 | . | hv   | 56      | 1                                 | 1 | 1 | . | . | . |
| 27      | pm   | .                                 | 1 | 1 | . | 1 | 1 | il   | 44      | 1                                 | . | 1 | 1 | . | . |
| 28      | xr   | .                                 | 1 | 1 | 1 | . | . | is   | 36      | 1                                 | . | . | 1 | . | . |
| 29      | gi   | .                                 | 1 | 1 | 1 | . | 1 | it   | 37      | 1                                 | . | . | 1 | . | 1 |
| 30      | ps   | .                                 | 1 | 1 | 1 | 1 | . | lk   | 52      | 1                                 | 1 | . | 1 | . | . |
| 31      | pp   | .                                 | 1 | 1 | 1 | 1 | 1 | ly   | 59      | 1                                 | 1 | 1 | . | 1 | 1 |
| 32      | pa   | 1                                 | . | . | . | . | . | mb   | 8       | .                                 | . | 1 | . | . | . |
| 33      | pt   | 1                                 | . | . | . | . | 1 | mk   | 11      | .                                 | . | 1 | . | 1 | 1 |
| 34      | hk   | 1                                 | . | . | . | 1 | . | ml   | 12      | .                                 | . | 1 | 1 | . | . |
| 35      | pi   | 1                                 | . | . | . | 1 | 1 | mt   | 10      | .                                 | . | 1 | . | 1 | . |
| 36      | is   | 1                                 | . | . | 1 | . | . | nc   | 43      | 1                                 | . | 1 | . | 1 | 1 |
| 37      | it   | 1                                 | . | . | 1 | . | 1 | nk   | 15      | .                                 | . | 1 | 1 | 1 | 1 |
| 38      | cm   | 1                                 | . | . | 1 | 1 | . | nl   | 16      | .                                 | 1 | . | . | . | . |
| 39      | bt   | 1                                 | . | . | 1 | 1 | 1 | ns   | 40      | 1                                 | . | 1 | . | . | . |
| 40      | ns   | 1                                 | . | 1 | . | . | . | nt   | 41      | 1                                 | . | 1 | . | . | 1 |
| 41      | nt   | 1                                 | . | 1 | . | . | 1 | pa   | 32      | 1                                 | . | . | . | . | . |
| 42      | gp   | 1                                 | . | 1 | . | 1 | . | pc   | 48      | 1                                 | 1 | . | . | . | . |
| 43      | nc   | 1                                 | . | 1 | . | 1 | 1 | pi   | 35      | 1                                 | . | . | . | 1 | 1 |
| 44      | il   | 1                                 | . | 1 | 1 | . | . | pm   | 27      | .                                 | 1 | 1 | . | 1 | 1 |
| 45      | us   | 1                                 | . | 1 | 1 | . | 1 | pp   | 31      | .                                 | 1 | 1 | 1 | 1 | 1 |
| 46      | gg   | 1                                 | . | 1 | 1 | 1 | . | ps   | 30      | .                                 | 1 | 1 | 1 | 1 | . |
| 47      | gc   | 1                                 | . | 1 | 1 | 1 | 1 | pt   | 33      | 1                                 | . | . | . | . | 1 |
| 48      | pc   | 1                                 | 1 | . | . | . | . | qq   | 0       | .                                 | . | . | . | . | . |
| 49      | bs   | 1                                 | 1 | . | . | . | 1 | sc   | 7       | .                                 | . | . | 1 | 1 | 1 |
| 50      | hs   | 1                                 | 1 | . | . | 1 | . | sk   | 53      | 1                                 | 1 | . | 1 | . | 1 |
| 51      | vy   | 1                                 | 1 | . | . | 1 | 1 | sn   | 5       | .                                 | . | . | 1 | . | 1 |
| 52      | lk   | 1                                 | 1 | . | 1 | . | . | sr   | 3       | .                                 | . | . | . | 1 | 1 |
| 53      | sk   | 1                                 | 1 | . | 1 | . | 1 | sy   | 58      | 1                                 | 1 | 1 | . | 1 | . |
| 54      | gk   | 1                                 | 1 | . | 1 | 1 | . | tk   | 24      | .                                 | 1 | 1 | . | . | . |
| 55      | vk   | 1                                 | 1 | . | 1 | 1 | 1 | tl   | 18      | .                                 | 1 | . | . | 1 | . |
| 56      | hv   | 1                                 | 1 | 1 | . | . | . | ud   | 63      | 1                                 | 1 | 1 | 1 | 1 | 1 |
| 57      | zj   | 1                                 | 1 | 1 | . | . | 1 | us   | 45      | 1                                 | . | 1 | 1 | . | 1 |
| 58      | sy   | 1                                 | 1 | 1 | . | 1 | . | vk   | 55      | 1                                 | 1 | . | 1 | 1 | 1 |
| 59      | ly   | 1                                 | 1 | 1 | . | 1 | 1 | vy   | 51      | 1                                 | 1 | . | . | 1 | 1 |
| 60      | hh   | 1                                 | 1 | 1 | 1 | . | . | xr   | 28      | .                                 | 1 | 1 | 1 | . | . |
| 61      | gs   | 1                                 | 1 | 1 | 1 | . | 1 | zj   | 57      | 1                                 | 1 | 1 | . | . | 1 |
| 62      | zl   | 1                                 | 1 | 1 | 1 | 1 | . | zl   | 62      | 1                                 | 1 | 1 | 1 | 1 | . |
| 63      | ud   | 1                                 | 1 | 1 | 1 | 1 | 1 | zq   | 1       | .                                 | . | . | . | . | 1 |

apr 67  
jfm

TABLE OF INDICATORPARTS  
(inactive are marked with an x)

| 33 | 34 | 35 | 36 | 37 | 38 | 39 |       | 33 | 34 | 35 | 36 | 37 | 38 | 39 |      |
|----|----|----|----|----|----|----|-------|----|----|----|----|----|----|----|------|
| .  | .  | .  | .  | .  | .  | .  | I x   | 1  | .  | .  | .  | .  | .  | .  | N x  |
| .  | .  | .  | .  | .  | .  | 1  | IB x  | 1  | .  | .  | .  | .  | .  | 1  | NB   |
| .  | .  | .  | .  | .  | .  | 1  | IA x  | 1  | .  | .  | .  | .  | 1  | .  | NA   |
| .  | .  | .  | .  | .  | .  | 1  | IC x  | 1  | .  | .  | .  | .  | 1  | 1  | NC   |
| .  | .  | .  | .  | 1  | .  | .  | IK    | 1  | .  | .  | .  | 1  | .  | .  | NK x |
| .  | .  | .  | .  | 1  | .  | 1  | IKB   | 1  | .  | .  | .  | 1  | .  | 1  | NKB  |
| .  | .  | .  | .  | 1  | .  | 1  | IKA   | 1  | .  | .  | .  | 1  | 1  | .  | NKA  |
| .  | .  | .  | .  | 1  | 1  | 1  | IKC   | 1  | .  | .  | .  | 1  | 1  | 1  | NKC  |
| .  | .  | .  | 1  | .  | .  | .  | IZ x  | 1  | .  | .  | 1  | .  | .  | .  | NZ   |
| .  | .  | .  | 1  | .  | .  | 1  | IZB   | 1  | .  | .  | 1  | .  | .  | 1  | NZB  |
| .  | .  | .  | 1  | .  | .  | 1  | IZA   | 1  | .  | .  | 1  | .  | 1  | .  | NZA  |
| .  | .  | .  | 1  | .  | 1  | 1  | IZC   | 1  | .  | .  | 1  | .  | 1  | 1  | NZC  |
| .  | .  | .  | 1  | 1  | .  | .  | IO x  | 1  | .  | .  | 1  | 1  | .  | .  | NO   |
| .  | .  | .  | 1  | 1  | .  | 1  | IOB   | 1  | .  | .  | 1  | 1  | .  | 1  | NOB  |
| .  | .  | .  | 1  | 1  | 1  | 1  | IOA   | 1  | .  | .  | 1  | 1  | 1  | .  | NOA  |
| .  | .  | .  | 1  | 1  | 1  | 1  | IOC   | 1  | .  | .  | 1  | 1  | 1  | 1  | NOC  |
| .  | .  | 1  | .  | .  | .  | .  | IT x  | 1  | .  | 1  | .  | .  | .  | .  | NT   |
| .  | .  | 1  | .  | .  | .  | 1  | ITB   | 1  | .  | 1  | .  | .  | .  | 1  | NTB  |
| .  | .  | 1  | .  | .  | .  | 1  | ITA   | 1  | .  | 1  | .  | .  | 1  | .  | NTA  |
| .  | .  | 1  | .  | .  | 1  | 1  | ITC   | 1  | .  | 1  | .  | .  | 1  | 1  | NTC  |
| .  | .  | 1  | .  | 1  | .  | .  | IP x  | 1  | .  | 1  | .  | 1  | .  | .  | NP x |
| .  | .  | 1  | .  | 1  | .  | 1  | IPB   | 1  | .  | 1  | .  | 1  | .  | 1  | NPB  |
| .  | .  | 1  | .  | 1  | 1  | 1  | IPA   | 1  | .  | 1  | .  | 1  | 1  | .  | NPA  |
| .  | .  | 1  | .  | 1  | 1  | 1  | IPC   | 1  | .  | 1  | .  | 1  | 1  | 1  | NPC  |
| .  | .  | 1  | 1  | .  | .  | .  | IQ x  | 1  | .  | 1  | 1  | .  | .  | .  | NQ x |
| .  | .  | 1  | 1  | .  | .  | 1  | IQB   | 1  | .  | 1  | 1  | .  | .  | 1  | NQB  |
| .  | .  | 1  | 1  | .  | 1  | .  | IQA   | 1  | .  | 1  | 1  | .  | 1  | .  | NQA  |
| .  | .  | 1  | 1  | .  | 1  | 1  | IQC   | 1  | .  | 1  | 1  | .  | 1  | 1  | NQC  |
| .  | .  | 1  | 1  | 1  | .  | .  | IR x  | 1  | .  | 1  | 1  | 1  | .  | .  | NR x |
| .  | .  | 1  | 1  | 1  | .  | 1  | IRB   | 1  | .  | 1  | 1  | 1  | .  | 1  | NRB  |
| .  | .  | 1  | 1  | 1  | 1  | .  | IRA   | 1  | .  | 1  | 1  | 1  | 1  | .  | NRA  |
| .  | .  | 1  | 1  | 1  | 1  | 1  | IRC   | 1  | .  | 1  | 1  | 1  | 1  | 1  | NRC  |
| .  | 1  | .  | .  | .  | .  | .  | M     | 1  | 1  | .  | .  | .  | .  | .  | L x  |
| .  | 1  | .  | .  | .  | .  | 1  | MB    | 1  | 1  | .  | .  | .  | .  | 1  | LB   |
| .  | 1  | .  | .  | .  | .  | 1  | MA    | 1  | 1  | .  | .  | .  | .  | 1  | LA   |
| .  | 1  | .  | .  | .  | .  | 1  | MC    | 1  | 1  | .  | .  | .  | .  | 1  | LC   |
| .  | 1  | .  | .  | 1  | .  | .  | MK x  | 1  | 1  | .  | .  | 1  | .  | .  | LK x |
| .  | 1  | .  | .  | 1  | .  | 1  | MKB x | 1  | 1  | .  | .  | 1  | .  | 1  | LKB  |
| .  | 1  | .  | .  | 1  | 1  | .  | MKA x | 1  | 1  | .  | .  | 1  | 1  | .  | LKA  |
| .  | 1  | .  | .  | 1  | 1  | 1  | MKC x | 1  | 1  | .  | .  | 1  | 1  | 1  | LKC  |
| .  | 1  | .  | 1  | .  | .  | .  | MZ x  | 1  | 1  | .  | 1  | .  | .  | .  | LZ   |
| .  | 1  | .  | 1  | .  | .  | 1  | MZB x | 1  | 1  | .  | 1  | .  | .  | 1  | LZB  |
| .  | 1  | .  | 1  | .  | 1  | .  | MZA x | 1  | 1  | .  | 1  | .  | 1  | .  | LZA  |
| .  | 1  | .  | 1  | .  | 1  | 1  | MZC x | 1  | 1  | .  | 1  | .  | 1  | 1  | LZC  |
| .  | 1  | .  | 1  | 1  | .  | .  | MO x  | 1  | 1  | .  | 1  | 1  | .  | .  | LO   |
| .  | 1  | .  | 1  | 1  | .  | 1  | MOB   | 1  | 1  | .  | 1  | 1  | .  | 1  | LOB  |
| .  | 1  | .  | 1  | 1  | 1  | .  | MOA   | 1  | 1  | .  | 1  | 1  | 1  | .  | LOA  |
| .  | 1  | .  | 1  | 1  | 1  | 1  | MOC   | 1  | 1  | .  | 1  | 1  | 1  | 1  | LOC  |
| .  | 1  | 1  | .  | .  | .  | .  | MT x  | 1  | 1  | 1  | .  | .  | .  | .  | LT   |
| .  | 1  | 1  | .  | .  | .  | 1  | MTB   | 1  | 1  | 1  | .  | .  | .  | 1  | LTB  |
| .  | 1  | 1  | .  | .  | 1  | .  | MTA   | 1  | 1  | 1  | .  | .  | 1  | .  | LTA  |
| .  | 1  | 1  | .  | .  | 1  | 1  | MTC   | 1  | 1  | 1  | .  | .  | 1  | 1  | LTC  |
| .  | 1  | 1  | .  | 1  | .  | .  | MP x  | 1  | 1  | 1  | .  | 1  | .  | .  | LP x |
| .  | 1  | 1  | .  | 1  | .  | 1  | MPB   | 1  | 1  | 1  | .  | 1  | .  | 1  | LPB  |
| .  | 1  | 1  | .  | 1  | 1  | .  | MPA   | 1  | 1  | 1  | .  | 1  | 1  | .  | LPA  |
| .  | 1  | 1  | .  | 1  | 1  | 1  | MPC   | 1  | 1  | 1  | .  | 1  | 1  | 1  | LPC  |
| .  | 1  | 1  | 1  | .  | .  | .  | MQ x  | 1  | 1  | 1  | 1  | .  | .  | .  | LQ x |
| .  | 1  | 1  | 1  | .  | .  | 1  | MQB   | 1  | 1  | 1  | 1  | .  | .  | 1  | LQB  |
| .  | 1  | 1  | 1  | .  | 1  | .  | MQA   | 1  | 1  | 1  | 1  | .  | 1  | .  | LQA  |
| .  | 1  | 1  | 1  | .  | 1  | 1  | MQC   | 1  | 1  | 1  | 1  | .  | 1  | 1  | LQC  |
| .  | 1  | 1  | 1  | 1  | .  | .  | MR x  | 1  | 1  | 1  | 1  | 1  | .  | .  | LR x |
| .  | 1  | 1  | 1  | 1  | .  | 1  | MRB   | 1  | 1  | 1  | 1  | 1  | .  | 1  | LRB  |
| .  | 1  | 1  | 1  | 1  | 1  | .  | MRA   | 1  | 1  | 1  | 1  | 1  | 1  | .  | LRA  |
| .  | 1  | 1  | 1  | 1  | 1  | 1  | MRC   | 1  | 1  | 1  | 1  | 1  | 1  | 1  | LRC  |

Testprograms Type C  
RIALTO, 19.8.1968  
JFM

The usual testprograms of B type can not be read by the primitive input program on track 0 in HELP 3. This paper describes how the modified tapes, called C programs, may be read by HELP 3.

### FORMAT OF C TAPES

The paper tapes containing C programs consists of a short header followed by the corresponding B program. The header can be read by HELP 3 and enables the user to read the B program.

### INPUT PROCEDURE

The header is followed by a tape gap 1" long. The reading may start before the header or in this gap. If the should be read by HJÆLP one starts in the gap, and if HELP 3 is used for reading one starts before the header. In the last case the input procedure is as follows:

- eller  $r <$  {
- (1) Read track 0 to the core store by
    - a. Pressing RESET or MICROTEMPI STOP.
    - b. Pressing HP-BUTTON while NORMAL STOP is pressed.
  - (2) Place the tape in the reader and start GIER in cell 23 by
    - a. Setting  $r1=23$
    - b.  $BY=0$
    - c. Pressing NORMAL START
  - (3) When the program types  
 $t < \text{number of program}$   
the header has been read and the remaining part of the tape (the B program) will be read immediately.
  - (4) When the B program has been read, the program in question starts running.

The actual procedure between (2) and (3) above is:

- (A) A program (in bin 0 form) containing the primitive loader of HJÆLP is read to the core store in cells 493-512 and entered.
- (B) This program types the test number and moves the loader to core 34-39.
- (C) The program jumps to core 34 and from this point the action is as if track 0 of HJÆLP has been called.

### PUNCHING OF C PROGRAMS

C programs are punched by the slip program A-224, "B to C Producer", and this program and how to use it is described in a separate paper.

Rialto, 25. april 1968  
JFM  
t15

### Test 15, Input and Output of 5 track paper tape

The program is used for test of input (from RC-2000) and output (to Facit Punch) of 5 track paper tape. The program is published as a binary paper tape, and may be loaded to the core store by the loaderprogram on track 0 for HJÆLP or HELP 3.

### Subprograms

The program may be used in four different ways. The actual subprogram is selected when the program types:

Type c for copy, t for typeout, i for inputtest, o for outputtest:

The programs which may be selected are:

- |   |          |
|---|----------|
| 1. Copying of 5 track paper tape  | (type c) |
| 2. Output of a special 5 track test tape  | (type o) |
| 3. Input and test of the tape produced<br>by program 2                                      | (type i) |
| 4. Conversion from 5 track paper tape in<br>TELEX code to typewriter output in<br>GIER code | (type t) |

The subprograms 1,2 and 4 may be stopped by setting KA=1. This causes a return to the startsituation and a new subprogram may be selected.

Test C-16

GIER-CP

Technical Center, 26.9.1968

JFM

The program is used for test of Mode 5 in GIER. Mode 5 is executed whenever the HP-button is pressed. The program is published as a B-C program only.

#### Method

After start (in Core[41]) the following happens:

1. Track 0 is saved in the core store during the test. Core[128:167]:=Track[0];
2. A special track 0 (part of the program) is written.
3. Track 38 is destroyed with special information.
4. The instructions  
[512] vy        0, vk        87  
[513] hv        512  
are moved to Core[512:513] and entered.

The program will now loop in 512 and 513 until the HP-button is pressed. When this happens the following test sequence is executed:

1. Core[0:39] is stored on track 38 (by Mode 5)
2. Track 0 is read to the core store  
( Core[0:39]:=Track[0]). (by Mode 5)
3. The instruction counter CT (r1) is stored in the address part of Core[0] and the remaining bits cleared. (by Mode 5);
4. Core[1] is enterdd in either righth halfword or in left halfword. The entry depends on the state of the h-bit when HP was pressed. (by Mode 5);
5. Now the functions 1-4 above are checked by the program on track 0.
6. A jump to the instructions in Core[512:513] is performed and the test continue.

In case of errors, messages are given on the typewriter.



### Use of KA, KB

KB=1                   The program stops in Core[41] when the tape has been read.

KA=0                   The normal state of KA during the test.

KA=1                   After press on HP-button and the following test, the old track 0 is reestablished. One more press on HP will then activate the normal function of track 0 and the test is finished.

### Error Messages

The following five messages are possible during the test, and the meaning is considered evident:

1. wrong tk stored
2. wrong rl stored
3. -entry in Core[1]
4. Core[0:39] not stored on track 38
5. track 0 not transferred to core store

```
;slip<
;Test of HP function and mode 5, 1.8.68.4
```

```
b i=h1, a10
```

```
[Core part of test,executed after track 0]
```

```

      zq          LKB          ; if kbon then STOP
vy      512, grn      -1 ; set HP-inhibit; sum:=0;
pa      a7      t      207 ; setsum of track 38:
pa      a8      t      30 ;
a7:    arn      207      t      1 ;
ar      1.8      DLA          ; include marks in sum
ar      1.9      DLB          ;
sc      -1          ; sum:=sum-R;
a8:    bt      30      t      -1 ;
hv      a7          ;
pm      -1, gm      228 ;
vk      0      lk      128 ; save present track 0 in core;
sk      168, vk      38 ; set new track zero;
sk      208, lk      0 ;
sk      288, vk      0 ; noise to track 38 after setting core;
pm      a9, arn      a10 ;
gm      512      MA          ; set fixed program in core;
gr      513      M          ; program used for interrupt by HP;
hv      512          ; goto program;
```

```

a9:
[512] vy      0, vk      87 ; release HP-inhibit; set tk to 87;
a10:
[513] hv      512          ; goto Core[512];
```

```

a1:    gr      a12          ; saveR:=R; error in tk:
hs      a11          ; writetext(<<
qq      a13          ; wrong tk stored>);
arn      a12, hr      s1 ; R:=saveR; return;
```

```

a2:    gr      a12          ; saveR:=R; error in OT:
hs      a11          ; writetext(<<
qq      a14          ; wrong r1 stored>);
arn      a12, hr      s1 ; R:=saveR; return;
```

```

a3:    hs      a11          ; improper entry to track 0: writetext(<<
qq      a15          ; -entry in Core[1]>);
hr      s1          ; return;
```

```

a6:    hs      a11          ; error track 38: writetext(<<
qq      a16          ; Core[0:39] not stored on track 38>);
hr      s1          ; return;
```

```

a13:    k6h 58twrong tk stored;58.
a14:    k6h 58twrong r1 stored;58.
a15:    k6h 58t-entry in Core[1];58.
a16:    k6h 58tCore[0:39] not stored on track 38;58.
```

```

a11: [textprint of HELP 3]
      gs    r5, an    s ;
      is    s1  MA    ;
      ps    (s), arn   r-2 ;
      pm    s, ps    s1 ;
      cl    -6, ca    10.5 ;
      ps    -1, hr    s1 ; return;
      ca    15.5, hh   r-h ;
      tk    -h, ga    r2 ;
      ca    63, it    1 ;
      sy    0, hvm    r-5 ;

a12: qq    0, qq    0 ; saveR;

```

d i=168

[New track 0 replacing the existing in the machine.  
Handles and checks all actions taken by the HP-button  
and mode 5]

```

[ 0] qq    0, t    517 ; used for save OT;
      it    311, pt    0 ; normal entry: set bits(10-19) of Core[0];
      gk    -1, arn   -1 ; save by and tk; Rcount:=tk;
      vy    529, tk    10 ; set HP-inhibit;
      nc    87, hs    a1 ; if tk≠87 then call error;
      arn    0,      ; R:=Core[0];
      ca    512, hv    ra17 ;
      ca    513, hv    ra17 ;
      ca    1, hv    ra17 ;
      ca    2, hv    ra17 ;
      ca    3, hv    ra17 ;
      hs    a2,      ;
a17: tk    10,      ;
      nc    311, ca    0 ;
      hv    ra18,      ;
      hs    a3,      ;
a18: vk    38, lk    288 ; read stored track 38 to core;
      vk    38, grn   -2 ; sum:=0;
      pa    ra4, t    287 ; setsum of track 38 in core[-2];
      pa    ra5, t    39 ;
a19: arn    287, t    1 ;
      ar    1.8, DLA   ;
      ar    1.9, DLB   ;
[20] sc    -2,      ;
a5: bt    30, t    -1 ;
      hv    ra4,      ;
      arn    -2,      ; R:=computed sum;
      hv    ra19, NZ    ; if R ≠ 0 then call error;
a20:
[27] sk    208, lk    0 ; switch to new track 38;
[28] hk    r1, hv    r ;
a19: arn    289, nc    311 ;
      hs    a6,      ;
      hv    ra20,      ;
      qq,      ;
      qq,      ;
      qq,      ;
      qq,      ;
[30] prn    1.3, DXIZA ; Primitive input of HELP:
      tl    -7, ly    r1 ;
      pi    0, IZA t508 ;
      xr    0, XIZB ;
      hv    35, IZB ;
[39] gr    h1, MRC t-1 ;

```

d i=208

[Core 0:39 during the test. Stored on track 38 after HP.  
The storing is performed by mode 5.]

```

[ 0] qq          ;
    vy 520, sy 6h ; writetext(
    sy 58, sy 19 ; track 0 not transferred to core store);
    sy h1, sy h9 ;
    sy 51, sy 3h ;
    sy 0, sy 16 ;
    sy 0, sy 37 ;
    sy 38, sy 19 ;
    sy 0, sy 19 ;
    sy h1, sy h9 ;
[10] sy 37, sy 18 ;
    sy 5h, sy 53 ;
    sy h1, sy h1 ;
    sy 53, sy 52 ;
    hv 26 ;
    qq ;
    qq ;
    qq ;
    qq ;
    qq ;
    qq ;
    qq ;
    qq ;
    qq ;
[20] qq ; sumbalance for track;
    qq ;
    qq ;
    qq ;
    qq ;
    qq ;
    qq ;
    qq ;
[28] hk r1, hv r ; wait for transfer from drum;
    vk 38, sk 288 ; noise to track 38;
    hv 512, MKA ; if - kaon then exit to core;
    vk 0, sk 128 ; regenerate track 0 of machine;
[30] vk 0, hv 512 ; exit to core;
    qq ;
[3h] prn 1.3, DNIZA ; Primitive input of HJMLP:
    tl -7, ly r1 ;
    pi 0, LZA t508 ;
    xr 0, XIZE ;
    hv 35, LZB ;
[39] gr h1, MRC t-1 ;

```

s  
eh1

```

25 1.8.68 849
start_image<
exit, 10<
p26 1.8.68 e11
r<

```

```

1
201 11 218 300
a1 62
a2 66
a3 70
a4 188
a5 102
a6 73
a7 115
a8 119
a9 60
a10 61
a11 95
a12 105
a13 76
a14 79
a15 82
a16 87
a17 180
a18 181
a19 198
a20 196

```

```

27 1.8.68 e42
binout, 0, 11, 512<
print, p11..75, t76..91, p95..105, p168..217<

```

41. zq  
 42. vy 512  
 43. pa 45  
 44. pa 49  
 45. arm 207  
 46. ar 2  
 47. ar 1  
 48. gc -1  
 49. bt 30  
 50. hv 45  
 51. pm -1  
 52. vk  
 53. sk 168  
 54. sk 208  
 55. sk 288  
 56. pm 60  
 57. gm 512  
 58. gr 513  
 59. hv 512  
 60. vy  
 61. hv 512  
 62. gr 105  
 63. hs 95  
 64. qd 76  
 65. arm 105  
 66. gr 105  
 67. hs 95  
 68. qd 79  
 69. arm 105  
 70. hs 95  
 71. qd 82  
 72. hr s1  
 73. hs 95  
 74. qd 87  
 75. hr s1

LKB  
 ,gm -1  
 t207  
 t39  
 t1

D LA  
 D LB

t-1

,gm 228  
 ,lk 128  
 ,vk 38  
 ,lk  
 ,vk  
 ,arm 61  
 MA  
 M

,vk 87

,hr s1

,hr s1

76.  
 wron  
 77. g tk s  
 78. tored  
 79.  
 wron  
 80. g r1 s  
 81. tored  
 82.  
 -ent  
 83. ry in  
 84. Core  
 85. [1]  
 86.  
 87.  
 Co  
 88. re[0  
 89. :39  
 90. ] not  
 91. store  
 92. d on t  
 93. rack 3  
 94. 8

95. gs r5 [100]  
 96. is s1

,an s  
 NA

|      |    |     |     |          |
|------|----|-----|-----|----------|
| 98.  | pm | s   | ps  | s1       |
| 99.  | cl | -6  | ca  | 160      |
| 100. | ps | -1  | hr  | s1       |
| 101. | ca | 2h0 | hh  | r-h [97] |
| 102. | tk | -h  | ga  | r2 [10h] |
| 103. | ca | 63  | it  | 1        |
| 104. | sy |     | hvn | r-5 [99] |
| 105. | qq |     | qq  |          |

|      |     |     |     |          |
|------|-----|-----|-----|----------|
| 168. | qq  |     |     | t517     |
| 169. | it  | 311 | pt  |          |
| 170. | gk  | -1  | arn | -1       |
| 171. | vy  | 529 | tk  | 10       |
| 172. | nc  | 87  | hs  | 62       |
| 173. | arn |     |     |          |
| 174. | ca  | 512 | hv  | r6 [180] |
| 175. | ca  | 513 | hv  | r5 [180] |
| 176. | ca  | 1   | hv  | rh [180] |
| 177. | ca  | 2   | hv  | r3 [180] |
| 178. | ca  | 3   | hv  | r2 [180] |

|      |     |          |     |      |
|------|-----|----------|-----|------|
| 179. | hs  | 66       |     |      |
| 180. | tk  | 10       |     |      |
| 181. | nc  | 311      | ca  |      |
| 182. | hv  | r2 [18h] |     |      |
| 183. | hs  | 70       |     |      |
| 184. | wk  | 38       | lk  | 288  |
| 185. | wk  | 38       | grn | -2   |
| 186. | pa  | r2 [188] |     | t287 |
| 187. | pa  | r5 [192] |     | t39  |
| 188. | arn | 287      |     | t1   |

|      |    |    |      |     |
|------|----|----|------|-----|
| 189. | ar | 2  | D LA |     |
| 190. | ar | 1  | D LB |     |
| 191. | sc | -2 |      |     |
| 192. | bt | 39 |      | t-1 |

|      |     |           |    |         |
|------|-----|-----------|----|---------|
| 193. | hv  | r-5 [188] |    |         |
| 194. | arn | -2        |    |         |
| 195. | hv  | r3 [198]  | NZ |         |
| 196. | sk  | 208       | lk |         |
| 197. | hk  | r1 [198]  | hv | r [197] |
| 198. | arn | 289       | nc | 311     |
| 199. | hs  | 73        |    |         |
| 200. | hv  | r-h [196] |    |         |

|      |     |    |        |          |
|------|-----|----|--------|----------|
| 201. | qq  |    |        |          |
| 202. | qq  |    |        |          |
| 203. | qq  |    |        |          |
| 204. | qq  |    |        |          |
| 205. | pmn | 6h | XD IZA |          |
| 206. | tl  | -7 | ly     | r1 [207] |
| 207. | pi  |    |        | LZA t508 |
| 208. | qq  |    |        |          |

|      |    |     |    |    |
|------|----|-----|----|----|
| 209. | vy | 529 | sy | 6h |
| 210. | sy | 58  | sy | 19 |
| 211. | sy | h1  | sy | h9 |
| 212. | sy | 51  | sy | 3h |
| 213. | sy |     | sy | 16 |
| 214. | sy |     | sy | 37 |
| 215. | sy | 38  | sy | 19 |
| 216. | sy |     | sy | 19 |
| 217. | sy | h1  | sy | h9 |
| 218. | sy | 37  | sy | 18 |
| 219. | sy | 5h  | sy | 53 |
| 220. | sy | h1  | sy | h1 |
| 221. | sy | 53  | sy | 52 |
| 222. | hv | 26  |    |    |
| 223. | qq |     |    |    |
| 224. | qq |     |    |    |
| 225. | qq |     |    |    |

|      |     |          |             |
|------|-----|----------|-------------|
| 227. | qa  |          |             |
| 228. | qa  |          |             |
| 229. | qa  |          |             |
| 230. | qa  |          |             |
| 231. | qa  |          |             |
| 232. | qa  |          |             |
| 233. | qa  |          |             |
| 234. | qa  |          |             |
| 235. | qa  |          |             |
| 236. | hk  | r1 [237] | hv r [236]  |
| 237. | vk  | 38       | sk 288      |
| 238. | hv  | 512      | NKA         |
| 239. | vk  |          | sk 128      |
| 240. | vk  |          | hv 512      |
| 241. | qa  |          |             |
| 242. | pmn | 64       | XD IZA      |
| 243. | tl  | -7       | ly r1 [244] |
| 244. | pi  |          | IZA t508    |
| 245. | kr  |          | X IZB       |
| 246. | hv  | 35       | IZB         |
| 247. | gr  | 41       | MRC t-1     |



Rialto, 16 april 1968.

JFM

t 17

### Test 17, Printer

The program is intended for test of the lineprinter. It is published as a binary papertape and may be loaded to the core store by the primitive input program on track 0 of either HJÆLP or HELP 3.

### Method

The program prints characters in 159 positions on the printer.

The characters printed depends on the setting of KA and KB in the following manner:

- 1) KA=0, KB=0 : One line is printed consisting of one specific character. This character is typed on the typewriter when the program types Hej .
- 2) KA=1 , KB=0 : Each line contains all characters in both cases. The printing continues as long as KA is one. The first character in each line will be the one typed in the Hej-situation.
- 3) KA=0 , KB=1 : Each line contains the same character, but the both in upper case and lower case. The printerposition for shift between UC and LC will be shifted one towards left for each line. The first line will consist of the character typed in the Hej-situation.
- 4) KA=1 , KB=1 : Each line contain all characters and the printing is shifted one position towards left for each new line.

### Blind symbols

All blind characters are printed as SPACE. This is also valid for STOPCODE and TABULATOR.

RC-RIALTO  
21.3.1966  
TESTPROGRAM B-18  
JFM

1 (2)

The program is intended for test of disk files, in the cases where the disk unit replaces the usual drum unit; of course the program can be used for drum test, too.

#### PRINCIP

After reading in the program tape, the user specifies the area of the disk file he want to test. Then the program write known information in each word of this area. The information consist of word of the following format:

qq 'disknumber'. 9 + 'group'. 19 + 'sector'. 29 + 'wordnumber'. 39

After writing, this information is read to the core store in groups of eight sectors and compared with the correct information. This correct information is generated during reading and adjusted according to the current value of disk, group, sector, and word.

#### STORAGE LAYOUT

The core store is used as follows:

- 0 - 39 : track 0 of HELP
- 41 : the instruction zq LKB
- 42 - 143 : program administration
- 144 - 244 : number read routine
- 245 - 274 : number print routine
- 275 - 289 : text print routine
- 290 - 316 : routine for generation of correct information
- 317 - 334 : error print routine
- 335 : last group + 1
- 336 : last sector + 1
- 337 : disk unit number
- 338 : first group
- 339 : last group
- 340 : first sector
- 341 : last sector
- 342 : error used
- 343 : current value of group
- 344 : current value of sector
- 345 : address for choice of disk and tensgroup
- 346 : not used
- 347 : 4 (Floating)
- 348 : 10 -
- 349 : 961 -
- 350 : -40 (address)
- 351 : 960 -
- 352 - 382 : text strings
- 383 - 702 : 8 sectors of correct information
- 703 - 1022 : 8 sectors read from the disk

After reading in the program types:

|               |                               |
|---------------|-------------------------------|
| Disk No.:     | (type disk unit number)       |
| First Group:  | (type the wanted start group) |
| Last Group:   | ( - - - end - )               |
| First Sector: | ( - - - start sector)         |
| Last Sector:  | ( - - - end - )               |

First sector must be less than last sector and both  $< 960$ . First sector will be rounded to the nearest lower number divisible by 8. Last sector will be rounded to the nearest higher number divisible by 7, thus giving the possibility of writing and testing one entire track of eight sectors in one loop. First group must be less than or equal to last group and both less than 10. Disk unit must be less than 4. After typing last section the program starts. When one complete testcycle is finished, the program jumps to the start situation, if KB = 1 and stops in cell 41. If KB = 0, the program goes through another complete testcycle.

## NUMBERS

The numbers to be typed must conform with the syntax for input in Gier-Algol III, because this is the input routine which is used.

## ERRORS

When an error has been found, two lines are printed. One line in black showing the written information and one line in red showing the information which was read from the disk. The first error gives printing of a heading:

Disk Group Sect. Word

and the error print could be:

|   |   |     |    |         |
|---|---|-----|----|---------|
| 0 | 0 | 25  | 17 | (black) |
| 0 | 0 | 875 | 19 | (red)   |

; slip<

[ Diagnostic program t 21 test of mode 1 and 4 oct.68 PEH

The program tests all possible combinations of the conditions in mode 1 and 4. If an error is detected output is given on typewriter according to the following table

| output     | type of non-successful function                                      |
|------------|--|
| g0, g1, g2 | basic operation fullword, LH, RH halfword                            |
| a0, a1, a2 | address part of - - - - -  |
| n0, n1, n2 | n-mark (S-mark) - - - - -  |
| i0, i1, i2 | indirect addressing - - - - -  |
| r0, r1, r2 | relative-mark - - - - -  |
| s0, s1, s2 | subroutinemark - - - - -   |
| p0, p1, p2 | p-index - - - - -  |
| B          | indicator condition  |
| D          | D-mark   |
| f          | floating-point mark  |
| H          | halfword mark added  |
| h          | - - - - - deleted  |
| IK         | IKC operation  |
| K          | K-part of indicator (bit pos.37)                                     |
| T          | T-part of indicator (bit pos.35)                                     |
| Z          | Z-part of indicator (bit pos.36)                                     |
| L          | LA or LB operation (bit pos.33, 34, 38, 39)                          |
| X          | X-modification   |
| V          | V-modification   |
| q          | incremental operation  |
| qs         | incremental operation is erroneously treated as static or vice-versa |

The letters may be combined, thus the message  
isB

means that a mode 1 or 4 error is detected during execution of an instruction which is indirect addressed, s-marked and furnished with some indicator condition.

If KA is set during run the error message will be followed by a three-digit number which gives the address of the cell from which the alarm was called.

Pressing of KB causes the machine to stop.

If no errors are detected an ok message is typed every 20 seconds.

Input of program.

The program may be read in like any other B or C test. However, if this does not work the program may be read in using as simple instructions as possible in this way:

1. RESET GIER.
2. place the tape in the reader starting in the middle of the 100 spaces found a few inches after the starting point used for old track 0.
3. clear the entire core store using hardware test 1.
4. clear R, M and by.
5. insert in cell 41 - 43 the following instructions:

|     |       |   |
|-----|-------|---|
| 41. | ly 43 | bit pos. 4, 6, 8, 9, 20, 21, 22, 24, 25 |
| 42. | cl 76 | - - 3, 6, 7, 21, 23                     |
| 43. | gm    | - - 21, 22, 24                          |

6. start GIER in cell 41

When the program has been read in the primitive input program in cell 34 - 39 is re-established.

i=27

```

[ 27]    pm i+5    ;
[ 28]    gm -2 M   ;
[ 29]    pm i+4    ;
[ 30]    gm 0 M    ;
[ 31]    hv 40     ;
[ 32]    ar a1     ;
[ 33]    tk 42     ;
[ 34]    pm64XDIZA; primitive input
[ 35]    tl -7,lyr1;
[ 36]    pi LZAt508;
[ 37]    xr X IZB  ;
[ 38]    hv 35 LZB ;
[ 39]    gr41MRct-1;
[ 40]    tk 42     ;
[ 41]    qq        ;
[ 42]    vy 16     ;
[ 43]    sy 29     ; red ribbon
[ 44]    sy 53     ; LC
[ 45]    sy 64     ;
[ 46]    hv a0     ; goto start

```

; alarm print

```

[ 47]b0:  qq        ; work
[ 48]    qq        ; constant
[ 49]    sy 55     ; g
[ 50]    qq        ;
[ 51]    sy 49     ; a
[ 52]    hv b1     ;
[ 53]    sy 37     ; n
[ 54]    hv b1     ;
[ 55]    sy 57     ; i
[ 56]    hv b1     ;
[ 57]    sy 41     ; r
[ 58]    hv b1     ;
[ 59]    sy 18     ; s
[ 60]    hv b1     ;
[ 61]    sy 39     ; p
[ 62]b1:  sy 16     ; [full-word]
[ 63]    hv a2     ; goto s-print
[ 64]    sy 55     ; g
[ 65]    hv b2     ;
[ 66]    sy 49     ; a
[ 67]    hv b2     ;
[ 68]    sy 37     ; n
[ 69]    hv b2     ;
[ 70]    sy 57     ; i
[ 71]    hv b2     ;
[ 72]    sy 41     ; r
[ 73]    hv b2     ;
[ 74]    sy 18     ; s
[ 75]    hv b2     ;
[ 76]    sy 39     ; p
[ 77]b2:  sy 1      ; 1 [LH half-word]
[ 78]    hv a2     ; goto s-print
[ 79]    sy 55     ; g

```

```

[ 80]    hv b3      ;
[ 81]    sy 49      ; a
[ 82]    hv b3      ;
[ 83]    sy 37      ; n
[ 84]    hv b3      ;
[ 85]    sy 57      ; i
[ 86]    hv b3      ;
[ 87]    sy 41      ; r
[ 88]    hv b3      ;
[ 89]    sy 16      ; s
[ 90]    hv b3      ;
[ 91]    sy 39      ; p
[ 92]b3:  sy 2       ; 2 [RH half-word]
[ 93]    hv a2      ; goto s-print
[ 94]    sy 60      ; B [indicator condition]
[ 95]    sy 50      ;
[ 96]    hv a2      ;
[ 97]    sy 60      ; D
[ 98]    sy 52      ;
[ 99]    hv a2      ;
[100]    sy 54      ; f [floating-point mark]
[101]    hv a2      ;
[102]b4:  sy 60      ; H
[103]    sy 56      ; h
[104]    hv a2      ;
[105]    sy 60      ; IK [IKC operation]
[106]    sy 57      ;
[107]    sy 60      ; K
[108]    sy 34      ;
[109]    hv a2      ;
[110]    sy 60      ; L
[111]    sy 35      ;
[112]    hv a2      ;
[113]b5:  sy 40      ; q
[114]    hv a2      ;
[115]    sy 40      ; qs
[116]    sy 18      ; [static op treated as incremental
[117]    hv a2      ; or vice-versa]
[118]    sy 60      ; T
[119]    sy 19      ;
[120]    hv a2      ;
[121]    sy 60      ; X
[122]    sy 23      ;
[123]    hv a2      ;
[124]b6:  sy 60      ; XV
[125]    sy 23      ;
[126]    sy 60      ; V
[127]    sy 21      ;
[128]    hv a2      ;
[129]    sy 60      ; Z
[130]    sy 25      ;

```

```

;      s-print

```

```

[131]a2:  sy 58      ;
[132]    hv a3 NKA    ;
[133]    sy 0         ;
[134]    tk 42        ;
[135]    ar c2        ;
[136]    gr c3        ;
[137]    tl 00        ; R:=M:=0
[138]    gs 1+1       ;

```

```

[ 139]    qq [s]      ;
[ 140]    ar 1-1      ;
[ 141]    cl 10       ;
[ 142]    ml c        ;
[ 143]c4:  ck -10     ;
[ 144]    ca 0        ;
[ 145]    hv 1+2      ;
[ 146]    hv 1+3      ;
[ 147]    arn 1+1     ;
[ 148]    qq 16       ;
[ 149]    ga 1+1      ;
[ 150]    sy         ;
[ 151]    tk 42       ;
[ 152]    ar c3       ;
[ 153]    ar a1       ;
[ 154]    gr c3       ;
[ 155]    ca 0        ;
[ 156]    hv 1+3      ;
[ 157]    ac c6       ;
[ 158]    hv a3       ;
[ 159]    ml c1       ;
[ 160]    hv c4       ;
[ 161]c0:  m 10-2     ;
[ 162]c1:  qq 10.39   ;
[ 163]c2:  qq 2.39    ;
[ 164]c3:  qq         ; work

```

```

;    message counter

```

```

[ 165]a3:  sy 0       ;
[ 166]    tk 42       ;
[ 167]    ar c6       ;
[ 168]    ar a1       ;
[ 169]    gr c6       ;
[ 170]    ca 0        ;
[ 171]    hv a0       ;
[ 172]    sy 64       ;
[ 173]    ar c5       ;
[ 174]    gr c6       ;
[ 175]    hv a0       ;
[ 176]c5:  qq 20.39   ;
[ 177]c6:  qq 19.39   ;

```

```

;    reset and start

```

```

[ 178]a0:  tk 42      ;
[ 179]    ar c7       ;
[ 180]    gr c8       ; reset ok-counter
[ 181]    pp 0        ;
[ 182]    ps 0        ;
[ 183]    hv 1+2      ;
[ 184]a1:  qq -1.39   ; constant
[ 185]    tk 42       ;
[ 186]    hv 1+2 NKB;
[ 187]    zq LKB      ;
[ 188]    ud -2       ; test of adress, fullword
[ 189]    sr a1       ;
[ 190]    ca 0        ;
[ 191]    hv 1+2      ;
[ 192]    hs 2b       ; print(ga0)
[ 193]    qqt b4XVD   ; [qq ,hv.b4], test of +half-word mark, print(H)

```

```

[ 194]      qq      ; dummy
[ 195]a4:   ar a1    ; test of LA, LB
[ 196]      hs 8b4 LA ; print(L)
[ 197]      hs 8b4 LB ; print(L)
[ 198]      pi -1     ; test of T, Z, K
[ 199]      hs 5b5NTC ; print(T)
[ 200]      hs 5b6 LZ ; print(Z)
[ 201]      tk 42     ;
[ 202]      hs 5b6 NZ ; print(Z)
[ 203]      hs 5b4 LO ; print(K)
[ 204]      tk 42     ; R:=0
[ 205]a5:   pm a1    ; test of X, M:=-1.39
[ 206]      cl 40 X   ;
[ 207]      hv i+2 LZ ;
[ 208]      hs 8b5 NZ ; print(X)
[ 209]      pm a1 X   ; R:=-1.39, M:=0
[ 210]      sr a1    ; R:=0
[ 211]      hv i+2 LZ ;
[ 212]      hs 8b5 NZ ; print(X)
[ 213]      tk 42 X   ; M:=0
[ 214]      xr      ; R:=0
[ 215]a6:   hv i+2 LZ ;
[ 216]      hs 8b5 NZ ; print(X)
[ 217]      ar a1 X   ; M:=-1.39
[ 218]      xr      ; R:=-1.39
[ 219]      sr a1    ; R:=0
[ 220]      hv i+2 LZ ;
[ 221]      hs 8b5 NZ ; print(X)
[ 222]      qq      V ; test of V
[ 223]      hs 2b6    ; print(V)
[ 224]      pm a1 XV  ; test of XV
[ 225]a7:   hs b6    ; print(XV)
[ 226]      sr a1    ;
[ 227]      hv i+2 LZ ;
[ 228]      hs b6 NZ  ; print(XV)
[ 229]      arf a1 X  ; test of floating-point mark
[ 230]      hv i+2 NZ ;
[ 231]      hs 8b3    ; print(f)
[ 232]      tk 42     ;
[ 233]      ar a1 D   ; test of D
[ 234]      ca a1     ;
[ 235]      hv i+2    ;
[ 236]      hs 5b3    ; print(D)
[ 237]      tk 42     ;
[ 238]      ar a1     ; test of n, full-word
[ 239]a8:   qqn      ;
[ 240]      hv i+2 LZ ;
[ 241]      hs 6b NZ  ; print(n0)
[ 242]      ca (1b)   ; test of i, full-word
[ 243]      hv i+2    ;
[ 244]      hs 8b     ; print(i0)
[ 245]      tk 42     ;
[ 246]      ar ra1    ; test of r, full-word
[ 247]      sr a1     ;
[ 248]      hv i+2 LZ ;
[ 249]a9:   hs 10b NZ ; print(r0)
[ 250]      ps a1     ; test of s, full-word
[ 251]      ar s      ;
[ 252]      sr a1     ;
[ 253]      ps 0      ;
[ 254]      hv i+2 LZ ;
[ 255]      hs 12b NZ ; print(s0)
[ 256]      pp a1     ; test of p, full-word

```



```

[ 257]      ar p      ;
[ 258]      sr a1     ;
[ 259]a10: pp 0       ;
[ 260]      hv i+2 LZ ;
[ 261]      hs 14b NZ ; print(p0)
[ 262]      ar a1     ; test of LH half-word
[ 263]      ps 42     ;
[ 264]      ud ,      ; LH, basic op
[ 265]      ps 0      ;
[ 266]      hv i+2 LZ ;
[ 267]      hs 2b1 NZ ; print(g1)
[ 268]      ps -1     ; test of LH address
[ 269]a11: ud -2,    ;
[ 270]      ps 0      ;
[ 271]      sr a1     ;
[ 272]      hv i+2 LZ ;
[ 273]      hs 4b1 NZ ; print(a1)
[ 274]      ar a1     ; n, LH
[ 275]      qqn ,     ;
[ 276]      hv i+2 LZ ;
[ 277]      hs 6b1 NZ ; print(n1)
[ 278]      pi i-4    ;
[ 279]      gi i+1    ;
[ 280]      ar (i-6), ; i, LH
[ 281]a12: sr a1     ;
[ 282]      hv i+2 LZ ;
[ 283]      hs 8b1 NZ ; print(i1)
[ 284]      pi a1-i-2 ;
[ 285]      gi i+1    ;
[ 286]      ar ra1,   ; r, LH
[ 287]      sr a1     ;
[ 288]      hv i+2 LZ ;
[ 289]      hs 10b1NZ ; print(r1)
[ 290]      ps a1     ;
[ 291]      ar s,     ;
[ 292]      sr a1     ;
[ 293]a13: ps 0       ;
[ 294]      hv i+2 LZ ;
[ 295]      hs 12b1NZ ; print(s1)
[ 296]      pp a1     ;
[ 297]      ar p,     ;
[ 298]      sr a1     ;
[ 299]      pp 0      ;
[ 300]      hv i+2 LZ ;
[ 301]      hs 14b1NZ ; print(p1)
[ 302]      ,tl [VM] ; test of -half-word
[ 303]a14: hv i+2     ;
[ 304]      hs 1b4    ; print(h)
[ 305]      tk 42     ;
[ 306]      ar a1     ; test of RH half-word
[ 307]      ps 42     ;
[ 308]      ,ud      ; basic op
[ 309]      qq       ; dummy
[ 310]      ps 0      ;
[ 311]      hv i+2 LZ ;
[ 312]      hs 2b2 NZ ; print(g2)
[ 313]a15: ps -1     ; RH address
[ 314]      ,ud -2    ;
[ 315]      sr a1     ;
[ 316]      ps 0      ;
[ 317]      hv i+2 LZ ;
[ 318]      hs 4b2 NZ ; print(a2)
[ 319]      ar a1     ; n, RH

```

```

[ 320]      ,qqn      ;
[ 321]      hv i+2 LZ ;
[ 322]      hs 6b2 NZ ; print(n2)
[ 323]a16: ,ca (1b) ; i, RH
[ 324]      hv i+2      ;
[ 325]      hs 8b2      ; print(i2)
[ 326]      ,ar ra1     ; r, RH
[ 327]      sr a1       ;
[ 328]      hv i+2 LZ ;
[ 329]      hs 10b2NZ ; print(r2)
[ 330]      ps a1       ; s, RH
[ 331]      ,ar s       ;
[ 332]      sr a1       ;
[ 333]a17: ps 0        ;
[ 334]      hv i+2 LZ ;
[ 335]      hs 12b2NZ ; print(s2)
[ 336]      pp a1       ; p, RH
[ 337]      ,ar p       ;
[ 338]      sr a1       ;
[ 339]      pp 0        ;
[ 340]      hv i+2 LZ ;
[ 341]      hs 14b2NZ ; print(p2)
[ 342]      ,tl [VM] ; test of -half-word mark
[ 343]a18: hv i+2      ;
[ 344]      hs 1b4      ; print(h)
[ 345]      pa i+1      ; test of increment
[ 346]      qq ,qq 1    ;
[ 347]      ar i-1      ;
[ 348]      ca 0         ;
[ 349]      hv i+2      ;
[ 350]      hs b5        ; print(q)
[ 351]      tk 42        ;
[ 352]      pa i+1      ; test of -,B^q
[ 353]a19: ar ta1 NZ ;
[ 354]      hv i+3 LZ ;
[ 355]      ud b5 NZ ; print(qB)
[ 356]      hs 2b3 NZ ;
[ 357]      ar a1       ; test of q
[ 358]      pa i+1      ;
[ 359]      sr ta1      ;
[ 360]      hv i+2 LZ ;
[ 361]      hs b5 NZ ; print(q)
[ 362]      qq tb4 XVM; [qq ,hs b4]
[ 363]a20: qq          ; test of +half-word mark, print(H)
[ 364]      tk 42        ;
[ 365]      ca (1b)      ; test of i, full-word
[ 366]      hv i+2      ;
[ 367]      hs 8b        ; print(i0)
[ 368]      tk 42        ; test of increment
[ 369]      ga i+12      ; decoding of TD+0
[ 370]      ar a1       ;
[ 371]      qq(i+10)t512
[ 372]      qq(i+9)t256
[ 373]      qq(i+8)t128
[ 374]a21: qq(i+7)t64;
[ 375]      qq(i+6)t32;
[ 376]      qq(i+5)t16;
[ 377]      qq(i+4)t8 ;
[ 378]      qq(i+3)t4 ;
[ 379]      qq(i+2)t2 ;
[ 380]      qq(i+1)t1 ;
[ 381]      ca -1       ;
[ 382]      hv i+2      ;

```

```

[ 383]      hs b5      ; print(q)
[ 384]a22:  ga i+1    ; decoding of
[ 385]      pi -1 t1   ; static op
[ 386]      tk 42      ;
[ 387]      ar 1-2     ;
[ 388]      ca -1      ;
[ 389]      hv i+2     ;
[ 390]      hs 2b5     ; print(qs)
[ 391]      pi -500     ;
[ 392]      gi i+1     ; decoding of non-static op
[ 393]      bt-500t-100
[ 394]a23:  hv i+2     ;
[ 395]      hs 2b5     ; print(qs)
[ 396]      tk 42      ;
[ 397]      pa i+1     ; decoding of
[ 398]      nc 0 t-1   ; non-static op
[ 399]      hv i+2     ;
[ 400]      hs 2b5     ; print(qs)
[ 401]      qq tb4 XVM; test of +h
[ 402]      qq          ;
[ 403]      tk 42      ;
[ 404]      pa i+2     ; test of step 12
[ 405]      nt i+1     ; increment^r
[ 406]a24:  ca r       ;
[ 407]      hv i+3     ;
[ 408]      ud 10b     ; print(rq)
[ 409]      hs b5      ;
[ 410]      pa i+3     ;
[ 411]      ps i+2     ;
[ 412]      nt i+1     ; increment^s
[ 413]      ca s       ;
[ 414]      hv i+4     ;
[ 415]      ps 0       ;
[ 416]      ud 12b     ; print(sq)
[ 417]a25:  hs b5      ;
[ 418]      ps 0       ;
[ 419]      pa i+3     ;
[ 420]      pp i+2     ; increment^p
[ 421]      nt i+1     ;
[ 422]      ca p       ;
[ 423]      hv i+3     ;
[ 424]      ud 14b     ; print(pq)
[ 425]      hs b5      ;
[ 426]      pp 0       ;
[ 427]      tk 42      ;
[ 428]      hv 1a1 NZ ;
[ 429]a26:  ar a1      ;
[ 430]      ncn LZ    ; test of -,B^a
[ 431]      hv i+3     ;
[ 432]      ud 6b      ; print(nB)
[ 433]      hs 2b3     ;
[ 434]      tk 42      ;
[ 435]      ar a1      ; test of -,B^(s)
[ 436]      ga i+1     ;
[ 437]      qq          ;
[ 438]      ps i-1     ;
[ 439]      nc (s) LZ ;
[ 440]      hv i+5     ;
[ 441]a27:  ps 0       ;
[ 442]      ud 8b      ; print(isB)
[ 443]      ud 12b     ;
[ 444]      hs 2b3     ;
[ 445]      ga i+1     ; test of (r) and (s)

```

```

[ 446]      qq      ;
[ 447]      ps i-1  ;
[ 448]      ca (s)   ;
[ 449]      hv i+4   ;
[ 450]      ps 0      ;
[ 451]a28: ud 8b    ; print(is0)
[ 452]      hs 12b   ;
[ 453]      ps 0      ;
[ 454]      ca (r-8) ;
[ 455]      hv i+3   ;
[ 456]      ud 8b    ; print(ir0)
[ 457]      hs 10b   ;
[ 458]a29: pp -1    ; test of IK (mode 4)
[ 459]      pi 0      ;
[ 460]      tk 42     ;
[ 461]      nc 0 IKC  ; p:=0, in:=-1
[ 462]      hs b4     ; if +h then print(H)
[ 463]      gp i+1   ;
[ 464]      ca        ;
[ 465]      hv i+2   ;
[ 466]a30: hs 3b4   ; print(IK)
[ 467]      gi i+1   ;
[ 468]      qq        ;
[ 469]      nc 0 IKC  ; p:=-1, in:=0
[ 470]      hs b4     ; if +h then print(H)
[ 471]      ar i-3    ;
[ 472]      ca -1     ;
[ 473]      hv i+2   ;
[ 474]      hs 3b4   ; print(IK)
[ 475]      gp i+1   ;
[ 476]      ca        ;
[ 477]a31: hv i+2   ;
[ 478]      hs 3b4   ; print(IK)
[ 479]      gi i+2   ;
[ 480]      tk 42     ;
[ 481]      ca        ;
[ 482]      hv i+2   ;
[ 483]      hs 3b4   ; print(IK)
[ 484]      qq V      ; test of V
[ 485]      hs 2b6   ; print(V)
[ 486]      pp -1    ; test of VIK
[ 487]      pi 0 VIKC; p:=0, in:=-1
[ 488]      hs i+2   ; print(VIK)
[ 489]a32: hv i+4   ;
[ 490]      ud 2b6   ;
[ 491]      ud 3b6   ;
[ 492]      hv 3b4   ;
[ 493]      tk 42     ;
[ 494]      gp i+1   ;
[ 495]      ca        ;
[ 496]      hv i+2   ;
[ 497]      hs i-7    ; print(VIK)
[ 498]      hv 1a1 NZ ; skip if +h
[ 499]      pm a1 X   ; test of X
[ 500]      hs 8b5 IZ ; print(X)
[ 501]      pm a1 XIKC; test of XIK
[ 502]      gp i+1   ; R:=-1, M:=0, p:=-1, in:=0
[ 503]a33: ca        ;
[ 504]      hv i+4 NZ ;
[ 505]      ud 8b5   ; print (XIK)
[ 506]      ud 9b5   ;
[ 507]      hs 3b4   ;
[ 508]c7:  qq 2000.39; Ok counter

```

```

[ 509]c8: qq      ; work
[ 510]      tk 42  ;
[ 511]      ar 1-2 ;
[ 512]      ar a1  ;
[ 513]a34: gr 1-4  ;
[ 514]      hv 1a1 NZ ; if 2000 successful runs then
[ 515]      sy 62   ; print(ok)
[ 516]      sy 38   ;
[ 517]      sy 34   ;
[ 518]      sy 29   ;
[ 519]a35: hv a3    ; goto start and reset

```

t21-10

e27

Rialto, 25 april 1968

JFM

t26

### Test 26, Input/Output Typewriter

The program is used for test of the typewriter, when the typewriter is used as outputmedium. For test of inputfunctions one should use t9.

The program is published as a binary punched papertape, which may be read to the core store by means of the primitive loaderprogram on track 0 of HJÆLP or HELP 3.

### Method

The program writes lines as shown on the figure. These lines are constructed in such a way that all characters are typed and all functions (caseshift, carriage return, tabulation and ribbon shift) are activated several times. When the output on the figure has been typed the program repeats the entire process.

|              |             |             |     |      |     |      |     |                          |
|--------------|-------------|-------------|-----|------|-----|------|-----|--------------------------|
| 123          | 456         | 789         | 0-< | qwe  | rty | uio  | påa |                          |
| vx/          | =;[         | ]()         | ^+> | QWE  | RTY | UIO  | PÅA |                          |
| 123          | 456         | 789         | 0-< | qwe  | rty | uio  | påa |                          |
| vx/          | =;[         | ]()         | ^+> | QWE  | RTY | UIO  | PÅA |                          |
| 123          | 456         | 789         | 0-< | qwe  | rty | uio  | påa |                          |
| vx/          | =;[         | ]()         | ^+> | QWE  | RTY | UIO  | PÅA |                          |
| 123          | 456         | 789         | 0-< | qwe  | rty | uio  | påa |                          |
| vx/          | =;[         | ]()         | ^+> | QWE  | RTY | UIO  | PÅA |                          |
| sdfg         |             | hjkl        |     | æøzx |     | cvbn |     | m. .-                    |
| SDFG         |             | HJKL        |     | ÆØZX |     | CVBN |     | M <sub>10</sub> :+       |
| sdfg         |             | hjkl        |     | æøzx |     | cvbn |     | m. .-                    |
| SDFG         |             | HJKL        |     | ÆØZX |     | CVBN |     | M <sub>10</sub> :+       |
| sdfg         |             | hjkl        |     | æøzx |     | cvbn |     | m. .-                    |
| SDFG         |             | HJKL        |     | ÆØZX |     | CVBN |     | M <sub>10</sub> :+       |
| sdfg         |             | hjkl        |     | æøzx |     | cvbn |     | m. .-                    |
| SDFG         |             | HJKL        |     | ÆØZX |     | CVBN |     | M <sub>10</sub> :+       |
| 1234567890<  | qwertyuiopå | asdfghjklæø |     |      |     |      |     | zxcvbnm. .-              |
| vx/>=;[ ]()^ | QWERTYUIOPÅ | ASDFGHJKLÆØ |     |      |     |      |     | ZXCVBNM <sub>10</sub> :+ |
| 1234567890<  | qwertyuiopå | asdfghjklæø |     |      |     |      |     | zxcvbnm. .-              |
| vx/>=;[ ]()^ | QWERTYUIOPÅ | ASDFGHJKLÆØ |     |      |     |      |     | ZXCVBNM <sub>10</sub> :+ |
| 1234567890<  | qwertyuiopå | asdfghjklæø |     |      |     |      |     | zxcvbnm. .-              |
| vx/>=;[ ]()^ | QWERTYUIOPÅ | ASDFGHJKLÆØ |     |      |     |      |     | ZXCVBNM <sub>10</sub> :+ |
| 1234567890<  | qwertyuiopå | asdfghjklæø |     |      |     |      |     | zxcvbnm. .-              |
| vx/>=;[ ]()^ | QWERTYUIOPÅ | ASDFGHJKLÆØ |     |      |     |      |     | ZXCVBNM <sub>10</sub> :+ |

**GIER**  
SYSTEM LIBRARY

Order No. 1 24

Class 1.2

Type Report

Author: Jan Filasiewicz

Ed.: December, 1955. (2)

Diagnostic Program for  
RC-3000 Converter Unit

## INTRODUCTION

This paper holds a description of some catalogues and data-tapes for testing of the RC 3000 converter unit. In the first place ~~the~~ purpose is to shorten the time necessary for trouble-shooting. Concerning the achievement of this certain aim catalogues and data-tapes are constructed in such a way that a maximum of information is given in registers, on the output medium etc. under the circumstances already given. Some of the catalogues, and data-tapes will be especially useful for measuring on oscilloscope of dynamic phenomena; other catalogues are merely intended on the testing of some static converter functions. By planning the catalogues and data-tapes first of all a standard equipment consisting of one RC 3000 converter unit, one RC 2000 paper tape reader, and one AMPEX TM-7 tape station is considered. Optional equipment such as line-printer, card reader, paper tape puncher, plotter, and card puncher are not considered as usual equipment, but on the other hand a line-printer or an apparatus simulating line-printer will, of course, be of great help in the trouble-shooting. The description of the catalogues and data-tapes hold information about the contents of the catalogue, and about the normal (errorfree) function, and the possible reasons to errorstops or erroroutput.



Abbreviations and Terminology

The following abbreviations are so frequently used that a list of brief explanations might come in handy.

| abbreviation | abbreviated from | explanation of the term   |
|--------------|------------------|---|
| DEL          | DELETE           | A specialcharacter meaning that the inputcharacter in question will not produce any output.   |
| LCS          | LOWER CAT.SHIFT  | A specialcharacter meaning that the addition of 256 (for reader input) or 64 (for magn.tape input) to input characters before catalogue reading will be skipped for all the input succeeding. |
| UCS          | UPPER CAT.SHIFT  | A specialcharacter meaning that addition of 256, viz. 64 shall take place on all the following input.   |
| EB           | END OF BLOCK     | A specialcharacter meaning that the accumulated block has to be output.   |
| EBS          | EB WITH STOP     | As EB, but with the stopping of RC 3000 after the output.   |

Other terms often in use are:

Catalogue which is to be used for catalogue paper tape as well as for the part of the core store which is used as catalogue.

Lower table is the part of the store which can be accessed between a LCS and a UCS.

Upper table is the part of the store which can be accessed between a UCS and a LCS.

Catalogue reading means reading of a cell in the catalogue, using an inputcharacter as address, and storing the cataloguecharacter in the block-accumulator or skipping the cataloguecharacter (only for DEL, LCS and UCS).

Blockaccumulator is the part of the core store in which characters are collected and stored before jump to an output program.

BASA is the address of the first cell used for the block accumulator.

To each catalogue and data-tape are assigned a name consisting of one to three letters, a number and in some cases an additional letter group.

The first letter group is built up as follows:

First letter:

- C     for catalogue tape
- D     for data-tape (paper tape or magnetic tape)

Second letter (if any):

- R     for input from paper tape
- M     for input from magnetic tape
- C     for input via RC 3000 (for instance card reader)

Third letter (if any):

- P     for output to printer or paper tape puncher
- M     for output to magnetic tape or
- C     for output to other device (card puncher)

The number following the first letter group is used as an index for tapes with equal first group. The second letter group is (when used) either BCD or CDC. BCD refers to magnetic tapes with even parity. CDC refers to a special mechanism for case shift on the line printer. One can have both BCD and CDC on the same tape.

Two special devices might be useful in trouble shooting. These are the printer simulator, and pushbutton for interruption of the parity check on transfers to and from the core store in RC 3000.

#### The printsimulator

Consists of a box with one switch and one pushbutton and two cables. The cables are connected to jacks J3 and J4 in the converter. The switch has the two positions RUN and STEP. In the RUN position a series of Busy and Ready signals are sent to RC 3000 which therefore can run continuously. In the STEP position a single ready signal is sent to RC 3000 each time the pushbutton is depressed, thus allowing us to process one character and stop.

The paritybutton

The paritybutton is a pushbutton situated behind the pushbuttonpanel by the display panel (this is valid from converter No. xxx, on earlier converters the button is situated inside the frontcover at the frame. When the button is depressed the ERROR flip-flop can not be set for parity errors in the IR-register, but ERROR can still be set for length-errors in the catalogue tape etc. Using this button it is possible to read in catalogues containing characters with even parity. This feature is very useful if one want to stop RC 3000 at the very moment an error occurs in a dynamic run.

CRM - 0, CRM - 1, CRM - 2, CRM - 3, CRM - 4, CRM - 5, CRM - 6, CRM - 7

These eight catalogues all have the length 512. Input is taken from paper tape and output is sent to magnetic tape and written with odd parity. The catalogues have the same character in all cells from 1 - 255, the cells 0 and 256 - 511 contains EBS.

| Catalogue | Catalogue contents (1 - 255) |
|-----------|------------------------------|
| CRM - 1   | 1                            |
| CRM - 2   | 2                            |
| CRM - 3   | 4                            |
| CRM - 4   | 8                            |
| CRM - 5   | 16                           |
| CRM - 6   | 32                           |
| CRM - 7   | 0                            |
| CRM - 0   | 64                           |

The data used is D - 1. In this way we obtain a constant information on the outputlines. The reason for the EBS's in all the not accessible cells up to 511 is that in this way an erroneous bit in the AR-register position 8 or zeroes in all positions of AR will cause a stop of RC-3000. The catalogue CRM - 7 will only write the parity bit on the magnetic tape, and CRM - 0 will give parity error on the magnetic tape. (The PET lamp will be lit). This means that with CRM - 7 one can test whether the parity bit is generated or not when it is present in the core store. With CRM - 0 one can test whether a parity bit is generated or not when it is not present in the core store.

CMP - 0

Catalogue for test of the magnetic tape produced by CRM - 1, CRM - 2, CRM - 3, CRM - 4, CRM - 5, CRM - 6 or CRM - 7. The output is sent to the line printer or the line printer simulator. The output is the number of the track on the magnetic tape (i.e. it is 1, 2, 3, 4, 5, 6 or 7). The catalogue is read in using the parity button and place parity errors in all cells except 0, 1, 2, 3, 4, 5 and 6. In this way a character from the magnetic tape will cause an immediate stop in the ERROR situation and in the AR-register the character which caused the stop can be seen.

The IR-register will contain in case of error the number of cell which caused the error using position 7 in the cell as parity bit. Therefore, normally, the contents of IR and AR should be equal. If not there must be some error in connection with the AR-register (e.g. the decoding), or an error in one or more positions or IR.

#### CMP - 1

As CMP = 0 but with EBS in all irrelevant cells. With this catalogue, which can be read in on all converters, one will have a stop after an error. In the stop situation the information displayed in the registers have no connection with the error, one can only register that there has been some sort of error. This is one of the reasons for the special parity button.

#### C - 0

Catalogue for test of the core store. The catalogue contents is 8 sets of characters each set having characters running from 0 to 127 with odd parity. To this 8 sets is added a character with value 127, so that we have in all  $128 \times 8 + 1 = 1025$ . The catalogue is constructed as an infinite loop. In this way we are able to displace the first character one cell in each loop and after 127 loops all legal bit combinations have been written in all cells, and the BASA has been set to all values from 0 to 1023. When the running is stopped by activating UP on the reader, the normal reaction will be that ERROR is lit because in only approx. 3% of the cases we will have read a multiple of 32 characters. If ERROR is lit during the run, and the converter stops in program 1, step 5 with even parity in the IR-register, the error was a parity error from the paper tape (i.e. an error on the paper tape or an error in the transfer from RC 2000 to the converter). For converters with serial number from 3122 stop with program 1, step 6 selected may occur. In this case we have an error in the core store, and the cell number can be seen in the AR-register, and the wrong cell contents in the IR-register. If the button "proceed read catalogue" is depressed the read of the catalogue tape will be continued.

#### C - 1

Catalogue for testing of counting in the OC-register, which is the only counting register in RC 3000 and vital for the correct function. The catalogue is a tape with  $1 + 1023$  characters. The first character is punched about one inch in front of the second and following characters. The characters used all have the one hole in track 5. If one read in the entire catalogue the following indicators should be lit: PAPERTAPE INPUT, MAGN. TAPE OUTPUT BINARY. All positions in OC except OC 10 should be zero. Of one reads in the catalogue starting with the second character ERROR should be lit (on converters from No. 3122 LENGTH ERROR), and the AR-register shall have ones in position 0 - 9 and zero in position 10.

CRM - 8

Catalogue for testing of the special character EBS. Each second cell of the catalogue contains EBS (i.e. EBS in cell 1, 3, 5, .....251). The other cells contains the values 1 - 63 in the following way:

| Cell | Value |
|------|-------|
| 0    | 1     |
| 2    | 2     |
| 4    | 3     |
| -    | -     |
| -    | -     |
| 124  | 63    |
| 126  | 1     |
| 128  | 2     |
| -    | -     |
| 250  | 63    |

The catalogue is used in connection with the data tape D - 10 which will refer to cell 1 - 2 - 3 up to 251 and then again to 1, 2, 3 etc. This means that each second character will give EBS and the output block (consisting of 512 characters) will be:

| data | block        |
|------|--------------|
| 1    | 1-1-1-....1  |
| 3    | 2-1-1-....1  |
| 5    | 3-1-1-....1  |
| 7    | 4-1-1-....1  |
| -    | -            |
| 125  | 63-1-1-....1 |
| 127  | 1-1-1-....1  |
| 129  | 2-1-1-....1  |
| -    | -            |
| 250  | 63-1-1-....1 |

The output to the magnetic tape can be checked to some degree with the catalogue CMP - 2, but the best check can be performed by a computer program. This program shall read the blocks one by one and check that the first character is the block number modulo 64, and that the rest of the block is ones. If the rest of the block is different from ones the reason could be that EBS does not act correctly. If all blocks consist of ones the EBS is derived also when the catalogue cell contains one of the values 1 - 63.

CRM - 8 BCD

Catalogue with functions as CRM - 8, but writing the magnetic tape with even parity.

CMP - 2

Catalogue for printing of tapes produced by CRM - 8. The catalogues output is one character per block and this character will be the value of the first character in the block, but ones will be neglected at output.

CMP - 2 BCD

Catalogue with functions as CMP - 2, but printing of tapes produced by CRM - 8 BCD.

CRM - 9

Catalogue for testing of the special characters DELETE, LOWER CATALOGUE SHIFT and UPPER CATALOGUE SHIFT. The lower table part of the catalogue is stored in cells 1 - 255 and the upper table part in cells 257 - 511. BASA is set to 1023. Therefore a single character which is not decoded as special character will produce output. Below is sketched how the catalogue is built up:

| Value of input character | Lower Table cell    | Upper Table cell |
|--------------------------|---------------------|------------------|
| not existing             | 0 parity            | 0 + 256 parity   |
| 1                        | 1 UCS               | 1 + 256 parity   |
| 2                        | 2 parity            | 2 + 256 DEL      |
| 3                        | 3 parity            | 3 + 256 LCS      |
| 4                        | 4 DEL               | 4 + 256 parity   |
| 5                        | 5 UCS               | 5 + 256 parity   |
| 6                        | 6 parity            | 6 + 256 DEL      |
| 7                        | 7 parity            | 7 + 256 LCS      |
| 8                        | 8 DEL               | 8 + 256 parity   |
| -                        |                     |                  |
| -                        |                     |                  |
| 254                      | 254 parity          | 254 + 256 DEL    |
| 255                      | 255 parity          | 255 + 256 LCS    |
| 512                      | all contains parity |                  |

Parity means that the cell has even parity, so that an erroneous reference to the cell will stop the converter in the ERROR-situation. As seen from the table each input character will refer to a cell with some special character and if LCS and UCS do not act correct, reference to a cell with parity error will be made, and the converter stops in the ERROR-situation with the input character in the AR-register positions 0 - 7 and AR 8 = 1, if 256 has been added in the lower table case and AR 8 = 0, if 256 has not been added in the upper table case.

### CRM - 10

As CRM - 9, but EBS instead of parity errors in the erroneous cells.

### CMP - 3

Catalogue for test of LCS and UCS when input is taken from magnetic tape. The lower table part is stored in cells 1 - 63 and the upper table part is stored from 65 - 127. In this case addition of 64 will take place when the UCS is derived. The catalogue is built up as follows:

| Value of input | Lower Table         |          | Upper Table |          |
|----------------|---------------------|----------|-------------|----------|
|                | cell No.            | contents | cell No.    | contents |
| not existing   | 0                   | parity   | 0 + 64      | parity   |
| 1              | 1                   | UCS      | 1 + 64      | parity   |
| 2              | 2                   | parity   | 2 + 64      | DEL      |
| 3              | 3                   | parity   | 3 + 64      | LCS      |
| 4              | 4                   | DEL      | 4 + 64      | parity   |
| 5              | 5                   | UCS      | 5 + 64      | parity   |
| 6              | 6                   | parity   | 6 + 64      | DEL      |
| 7              | 7                   | parity   | 7 + 64      | LCS      |
| 8              | 8                   | DEL      | 8 + 64      | parity   |
| -              | -                   | -        | -           | -        |
| -              | -                   | -        | -           | -        |
| 62             | 62                  | parity   | 62 + 64     | DEL      |
| 62             | 63                  | parity   | 63 + 64     | LCS      |
| not existing   | all contains parity |          |             |          |

In case of error (i.e. ERROR it lit) the AR-register positions 0 - 5 contains the input character and AR 6 = 1, if 64 has been added in the lower table case and AR 6 = 0, if 64 has not been added in the upper table case.



CMP - 7

As CMP - 3, but with EBS instead of parity errors.

CMP - 17

Catalogue for production of magnetic tape to be used in connection with CMP - 7. The data tape used is D - 1. The blocks produced consist of the 63 values 1 - 63. The catalogue is built up as follows:

|                |        |
|----------------|--------|
| value fo input | output |
| 1 - 63         | 1 - 63 |
| 64 - 125       | 1 - 63 |
| 127 - 189      | 1 - 63 |
| 190 - 252      | 1 - 63 |
| 253            | DEL    |
| 254            | DEL    |
| 255            | DEL    |

BASA is to obtain the correct block length, set to 961.

A few catalogues have been constructed for testing the selection of input and output and conversion mode. These catalogues all have the length 32. The necessary catalogues are listed below:

| CATALOGUE | INPUT LAMPS   | OUTPUT LAMPS  | MODE     | CU     |
|-----------|---------------|---------------|----------|--------|
| C2        | Magnetic tape | Printer       | CDC, BCD | 111111 |
| C3        | Paper tape    | Magnetic tape | Binary   | 000000 |

As seen from the list the catalogues are clear nonsense from the users point of view, they can only be used as test of the controlunit.

CRP - 1

Catalogue for test of the line printed. The data tape D - 2 is used, and the correct printout is given in the appendix.

CRP - 1 CDC

Catalogue for test of printout in the special CDC - mode. The data tape used is D - 3. The correct printout is given in the appendix.

CRM - 11, CRM - 12, CRM - 13, CRM - 15, CRM - 16

Catalogues for test of reading of OLIVETTI six track paper tape. Each catalogue test reading of one track and the output to magnetic tape will be the value of that track in the following manner:

| catalogue | test of track | output | from catalogue cell No. | data tape |
|-----------|---------------|--------|-------------------------|-----------|
| CRM - 11  | A             | 1      | 1                       | D4        |
| CRM - 12  | B             | 2      | 2                       | D5        |
| CRM - 13  | C             | 4      | 4                       | D6        |
| CRM - 14  | D             | 8      | 8                       | D7        |
| CRM - 15  | E             | 16     | 16                      | D8        |
| CRM - 16  | F             | 32     | 32                      | D9        |

All other cells in the catalogue than the test-cell with the output information contain parity errors and references to these due to erroneous reading will cause the converter to stop in ERROR. In this moment contents of the AR-register is the erroneous character.

C - 4

Catalogue tape for test of OLIVETTI reading. The tape should be read with the parity button depressed. After reading of the tape ERROR shall remain unlit, otherwise there was a length error, and the number of missing characters can be calculated as

$$\text{missing} = 32 - (\text{contents of OC 0} - 4)$$

This number is the number of missing characters modulo 32.

D - 1

A 8-track data tape consisting of four sets of characters. Each set holds the characters with values from 1 up to 255. The paper tape is an infinite loop. Using this tape as data for the catalogues, one obtain that references to all cells in the catalogue can be made. Cell 0 will be the only cell to which no reference can be made.

D - 2

Data tape for test of the line printer. The tape is used in connection with some of the catalogues and will give output of all types of relevant information to all print positions on the line printer.

D - 3

Data tape for test of the CDC printing on the line printer.

D - 4, D - 5, D - 6, D - 7, D - 8, D - 9

Infinite data tapes for test of reading of OLIVETTI six track paper tape.  
Each tape has holes on one single track.

D - 10

Data tape for CRM - 8 and CRM - 8 BCD. This infinite tape consists of four sets of characters each set running from 1 to 251.

# BUFFERTEST 2

(A 203)

hp-knap 121

1  
klar  
1w3  
ae4  
aed

KA = 1

repeat with same parameters

0000

number of errors by = 16 (eller By 8)

0000

0000

0000000000x0000000000x0000000101x0111001000x00

00000000001x0000000000x0000000101x0111001000x00 bf adr 0001

0000000000x0000000000x0000010000x0100101001x00

00000000001x0000000000x0000010000x0100101001x00 bf adr 0002

1. correct contents of the celle
- 2.read out contents

AD 9-10-11  
AD 6-7-8  
AD 3-4-5

bf adr octal code

AD 0-1-2

by = 8

start r1 := 512

Step r1 := 525 nois KB

0  
hp-knap -499

C D C 1

(TAPE TEST 1)

1      *hp-knap*  
st. nr=1  
klar  
wer  
dfr } *parametre*  
drf }

status 000011 001111 111111 110000 000000 000000 000000

p. 0000  
0000

st. nr=2  
klar  
as  
sd } *parametre*  
sd }

status 000011 001111 111111 110000 000000 000000 000000

p. 0000  
0000

status 100011 000010 110101 000000 000000 000000 000000

p. 0001

000000 100011 111101 011110 000010 110111 001000  
000000 100010 111101 011110 000010 110111 001000    bf adr 1323

000011 000000 000001 100000 101001 010010 110000  
000000 000000 000000 000000 000011 000000 000000    bf adr 1324

000010 111110 001110 011110 000001 001001 110000  
000000 000000 000000 000000 000000 000000 000000    bf adr 1325

as described at buffertest 2

p. = number of par. errors

st. nr. = 1 - 2 - 3

start r 1 : = 512

### BUFFERTEST - 3

Program for test of the buffer store according to the principles of test B10 and test B11.

#### INPUT AND START

~~The program is published in condensed form to be read in by track 0.~~  
After input the program types <buffertest - 3> and stops if KB is one. In the stopsituation it is possible to set the bits 0 - 39 of the R-reg. and RA and RB in the Indicator then these bits will be used in the test.

#### BUILD IN TEST BITS

The build in test bits is taken in sequence from an array of the following form

1,1,1,1,....1,0,0,0,0,....0,1,1,1,1,....1  
                    42 bits        42 bits        41 bits

This means that each cell is tested with 84 different bit patterns.

#### ERROR REACTIONS

The normal condition for KA is KA=0. In this case there will only be reaction from the program at the end of one complete testcycle.

The reaction will be:

NO ERRORS: The program types <CR, ok> and hoots in 5 second with the frequency 1000 c/s.

ERROR: The program types <CR, -> and hoots in 5 second with alternating frequency :  
(950 c/s and 1100 c/s).

KA=1 will cause the program to stop when an error is detected. There is four possible stop points in the program:

- 1) r1 = 138  
Informationerror, R: = bufferaddress 39
- 2) r1 = 140  
Informationerror, R: = wrong information  
M: = correct information
- 3) r1 = 143  
Error in marks, R 8-9: = correct marks,  
In RA, RB : = wrong marks
- 4) r1 = 148  
Error in marks, R: = bufferaddress 39.

Jan F. Hadser  
16.I.67

# INTEGER <=> BINARY CONVERSION

|    |             |       |    |             |      |     |                |      |
|----|-------------|-------|----|-------------|------|-----|----------------|------|
| 0  | .....       | -1024 | 50 | ....11...1. | -974 | 100 | ...11...1..    | -924 |
| 1  | .....1      | -1023 | 51 | ....11...11 | -973 | 101 | ...11...1.1    | -923 |
| 2  | .....1.     | -1022 | 52 | ....11.1..  | -972 | 102 | ...11...11.    | -922 |
| 3  | .....11     | -1021 | 53 | ....11.1.1  | -971 | 103 | ...11...111    | -921 |
| 4  | .....1..    | -1020 | 54 | ....11.11.  | -970 | 104 | ...11.1....    | -920 |
| 5  | .....1.1    | -1019 | 55 | ....11.111  | -969 | 105 | ...11.1..1     | -919 |
| 6  | .....11.    | -1018 | 56 | ....111...  | -968 | 106 | ...11.1.1.     | -918 |
| 7  | .....111    | -1017 | 57 | ....111...1 | -967 | 107 | ...11.1.11     | -917 |
| 8  | .....1...   | -1016 | 58 | ....111.1.  | -966 | 108 | ...11.11..     | -916 |
| 9  | .....1..1   | -1015 | 59 | ....111.11  | -965 | 109 | ...11.11.1     | -915 |
| 10 | .....1.1.   | -1014 | 60 | ....1111..  | -964 | 110 | ...11.111.     | -914 |
| 11 | .....1.11   | -1013 | 61 | ....1111.1  | -963 | 111 | ...11.1111     | -913 |
| 12 | .....11..   | -1012 | 62 | ....11111.  | -962 | 112 | ...111....     | -912 |
| 13 | .....11.1   | -1011 | 63 | ....111111  | -961 | 113 | ...111...1     | -911 |
| 14 | .....111.   | -1010 | 64 | ...1.....   | -960 | 114 | ...111...1.    | -910 |
| 15 | .....1111   | -1009 | 65 | ...1.....1  | -959 | 115 | ...111...11    | -909 |
| 16 | .....1....  | -1008 | 66 | ...1.....1. | -958 | 116 | ...111...1..   | -908 |
| 17 | .....1...1  | -1007 | 67 | ...1....11  | -957 | 117 | ...111...1.1   | -907 |
| 18 | .....1..1.  | -1006 | 68 | ...1...1..  | -956 | 118 | ...111...11.   | -906 |
| 19 | .....1..11  | -1005 | 69 | ...1...1.1  | -955 | 119 | ...111...111   | -905 |
| 20 | .....1.1..  | -1004 | 70 | ...1...11.  | -954 | 120 | ...1111...     | -904 |
| 21 | .....1.1.1  | -1003 | 71 | ...1...111  | -953 | 121 | ...1111...1    | -903 |
| 22 | .....1.11.  | -1002 | 72 | ...1..1...  | -952 | 122 | ...1111...1.   | -902 |
| 23 | .....1.111  | -1001 | 73 | ...1..1..1  | -951 | 123 | ...1111...11   | -901 |
| 24 | .....11...  | -1000 | 74 | ...1..1.1.  | -950 | 124 | ...11111..     | -900 |
| 25 | .....11...1 | -999  | 75 | ...1..1.11  | -949 | 125 | ...11111.1     | -899 |
| 26 | .....11.1.  | -998  | 76 | ...1..11..  | -948 | 126 | ...111111.     | -898 |
| 27 | .....11.11  | -997  | 77 | ...1..11.1  | -947 | 127 | ...1111111     | -897 |
| 28 | .....111..  | -996  | 78 | ...1..111.  | -946 | 128 | ...1.....      | -896 |
| 29 | .....111.1  | -995  | 79 | ...1..1111  | -945 | 129 | ...1.....1     | -895 |
| 30 | .....1111.  | -994  | 80 | ...1.1....  | -944 | 130 | ...1.....1.    | -894 |
| 31 | .....11111  | -993  | 81 | ...1.1...1  | -943 | 131 | ...1.....11    | -893 |
| 32 | ....1.....  | -992  | 82 | ...1.1...1. | -942 | 132 | ...1....1..    | -892 |
| 33 | ....1....1  | -991  | 83 | ...1.1...11 | -941 | 133 | ...1....1.1    | -891 |
| 34 | ....1...1.  | -990  | 84 | ...1.1.1..  | -940 | 134 | ...1....11.    | -890 |
| 35 | ....1...11  | -989  | 85 | ...1.1.1.1  | -939 | 135 | ...1....111    | -889 |
| 36 | ....1..1..  | -988  | 86 | ...1.1.11.  | -938 | 136 | ...1...1...    | -888 |
| 37 | ....1..1.1  | -987  | 87 | ...1.1.111  | -937 | 137 | ...1...1...1   | -887 |
| 38 | ....1..11.  | -986  | 88 | ...1.11...  | -936 | 138 | ...1...1.1.    | -886 |
| 39 | ....1..111  | -985  | 89 | ...1.11...1 | -935 | 139 | ...1...1.11    | -885 |
| 40 | ....1.1...  | -984  | 90 | ...1.11.1.  | -934 | 140 | ...1...11..    | -884 |
| 41 | ....1.1...1 | -983  | 91 | ...1.11.11  | -933 | 141 | ...1...11.1    | -883 |
| 42 | ....1.1.1.  | -982  | 92 | ...1.111..  | -932 | 142 | ...1...111.    | -882 |
| 43 | ....1.1.11  | -981  | 93 | ...1.111.1  | -931 | 143 | ...1...1111    | -881 |
| 44 | ....1.11..  | -980  | 94 | ...1.1111.  | -930 | 144 | ...1...1....   | -880 |
| 45 | ....1.11.1  | -979  | 95 | ...1.11111  | -929 | 145 | ...1...1...1   | -879 |
| 46 | ....1.111.  | -978  | 96 | ...11.....  | -928 | 146 | ...1...1...1.  | -878 |
| 47 | ....1.1111  | -977  | 97 | ...11....1  | -927 | 147 | ...1...1...11  | -877 |
| 48 | ....11....  | -976  | 98 | ...11...1.  | -926 | 148 | ...1...1...1.  | -876 |
| 49 | ....11...1  | -975  | 99 | ...11...11  | -925 | 149 | ...1...1...1.1 | -875 |

|     |                |      |
|-----|----------------|------|
| 150 | ..1..1.11.     | -874 |
| 151 | ..1..1.111     | -873 |
| 152 | ..1..11...     | -872 |
| 153 | ..1..11..1     | -871 |
| 154 | ..1..11.1.     | -870 |
| 155 | ..1..11.11     | -869 |
| 156 | ..1..111..     | -868 |
| 157 | ..1..111.1     | -867 |
| 158 | ..1..1111.     | -866 |
| 159 | ..1..11111     | -865 |
| 160 | ..1.1.....     | -864 |
| 161 | ..1.1.....1    | -863 |
| 162 | ..1.1.....1.   | -862 |
| 163 | ..1.1.....11   | -861 |
| 164 | ..1.1.....1..  | -860 |
| 165 | ..1.1.....1.1  | -859 |
| 166 | ..1.1.....11.  | -858 |
| 167 | ..1.1.....111  | -857 |
| 168 | ..1.1.....1... | -856 |
| 169 | ..1.1.....1..1 | -855 |
| 170 | ..1.1.....1.1. | -854 |
| 171 | ..1.1.....1.11 | -853 |
| 172 | ..1.1.....11.. | -852 |
| 173 | ..1.1.....11.1 | -851 |
| 174 | ..1.1.....111. | -850 |
| 175 | ..1.1.....1111 | -849 |
| 176 | ..1.11.....    | -848 |
| 177 | ..1.11.....1   | -847 |
| 178 | ..1.11.....1.  | -846 |
| 179 | ..1.11.....11  | -845 |
| 180 | ..1.11.....1.. | -844 |
| 181 | ..1.11.....1.1 | -843 |
| 182 | ..1.11.....11. | -842 |
| 183 | ..1.11.....111 | -841 |
| 184 | ..1.111....    | -840 |
| 185 | ..1.111...1    | -839 |
| 186 | ..1.111...1.   | -838 |
| 187 | ..1.111...11   | -837 |
| 188 | ..1.1111..     | -836 |
| 189 | ..1.1111.1     | -835 |
| 190 | ..1.11111.     | -834 |
| 191 | ..1.111111     | -833 |
| 192 | ..11.....      | -832 |
| 193 | ..11.....1     | -831 |
| 194 | ..11.....1.    | -830 |
| 195 | ..11.....11    | -829 |
| 196 | ..11.....1..   | -828 |
| 197 | ..11.....1.1   | -827 |
| 198 | ..11.....11.   | -826 |
| 199 | ..11.....111   | -825 |

|     |              |      |
|-----|--------------|------|
| 200 | ..11...1...  | -824 |
| 201 | ..11...1..1  | -823 |
| 202 | ..11...1.1.  | -822 |
| 203 | ..11...1.11  | -821 |
| 204 | ..11...11..  | -820 |
| 205 | ..11...11.1  | -819 |
| 206 | ..11...111.  | -818 |
| 207 | ..11...1111  | -817 |
| 208 | ..11.1....   | -816 |
| 209 | ..11.1...1   | -815 |
| 210 | ..11.1...1.  | -814 |
| 211 | ..11.1...11  | -813 |
| 212 | ..11.1.1..   | -812 |
| 213 | ..11.1.1.1   | -811 |
| 214 | ..11.1.11.   | -810 |
| 215 | ..11.1.111   | -809 |
| 216 | ..11.11...   | -808 |
| 217 | ..11.11...1  | -807 |
| 218 | ..11.11.1.   | -806 |
| 219 | ..11.11.11   | -805 |
| 220 | ..11.111..   | -804 |
| 221 | ..11.111.1   | -803 |
| 222 | ..11.1111.   | -802 |
| 223 | ..11.11111   | -801 |
| 224 | ..111.....   | -800 |
| 225 | ..111.....1  | -799 |
| 226 | ..111.....1. | -798 |
| 227 | ..111.....11 | -797 |
| 228 | ..111...1..  | -796 |
| 229 | ..111...1.1  | -795 |
| 230 | ..111...11.  | -794 |
| 231 | ..111...111  | -793 |
| 232 | ..111.1...   | -792 |
| 233 | ..111.1...1  | -791 |
| 234 | ..111.1.1.   | -790 |
| 235 | ..111.1.11   | -789 |
| 236 | ..111.11..   | -788 |
| 237 | ..111.11.1   | -787 |
| 238 | ..111.111.   | -786 |
| 239 | ..111.1111   | -785 |
| 240 | ..1111....   | -784 |
| 241 | ..1111...1   | -783 |
| 242 | ..1111...1.  | -782 |
| 243 | ..1111...11  | -781 |
| 244 | ..1111.1..   | -780 |
| 245 | ..1111.1.1   | -779 |
| 246 | ..1111.11.   | -778 |
| 247 | ..1111.111   | -777 |
| 248 | ..11111...   | -776 |
| 249 | ..11111...1  | -775 |

|     |             |      |
|-----|-------------|------|
| 250 | ..11111.1.  | -774 |
| 251 | ..11111.11  | -773 |
| 252 | ..111111..  | -772 |
| 253 | ..111111.1  | -771 |
| 254 | ..1111111.  | -770 |
| 255 | ..11111111  | -769 |
| 256 | .1.....     | -768 |
| 257 | .1.....1    | -767 |
| 258 | .1.....1.   | -766 |
| 259 | .1.....11   | -765 |
| 260 | .1.....1..  | -764 |
| 261 | .1.....1.1  | -763 |
| 262 | .1.....11.  | -762 |
| 263 | .1.....111  | -761 |
| 264 | .1....1...  | -760 |
| 265 | .1....1...1 | -759 |
| 266 | .1....1.1.  | -758 |
| 267 | .1....1.11  | -757 |
| 268 | .1....11..  | -756 |
| 269 | .1....11.1  | -755 |
| 270 | .1....111.  | -754 |
| 271 | .1....1111  | -753 |
| 272 | .1...1....  | -752 |
| 273 | .1...1...1  | -751 |
| 274 | .1...1...1. | -750 |
| 275 | .1...1...11 | -749 |
| 276 | .1...1.1..  | -748 |
| 277 | .1...1.1.1  | -747 |
| 278 | .1...1.11.  | -746 |
| 279 | .1...1.111  | -745 |
| 280 | .1...11...  | -744 |
| 281 | .1...11...1 | -743 |
| 282 | .1...11.1.  | -742 |
| 283 | .1...11.11  | -741 |
| 284 | .1...111..  | -740 |
| 285 | .1...111.1  | -739 |
| 286 | .1...1111.  | -738 |
| 287 | .1...11111  | -737 |
| 288 | .1..1.....  | -736 |
| 289 | .1..1....1  | -735 |
| 290 | .1..1...1.  | -734 |
| 291 | .1..1...11  | -733 |
| 292 | .1..1...1.. | -732 |
| 293 | .1..1...1.1 | -731 |
| 294 | .1..1...11. | -730 |
| 295 | .1..1...111 | -729 |
| 296 | .1..1.1...  | -728 |
| 297 | .1..1.1...1 | -727 |
| 298 | .1..1.1.1.  | -726 |
| 299 | .1..1.1.11  | -725 |



|     |             |      |
|-----|-------------|------|
| 300 | .1..1.11..  | -724 |
| 301 | .1..1.11.1  | -723 |
| 302 | .1..1.111.  | -722 |
| 303 | .1..1.1111  | -721 |
| 304 | .1..11....  | -720 |
| 305 | .1..11...1  | -719 |
| 306 | .1..11..1.  | -718 |
| 307 | .1..11...11 | -717 |
| 308 | .1..11.1..  | -716 |
| 309 | .1..11.1.1  | -715 |
| 310 | .1..11.11.  | -714 |
| 311 | .1..11.111  | -713 |
| 312 | .1..111.... | -712 |
| 313 | .1..111..1  | -711 |
| 314 | .1..111.1.  | -710 |
| 315 | .1..111.11  | -709 |
| 316 | .1..1111..  | -708 |
| 317 | .1..1111.1  | -707 |
| 318 | .1..11111.  | -706 |
| 319 | .1..111111  | -705 |
| 320 | .1.1.....   | -704 |
| 321 | .1.1.....1  | -703 |
| 322 | .1.1.....1. | -702 |
| 323 | .1.1.....11 | -701 |
| 324 | .1.1....1.. | -700 |
| 325 | .1.1....1.1 | -699 |
| 326 | .1.1....11. | -698 |
| 327 | .1.1....111 | -697 |
| 328 | .1.1...1... | -696 |
| 329 | .1.1...1..1 | -695 |
| 330 | .1.1...1.1. | -694 |
| 331 | .1.1...1.11 | -693 |
| 332 | .1.1...11.. | -692 |
| 333 | .1.1...11.1 | -691 |
| 334 | .1.1...111. | -690 |
| 335 | .1.1...1111 | -689 |
| 336 | .1.1.1....  | -688 |
| 337 | .1.1.1...1  | -687 |
| 338 | .1.1.1..1.  | -686 |
| 339 | .1.1.1...11 | -685 |
| 340 | .1.1.1.1..  | -684 |
| 341 | .1.1.1.1.1  | -683 |
| 342 | .1.1.1.11.  | -682 |
| 343 | .1.1.1.111  | -681 |
| 344 | .1.1.11.... | -680 |
| 345 | .1.1.11...1 | -679 |
| 346 | .1.1.11.1.  | -678 |
| 347 | .1.1.11.11  | -677 |
| 348 | .1.1.111..  | -676 |
| 349 | .1.1.111.1  | -675 |

|     |             |      |
|-----|-------------|------|
| 350 | .1.1.1111.  | -674 |
| 351 | .1.1.11111  | -673 |
| 352 | .1.11.....  | -672 |
| 353 | .1.11....1  | -671 |
| 354 | .1.11...1.  | -670 |
| 355 | .1.11...11  | -669 |
| 356 | .1.11..1..  | -668 |
| 357 | .1.11..1.1  | -667 |
| 358 | .1.11..11.  | -666 |
| 359 | .1.11..111  | -665 |
| 360 | .1.11.1...  | -664 |
| 361 | .1.11.1..1  | -663 |
| 362 | .1.11.1.1.  | -662 |
| 363 | .1.11.1.11  | -661 |
| 364 | .1.11.11..  | -660 |
| 365 | .1.11.11.1  | -659 |
| 366 | .1.11.111.  | -658 |
| 367 | .1.11.1111  | -657 |
| 368 | .1.111....  | -656 |
| 369 | .1.111...1  | -655 |
| 370 | .1.111..1.  | -654 |
| 371 | .1.111..11  | -653 |
| 372 | .1.111.1..  | -652 |
| 373 | .1.111.1.1  | -651 |
| 374 | .1.111.11.  | -650 |
| 375 | .1.111.111  | -649 |
| 376 | .1.1111.... | -648 |
| 377 | .1.1111..1  | -647 |
| 378 | .1.1111.1.  | -646 |
| 379 | .1.1111.11  | -645 |
| 380 | .1.11111..  | -644 |
| 381 | .1.11111.1  | -643 |
| 382 | .1.111111.  | -642 |
| 383 | .1.1111111  | -641 |
| 384 | .11.....    | -640 |
| 385 | .11.....1   | -639 |
| 386 | .11.....1.  | -638 |
| 387 | .11.....11  | -637 |
| 388 | .11....1..  | -636 |
| 389 | .11....1.1  | -635 |
| 390 | .11....11.  | -634 |
| 391 | .11....111  | -633 |
| 392 | .11...1...  | -632 |
| 393 | .11...1..1  | -631 |
| 394 | .11...1.1.  | -630 |
| 395 | .11...1.11  | -629 |
| 396 | .11...11..  | -628 |
| 397 | .11...11.1  | -627 |
| 398 | .11...111.  | -626 |
| 399 | .11...1111  | -625 |

|     |              |      |
|-----|--------------|------|
| 400 | .11...1....  | -624 |
| 401 | .11...1...1  | -623 |
| 402 | .11...1..1.  | -622 |
| 403 | .11...1..11  | -621 |
| 404 | .11...1.1..  | -620 |
| 405 | .11...1.1.1  | -619 |
| 406 | .11...1.11.  | -618 |
| 407 | .11...1.111  | -617 |
| 408 | .11...11.... | -616 |
| 409 | .11...11...1 | -615 |
| 410 | .11...11.1.  | -614 |
| 411 | .11...11.11  | -613 |
| 412 | .11...111..  | -612 |
| 413 | .11...111.1  | -611 |
| 414 | .11...1111.  | -610 |
| 415 | .11...11111  | -609 |
| 416 | .11.1.....   | -608 |
| 417 | .11.1....1   | -607 |
| 418 | .11.1...1.   | -606 |
| 419 | .11.1...11   | -605 |
| 420 | .11.1..1..   | -604 |
| 421 | .11.1..1.1   | -603 |
| 422 | .11.1..11.   | -602 |
| 423 | .11.1..111   | -601 |
| 424 | .11.1.1...   | -600 |
| 425 | .11.1.1..1   | -599 |
| 426 | .11.1.1.1.   | -598 |
| 427 | .11.1.1.11   | -597 |
| 428 | .11.1.11..   | -596 |
| 429 | .11.1.11.1   | -595 |
| 430 | .11.1.111.   | -594 |
| 431 | .11.1.1111   | -593 |
| 432 | .11.11....   | -592 |
| 433 | .11.11...1   | -591 |
| 434 | .11.11..1.   | -590 |
| 435 | .11.11..11   | -589 |
| 436 | .11.11.1..   | -588 |
| 437 | .11.11.1.1   | -587 |
| 438 | .11.11.11.   | -586 |
| 439 | .11.11.111   | -585 |
| 440 | .11.111...   | -584 |
| 441 | .11.111..1   | -583 |
| 442 | .11.111.1.   | -582 |
| 443 | .11.111.11   | -581 |
| 444 | .11.1111..   | -580 |
| 445 | .11.1111.1   | -579 |
| 446 | .11.11111.   | -578 |
| 447 | .11.111111   | -577 |
| 448 | .111.....    | -576 |
| 449 | .111.....1   | -575 |

|     |              |      |
|-----|--------------|------|
| 450 | .1111....1.  | -574 |
| 451 | .1111....11  | -573 |
| 452 | .1111....1.. | -572 |
| 453 | .1111....1.1 | -571 |
| 454 | .1111....11. | -570 |
| 455 | .1111....111 | -569 |
| 456 | .1111..1.... | -568 |
| 457 | .1111..1..1  | -567 |
| 458 | .1111..1.1.  | -566 |
| 459 | .1111..1.11  | -565 |
| 460 | .1111..11..  | -564 |
| 461 | .1111..11.1  | -563 |
| 462 | .1111..111.  | -562 |
| 463 | .1111..1111  | -561 |
| 4   | .1111.1....  | -560 |
| 465 | .1111.1...1  | -559 |
| 466 | .1111.1..1.  | -558 |
| 467 | .1111.1..11  | -557 |
| 468 | .1111.1.1..  | -556 |
| 469 | .1111.1.1.1  | -555 |
| 470 | .1111.1.11.  | -554 |
| 471 | .1111.1.111  | -553 |
| 472 | .1111.11...  | -552 |
| 473 | .1111.11..1  | -551 |
| 474 | .1111.11.1.  | -550 |
| 475 | .1111.11.11  | -549 |
| 476 | .1111.111..  | -548 |
| 477 | .1111.111.1  | -547 |
| 478 | .1111.1111.  | -546 |
| 479 | .1111.11111  | -545 |
| 480 | .1111.....   | -544 |
| 481 | .1111.....1  | -543 |
| 482 | .1111....1.  | -542 |
| 3   | .1111....11  | -541 |
| 484 | .1111..1..   | -540 |
| 485 | .1111..1.1   | -539 |
| 486 | .1111..11.   | -538 |
| 487 | .1111..111   | -537 |
| 488 | .1111.1....  | -536 |
| 489 | .1111.1..1   | -535 |
| 490 | .1111.1.1.   | -534 |
| 491 | .1111.1.11   | -533 |
| 492 | .1111.11..   | -532 |
| 493 | .1111.11.1   | -531 |
| 494 | .1111.111.   | -530 |
| 495 | .1111.1111   | -529 |
| 496 | .11111....   | -528 |
| 497 | .11111...1   | -527 |
| 498 | .11111..1.   | -526 |
| 499 | .11111..11   | -525 |

|     |             |      |
|-----|-------------|------|
| 500 | .11111.1..  | -524 |
| 501 | .11111.1.1  | -523 |
| 502 | .11111.11.  | -522 |
| 503 | .11111.111  | -521 |
| 504 | .111111...  | -520 |
| 505 | .111111..1  | -519 |
| 506 | .111111.1.  | -518 |
| 507 | .111111.11  | -517 |
| 508 | .1111111..  | -516 |
| 509 | .1111111.1  | -515 |
| 510 | .11111111.  | -514 |
| 511 | .111111111  | -513 |
| 512 | 1.....      | -512 |
| 513 | 1.....1     | -511 |
| 514 | 1.....1.    | -510 |
| 515 | 1.....11    | -509 |
| 516 | 1.....1..   | -508 |
| 517 | 1.....1.1   | -507 |
| 518 | 1.....11.   | -506 |
| 519 | 1.....111   | -505 |
| 520 | 1.....1...  | -504 |
| 521 | 1.....1..1  | -503 |
| 522 | 1.....1.1.  | -502 |
| 523 | 1.....1.11  | -501 |
| 524 | 1.....11..  | -500 |
| 525 | 1.....11.1  | -499 |
| 526 | 1.....111.  | -498 |
| 527 | 1.....1111  | -497 |
| 528 | 1.....1.... | -496 |
| 529 | 1.....1...1 | -495 |
| 530 | 1.....1..1. | -494 |
| 531 | 1.....1..11 | -493 |
| 532 | 1.....1.1.. | -492 |
| 533 | 1.....1.1.1 | -491 |
| 534 | 1.....1.11. | -490 |
| 535 | 1.....1.111 | -489 |
| 536 | 1.....11... | -488 |
| 537 | 1.....11..1 | -487 |
| 538 | 1.....11.1. | -486 |
| 539 | 1.....11.11 | -485 |
| 540 | 1.....111.. | -484 |
| 541 | 1.....111.1 | -483 |
| 542 | 1.....1111. | -482 |
| 543 | 1.....11111 | -481 |
| 544 | 1...1....   | -480 |
| 545 | 1...1....1  | -479 |
| 546 | 1...1...1.  | -478 |
| 547 | 1...1...11  | -477 |
| 548 | 1...1..1..  | -476 |
| 549 | 1...1..1.1  | -475 |

|     |             |      |
|-----|-------------|------|
| 550 | 1...1..11.  | -474 |
| 551 | 1...1..111  | -473 |
| 552 | 1...1.1...  | -472 |
| 553 | 1...1.1..1  | -471 |
| 554 | 1...1.1.1.  | -470 |
| 555 | 1...1.1.11  | -469 |
| 556 | 1...1.11..  | -468 |
| 557 | 1...1.11.1  | -467 |
| 558 | 1...1.111.  | -466 |
| 559 | 1...1.1111  | -465 |
| 560 | 1...11....  | -464 |
| 561 | 1...11...1  | -463 |
| 562 | 1...11...1. | -462 |
| 563 | 1...11...11 | -461 |
| 564 | 1...11.1..  | -460 |
| 565 | 1...11.1.1  | -459 |
| 566 | 1...11.11.  | -458 |
| 567 | 1...11.111  | -457 |
| 568 | 1...111...  | -456 |
| 569 | 1...111..1  | -455 |
| 570 | 1...111.1.  | -454 |
| 571 | 1...111.11  | -453 |
| 572 | 1...1111..  | -452 |
| 573 | 1...1111.1  | -451 |
| 574 | 1...11111.  | -450 |
| 575 | 1...111111  | -449 |
| 576 | 1..1.....   | -448 |
| 577 | 1..1.....1  | -447 |
| 578 | 1..1.....1. | -446 |
| 579 | 1..1.....11 | -445 |
| 580 | 1..1...1..  | -444 |
| 581 | 1..1...1.1  | -443 |
| 582 | 1..1...11.  | -442 |
| 583 | 1..1...111  | -441 |
| 584 | 1..1..1...  | -440 |
| 585 | 1..1..1..1  | -439 |
| 586 | 1..1..1.1.  | -438 |
| 587 | 1..1..1.11  | -437 |
| 588 | 1..1..11..  | -436 |
| 589 | 1..1..11.1  | -435 |
| 590 | 1..1..111.  | -434 |
| 591 | 1..1..1111  | -433 |
| 592 | 1..1.1....  | -432 |
| 593 | 1..1.1...1  | -431 |
| 594 | 1..1.1..1.  | -430 |
| 595 | 1..1.1..11  | -429 |
| 596 | 1..1.1.1..  | -428 |
| 597 | 1..1.1.1.1  | -427 |
| 598 | 1..1.1.11.  | -426 |
| 599 | 1..1.1.111  | -425 |

600 1..1.11... -424  
601 1..1.11..1 -423  
602 1..1.11.1. -422  
603 1..1.11.11 -421  
604 1..1.111.. -420  
605 1..1.111.1 -419  
606 1..1.1111. -418  
607 1..1.11111 -417  
608 1..11..... -416  
609 1..11....,1 -415  
610 1..11....1. -414  
611 1..11....11 -413  
612 1..11...1.. -412  
613 1..11...1.1 -411  
614 1..11...11. -410  
615 1..11...111 -409  
616 1..11.1... -408  
617 1..11.1..1 -407  
618 1..11.1.1. -406  
619 1..11.1.11 -405  
620 1..11.11.. -404  
621 1..11.11.1 -403  
622 1..11.111. -402  
623 1..11.1111 -401  
624 1..111..... -400  
625 1..111....1 -399  
626 1..111...1. -398  
627 1..111...11 -397  
628 1..111.1.. -396  
629 1..111.1.1 -395  
630 1..111.11. -394  
631 1..111.111 -393  
632 1..1111... -392  
633 1..1111...1 -391  
634 1..1111.1. -390  
635 1..1111.11 -389  
636 1..11111.. -388  
637 1..11111.1 -387  
638 1..111111. -386  
639 1..1111111 -385  
640 1.1..... -384  
641 1.1.....,1 -383  
642 1.1.....1. -382  
643 1.1.....11 -381  
644 1.1.....1.. -380  
645 1.1.....1.1 -379  
646 1.1.....11. -378  
647 1.1.....111 -377  
648 1.1...1... -376  
649 1.1...1..1 -375

650 1.1...1.1. -374  
651 1.1...1.11 -373  
652 1.1...11.. -372  
653 1.1...11.1 -371  
654 1.1...111. -370  
655 1.1...1111 -369  
656 1.1...1.... -368  
657 1.1...1...1 -367  
658 1.1...1..1. -366  
659 1.1...1..11 -365  
660 1.1...1.1.. -364  
661 1.1...1.1.1 -363  
662 1.1...1.11. -362  
663 1.1...1.111 -361  
664 1.1...11... -360  
665 1.1...11...1 -359  
666 1.1...11.1. -358  
667 1.1...11.11 -357  
668 1.1...111.. -356  
669 1.1...111.1 -355  
670 1.1...1111. -354  
671 1.1...11111 -353  
672 1.1.1..... -352  
673 1.1.1....,1 -351  
674 1.1.1...1. -350  
675 1.1.1...11 -349  
676 1.1.1...1.. -348  
677 1.1.1...1.1 -347  
678 1.1.1...11. -346  
679 1.1.1...111 -345  
680 1.1.1.1... -344  
681 1.1.1.1..1 -343  
682 1.1.1.1.1. -342  
683 1.1.1.1.11 -341  
684 1.1.1.11.. -340  
685 1.1.1.11.1 -339  
686 1.1.1.111. -338  
687 1.1.1.1111 -337  
688 1.1.11.... -336  
689 1.1.11...1 -335  
690 1.1.11...1. -334  
691 1.1.11...11 -333  
692 1.1.11.1.. -332  
693 1.1.11.1.1 -331  
694 1.1.11.11. -330  
695 1.1.11.111 -329  
696 1.1.111... -328  
697 1.1.111...1 -327  
698 1.1.111.1. -326  
699 1.1.111.11 -325

700 1.1.1111.. -324  
701 1.1.1111.1 -323  
702 1.1.11111. -322  
703 1.1.111111 -321  
704 1.11..... -320  
705 1.11....,1 -319  
706 1.11....1. -318  
707 1.11....11 -317  
708 1.11...1.. -316  
709 1.11...1.1 -315  
710 1.11...11. -314  
711 1.11...111 -313  
712 1.11..1... -312  
713 1.11..1...1 -311  
714 1.11..1.1. -310  
715 1.11..1.11 -309  
716 1.11..11.. -308  
717 1.11..11.1 -307  
718 1.11..111. -306  
719 1.11..1111 -305  
720 1.11.1.... -304  
721 1.11.1...1 -303  
722 1.11.1...1. -302  
723 1.11.1...11 -301  
724 1.11.1.1.. -300  
725 1.11.1.1.1 -299  
726 1.11.1.11. -298  
727 1.11.1.111 -297  
728 1.11.11... -296  
729 1.11.11...1 -295  
730 1.11.11.1. -294  
731 1.11.11.11 -293  
732 1.11.111.. -292  
733 1.11.111.1 -291  
734 1.11.1111. -290  
735 1.11.11111 -289  
736 1.111..... -288  
737 1.111....,1 -287  
738 1.111...1. -286  
739 1.111...11 -285  
740 1.111...1.. -284  
741 1.111...1.1 -283  
742 1.111...11. -282  
743 1.111...111 -281  
744 1.111.1... -280  
745 1.111.1..1 -279  
746 1.111.1.1. -278  
747 1.111.1.11 -277  
748 1.111.11.. -276  
749 1.111.11.1 -275

750 1.111.111. -274  
 751 1.111.1111 -273  
 752 1.1111.... -272  
 753 1.1111...1 -271  
 754 1.1111..1. -270  
 755 1.1111..11 -269  
 756 1.1111.1.. -268  
 757 1.1111.1,1 -267  
 758 1.1111.11. -266  
 759 1.1111.111 -265  
 760 1.11111... -264  
 761 1.11111..1 -263  
 762 1.11111.1. -262  
 763 1.11111.11 -261  
 764 1.111111.. -260  
 765 1.111111.1 -259  
 766 1.1111111. -258  
 767 1.11111111 -257  
 768 11..... -256  
 769 11.....1 -255  
 770 11.....1. -254  
 771 11.....11 -253  
 772 11.....1.. -252  
 773 11.....1.1 -251  
 774 11.....11. -250  
 775 11.....111 -249  
 776 11.....1... -248  
 777 11.....1..1 -247  
 778 11.....1.1. -246  
 779 11.....1.11 -245  
 780 11.....11.. -244  
 781 11.....11.1 -243  
 782 11.....111. -242  
 783 11.....1111 -241  
 784 11...1.... -240  
 785 11...1...1 -239  
 786 11...1..1. -238  
 787 11...1..11 -237  
 788 11...1.1.. -236  
 789 11...1.1.1 -235  
 790 11...1.11. -234  
 791 11...1.111 -233  
 792 11...11... -232  
 793 11...11..1 -231  
 794 11...11.1. -230  
 795 11...11.11 -229  
 796 11...111.. -228  
 797 11...111.1 -227  
 798 11...1111. -226  
 799 11...11111 -225

800 11..1..... -224  
 801 11..1....1 -223  
 802 11..1...1. -222  
 803 11..1...11 -221  
 804 11..1..1.. -220  
 805 11..1..1.1 -219  
 806 11..1..11. -218  
 807 11..1..111 -217  
 808 11..1.1... -216  
 809 11..1.1..1 -215  
 810 11..1.1.1. -214  
 811 11..1.1.11 -213  
 812 11..1.11.. -212  
 813 11..1.11.1 -211  
 814 11..1.111. -210  
 815 11..1.1111 -209  
 816 11..11.... -208  
 817 11..11...1 -207  
 818 11..11..1. -206  
 819 11..11..11 -205  
 820 11..11.1.. -204  
 821 11..11.1.1 -203  
 822 11..11.11. -202  
 823 11..11.111 -201  
 824 11..111... -200  
 825 11..111..1 -199  
 826 11..111.1. -198  
 827 11..111.11 -197  
 828 11..1111.. -196  
 829 11..1111.1 -195  
 830 11..11111. -194  
 831 11..111111 -193  
 832 11.1..... -192  
 833 11.1....1 -191  
 834 11.1....1. -190  
 835 11.1....11 -189  
 836 11.1...1.. -188  
 837 11.1...1.1 -187  
 838 11.1...11. -186  
 839 11.1...111 -185  
 840 11.1..1... -184  
 841 11.1..1..1 -183  
 842 11.1..1.1. -182  
 843 11.1..1.11 -181  
 844 11.1..11.. -180  
 845 11.1..11.1 -179  
 846 11.1..111. -178  
 847 11.1..1111 -177  
 848 11.1.1.... -176  
 849 11.1.1...1 -175

850 11.1.1..1. -174  
 851 11.1.1..11 -173  
 852 11.1.1.1.. -172  
 853 11.1.1.1.1 -171  
 854 11.1.1.11. -170  
 855 11.1.1.111 -169  
 856 11.1.11... -168  
 857 11.1.11..1 -167  
 858 11.1.11.1. -166  
 859 11.1.11.11 -165  
 860 11.1.111.. -164  
 861 11.1.111.1 -163  
 862 11.1.1111. -162  
 863 11.1.11111 -161  
 864 11.11..... -160  
 865 11.11....1 -159  
 866 11.11...1. -158  
 867 11.11...11 -157  
 868 11.11..1.. -156  
 869 11.11..1.1 -155  
 870 11.11..11. -154  
 871 11.11..111 -153  
 872 11.11.1... -152  
 873 11.11.1..1 -151  
 874 11.11.1.1. -150  
 875 11.11.1.11 -149  
 876 11.11.11.. -148  
 877 11.11.11.1 -147  
 878 11.11.111. -146  
 879 11.11.1111 -145  
 880 11.111... -144  
 881 11.111...1 -143  
 882 11.111..1. -142  
 883 11.111..11 -141  
 884 11.111.1.. -140  
 885 11.111.1.1 -139  
 886 11.111.11. -138  
 887 11.111.111 -137  
 888 11.1111... -136  
 889 11.1111..1 -135  
 890 11.1111.1. -134  
 891 11.1111.11 -133  
 892 11.11111.. -132  
 893 11.11111.1 -131  
 894 11.111111. -130  
 895 11.1111111 -129  
 896 111..... -128  
 897 111....1 -127  
 898 111....1. -126  
 899 111....11 -125

|     |             |      |
|-----|-------------|------|
| 900 | 111....1..  | -124 |
| 901 | 111....1.1  | -123 |
| 902 | 111....11.  | -122 |
| 903 | 111....111  | -121 |
| 904 | 111...1...  | -120 |
| 905 | 111...1..1  | -119 |
| 906 | 111...1.1.  | -118 |
| 907 | 111...1.11  | -117 |
| 908 | 111...11..  | -116 |
| 909 | 111...11.1  | -115 |
| 910 | 111...111.  | -114 |
| 911 | 111...1111  | -113 |
| 912 | 111..1....  | -112 |
| 913 | 111..1...1  | -111 |
| 14  | 111..1...1. | -110 |
| 915 | 111..1...11 | -109 |
| 916 | 111..1.1..  | -108 |
| 917 | 111..1.1.1  | -107 |
| 918 | 111..1.11.  | -106 |
| 919 | 111..1.111  | -105 |
| 920 | 111..11...  | -104 |
| 921 | 111..11...1 | -103 |
| 922 | 111..11.1.  | -102 |
| 923 | 111..11.11  | -101 |
| 924 | 111..111..  | -100 |
| 925 | 111..111.1  | -99  |
| 926 | 111..1111.  | -98  |
| 927 | 111..11111  | -97  |
| 928 | 111.1.....  | -96  |
| 929 | 111.1....1  | -95  |
| 930 | 111.1...1.  | -94  |
| 931 | 111.1...11  | -93  |
| 932 | 111.1..1..  | -92  |
| 33  | 111.1..1.1  | -91  |
| 934 | 111.1..11.  | -90  |
| 935 | 111.1..111  | -89  |
| 936 | 111.1.1...  | -88  |
| 937 | 111.1.1..1  | -87  |
| 938 | 111.1.1.1.  | -86  |
| 939 | 111.1.1.11  | -85  |
| 940 | 111.1.11..  | -84  |
| 941 | 111.1.11.1  | -83  |
| 942 | 111.1.111.  | -82  |
| 943 | 111.1.1111  | -81  |
| 944 | 111.11....  | -80  |
| 945 | 111.11...1  | -79  |
| 946 | 111.11..1.  | -78  |
| 947 | 111.11..11  | -77  |
| 948 | 111.11.1..  | -76  |
| 949 | 111.11.1.1  | -75  |

|     |            |     |
|-----|------------|-----|
| 950 | 111.11.11. | -74 |
| 951 | 111.11.111 | -73 |
| 952 | 111.111... | -72 |
| 953 | 111.111..1 | -71 |
| 954 | 111.111.1. | -70 |
| 955 | 111.111.11 | -69 |
| 956 | 111.1111.. | -68 |
| 957 | 111.1111.1 | -67 |
| 958 | 111.11111. | -66 |
| 959 | 111.111111 | -65 |
| 960 | 1111.....  | -64 |
| 961 | 1111.....1 | -63 |
| 962 | 1111....1. | -62 |
| 963 | 1111....11 | -61 |
| 964 | 1111...1.. | -60 |
| 965 | 1111...1.1 | -59 |
| 966 | 1111...11. | -58 |
| 967 | 1111...111 | -57 |
| 968 | 1111..1... | -56 |
| 969 | 1111..1..1 | -55 |
| 970 | 1111..1.1. | -54 |
| 971 | 1111..1.11 | -53 |
| 972 | 1111..11.. | -52 |
| 973 | 1111..11.1 | -51 |
| 974 | 1111..111. | -50 |
| 975 | 1111..1111 | -49 |
| 976 | 1111.1.... | -48 |
| 977 | 1111.1...1 | -47 |
| 978 | 1111.1..1. | -46 |
| 979 | 1111.1..11 | -45 |
| 980 | 1111.1.1.. | -44 |
| 981 | 1111.1.1.1 | -43 |
| 982 | 1111.1.11. | -42 |
| 983 | 1111.1.111 | -41 |
| 984 | 1111.11... | -40 |
| 985 | 1111.11..1 | -39 |
| 986 | 1111.11.1. | -38 |
| 987 | 1111.11.11 | -37 |
| 988 | 1111.111.. | -36 |
| 989 | 1111.111.1 | -35 |
| 990 | 1111.1111. | -34 |
| 991 | 1111.11111 | -33 |
| 992 | 11111..... | -32 |
| 993 | 11111....1 | -31 |
| 994 | 11111...1. | -30 |
| 995 | 11111...11 | -29 |
| 996 | 11111..1.. | -28 |
| 997 | 11111..1.1 | -27 |
| 998 | 11111..11. | -26 |
| 999 | 11111..111 | -25 |

|      |             |     |
|------|-------------|-----|
| 1000 | 11111.1...  | -24 |
| 1001 | 11111.1..1  | -23 |
| 1002 | 11111.1.1.  | -22 |
| 1003 | 11111.1.11  | -21 |
| 1004 | 11111.11..  | -20 |
| 1005 | 11111.11.1  | -19 |
| 1006 | 11111.111.  | -18 |
| 1007 | 11111.1111  | -17 |
| 1008 | 111111....  | -16 |
| 1009 | 111111...1  | -15 |
| 1010 | 111111...1. | -14 |
| 1011 | 111111...11 | -13 |
| 1012 | 111111.1..  | -12 |
| 1013 | 111111.1.1  | -11 |
| 1014 | 111111.11.  | -10 |
| 1015 | 111111.111  | -9  |
| 1016 | 1111111...  | -8  |
| 1017 | 1111111..1  | -7  |
| 1018 | 1111111.1.  | -6  |
| 1019 | 1111111.11  | -5  |
| 1020 | 11111111..  | -4  |
| 1021 | 11111111.1  | -3  |
| 1022 | 111111111.  | -2  |
| 1023 | 1111111111  | -1  |
| 1024 | .....       | 0   |
| 1025 | .....1      | 1   |
| 1026 | .....1.     | 2   |
| 1027 | .....11     | 3   |
| 1028 | .....1..    | 4   |
| 1029 | .....1.1    | 5   |
| 1030 | .....11.    | 6   |
| 1031 | .....111    | 7   |
| 1032 | .....1...   | 8   |
| 1033 | .....1..1   | 9   |
| 1034 | .....1.1.   | 10  |
| 1035 | .....1.11   | 11  |
| 1036 | .....11..   | 12  |
| 1037 | .....11.1   | 13  |
| 1038 | .....111.   | 14  |
| 1039 | .....1111   | 15  |
| 1040 | .....1....  | 16  |
| 1041 | .....1...1  | 17  |
| 1042 | .....1..1.  | 18  |
| 1043 | .....1..11  | 19  |
| 1044 | .....1.1..  | 20  |
| 1045 | .....1.1.1  | 21  |
| 1046 | .....1.11.  | 22  |
| 1047 | .....1.111  | 23  |
| 1048 | .....11...  | 24  |
| 1049 | .....11..1  | 25  |